


Organic light emitting display having threshold voltage compensation mechanism and driving method thereof

Abstract

An organic light emitting display (OLED) includes a voltage adjustment unit for adjusting a preliminary control voltage according to a second reference voltage, a couple unit for coupling a change of the preliminary control voltage to adjust a control voltage, a driving unit for providing a driving current and a driving voltage according to the control voltage, a first reset unit for resetting the driving voltage according to a first reference voltage, a second reset unit for resetting the control voltage according to the driving voltage, an organic light emitting diode for generating output light according to the driving current, and an emission enable unit for providing a control of furnishing the driving current to the organic light emitting diode. Through the circuit operation of the reset units and the voltage adjustment unit, occurrences of image retention phenomenon and pixel brightness distortion on the OLED screen can be avoided.

Images (5)



a driving unit, electrically connected to the couple unit, for providing a driving current and a driving voltage according to the control voltage and a first power voltage;

a first reset unit, electrically connected to the driving unit and the second scan line, for resetting the driving voltage according to the second scan signal and a first reference voltage;

a second reset unit, electrically connected to the driving unit, the first reset unit and the first scan line, for resetting the control voltage according to the first scan signal and the driving voltage;

an organic light emitting diode for generating output light according to the driving current; and

an emission enable unit, electrically connected to the transmission line, the driving unit and the organic light emitting diode, for providing a control of furnishing the driving current to the organic light emitting diode according to the emission signal.

2. The organic light emitting display of claim 1, wherein the input unit comprises a first transistor, the first transistor having a first end electrically connected to the data line, a gate end electrically connected to the first scan line, and a second end electrically connected to the voltage adjustment unit and the couple unit.

3. The organic light emitting display of claim 2, wherein the first transistor comprises a thin film transistor or a field effect transistor.

4. The organic light emitting display of claim 1, wherein the driving unit comprises a second transistor, the second transistor having a first end for receiving the first power voltage, a gate end for receiving the control voltage, and a second end for outputting the driving current and the driving voltage.

5. The organic light emitting display of claim 4, wherein the second transistor comprises a thin film transistor or a field effect transistor.

6. The organic light emitting display of claim 1, wherein the couple unit comprises a capacitor electrically connected between the input unit and the driving unit.

7. The organic light emitting display of claim 1, wherein the first reset unit comprises a third transistor, the third transistor having a first end for receiving the first reference voltage, a gate end electrically connected to the second scan line, and a second end electrically connected to the driving unit, the second reset unit and the emission enable unit.

8. The organic light emitting display of claim 7, wherein the third transistor comprises a thin film transistor or a field effect transistor.

9. The organic light emitting display of claim 1, wherein the second reset unit comprises a fourth transistor, the fourth transistor having a first end electrically connected to the driving unit, the first reset unit and the emission enable unit, a gate end electrically connected to the first scan line, and a second end electrically connected to the couple unit and the driving unit.

10. The organic light emitting display of claim 9, wherein the fourth transistor comprises a thin film transistor or a field effect transistor.

11. The organic light emitting display of claim 1, wherein the voltage adjustment unit comprises a fifth transistor, the fifth transistor having a first end for receiving the second reference voltage, a gate end electrically connected to the transmission line, and a second end electrically connected to the input unit and the couple unit.

12. The organic light emitting display of claim 11, wherein the fifth transistor comprises a thin film transistor or a field effect transistor.

13. The organic light emitting display of claim 11, wherein the second reference voltage is the first power voltage.

14. The organic light emitting display of claim 1, wherein the emission enable unit comprises a sixth transistor, the sixth transistor having a first end electrically connected to the driving unit, the first reset unit and the second reset unit, a gate end electrically connected to the transmission line, and a second end electrically connected to the organic light emitting diode.

15. The organic light emitting display of claim 14, wherein the sixth transistor comprises a thin film transistor or a field effect transistor.

16. The organic light emitting display of claim 1, wherein the organic light emitting diode comprises an anode electrically connected to the emission enable unit and a cathode for receiving a second power voltage.

17. A driving method, comprising:

outputting a preliminary control voltage by an input unit according to a data signal and a first scan signal;

adjusting the preliminary control voltage by a voltage adjustment unit according to an emission signal and a second reference voltage;

adjusting a control voltage by a couple unit through coupling a change of the preliminary control voltage;

providing a driving current and a driving voltage by a driving unit according to the control voltage and a power voltage;

resetting the driving voltage by a first reset unit according to a second scan signal and a first reference voltage;

resetting the control voltage by a second reset unit according to the first scan signal and the driving voltage;

generating output light by an organic light emitting diode according to the driving current;

providing a control of furnishing the driving current to the organic light emitting diode by an emission enable unit according to the emission signal;

providing the first scan signal with a first level to the input unit and the second reset unit, providing the second scan signal with the first level to the first reset unit, providing the emission signal with a second level different from the first level for disabling a voltage adjusting operation of the voltage adjustment unit and disabling a current furnishing operation of the emission enable unit, and providing the data signal to the input unit during a first interval;

outputting the preliminary control voltage by the input unit according to the data signal and the first scan signal during the first interval;

resetting the driving voltage by the first reset unit according to the second scan signal and the first reference voltage during the first interval;

resetting the control voltage by the second reset unit according to the first scan signal and the driving voltage during the first interval;

switching the second scan signal from the first level to the second level for disabling a resetting operation of the first reset unit during a second interval following the first interval;

performing a threshold voltage compensation operation on the control voltage by the second reset unit and the driving unit according to the first scan signal and the power voltage during the second interval;

switching the first scan signal from the first level to the second level for disabling a resetting operation of the second reset unit and disabling an inputting operation of the input unit during a third interval following the second interval;

switching the emission signal from the second level to the first level during a fourth interval following the third interval;

adjusting the preliminary control voltage by the voltage adjustment unit according to the emission signal and the second reference voltage during the fourth interval;

adjusting the control voltage by the couple unit through coupling a change of the preliminary control voltage during the fourth interval;

providing the driving current by the driving unit according to the control voltage and the power voltage during the fourth interval;

furnishing the driving current to the organic light emitting diode by the emission enable unit according to the emission signal during the fourth interval; and

generating output light by the organic light emitting diode according to the driving current during the fourth interval.

18. The driving method of claim 17, wherein the second level is greater than the first level.

19. The driving method of claim 17, wherein the first level is greater than the second level.

20. The driving method of claim 17, wherein the second reference voltage is the power voltage.

21. The driving method of claim 17, wherein a length of the second interval is greater than a length of the first interval.

Description

BACKGROUND

1. Technical Field

The disclosure relates to an organic light emitting display, and more particularly, to an organic light emitting display having threshold voltage compensation mechanism and driving method thereof.

2. Description of the Related Art

Because flat panel displays (FPDs) have advantages of thin appearance, low power consumption, and low radiation, various kinds of flat panel displays have been developed and widely applied in a variety of electronic products such as computer monitors, mobile phones, personal digital assistants (PDAs), or flat panel televisions. Among them, active matrix organic light emitting displays (AMOLEDs) have gained more and more attention due to further advantages of self-emitting light source, high brightness, high emission rate, high contrast, fast reaction, wide viewing angle, and extensive range of working temperature.

FIG. 1 is a structure diagram schematically showing a prior-art active matrix organic light emitting display **100**. As shown in FIG. 1, the active matrix organic light emitting display **100** comprises a scan driving circuit **110**, a data driving circuit **120**, and a plurality of pixel units **150**. Each pixel unit **150** includes an input transistor **151**, a driving transistor **152**, a storage capacitor **153**, and an organic light emitting diode **154**. The scan driving circuit **110** and the data driving circuit **120** are utilized for providing plural scan signals and plural data signals respectively. Each pixel unit **150** is employed to control a driving current I_d based on corresponding scan and data signals, for controlling the light-emitting operation of one organic light emitting diode **154** disposed therein. However, in the operation of the active matrix organic light emitting display **100**, the threshold voltage of the driving transistor **152** has an effect on the driving current I_d , and therefore the threshold voltage variation of the driving transistors **152** in the pixel units **150** will cause pixel brightness distortion on the OLED screen, thereby degrading display quality. Besides, the voltage/current hysteresis effect of the driving transistor **152** is likely to incur image retention phenomenon. For instance, if two adjacent pixel units **150** are employed to illustrate a white-color grey level and a black-color grey level respectively in a first frame, and the control voltages V_{ctr} of the two pixel units **150** are both set to one and the same voltage corresponding to a middle grey level between the white-color and black-color grey levels in a second frame following the first frame, the driving currents I_d of the two pixel units **150** are then different due to the aforementioned hysteresis effect, which results in edge residual phenomenon.

SUMMARY

In accordance with an embodiment, an organic light emitting display having threshold voltage compensation mechanism is provided. The organic light emitting display comprises a data line for transmitting a data signal, a first scan line for transmitting a first scan signal, a second scan line for transmitting a second scan signal, a transmission line for transmitting an emission signal, an input unit, a voltage adjustment unit, a couple unit, a driving unit, a first reset unit, a second reset unit, an emission enable unit, and an organic light emitting diode.

The input unit, electrically connected to the data line and the first scan line, is utilized for outputting a preliminary control voltage according to the data signal and the first scan signal. The voltage adjustment unit, electrically connected to the transmission line and the input unit, is put in use for adjusting the preliminary control voltage according to the emission signal and a second reference voltage. The couple unit, electrically connected to the input unit and the voltage adjustment unit, is employed to adjust a control voltage through coupling a change of the preliminary control voltage. The driving unit, electrically connected to the couple unit, is used for providing a driving current and a driving voltage according to the control voltage and a power voltage. The first reset unit, electrically connected to the driving unit and the second scan line, is utilized for resetting the driving voltage according to the second scan signal and a first reference voltage. The second reset unit, electrically connected to the driving unit, the first reset unit and the first scan line, is utilized for resetting the control voltage according to the first scan signal and the driving voltage. The emission enable unit, electrically connected to the transmission line, the driving unit and the organic light emitting diode, is employed to provide a control of furnishing the driving current to the organic light emitting diode according to the emission signal. The organic light emitting diode, electrically connected to the emission enable unit, is utilized for generating output light according to the driving current.

In accordance with the embodiment, a driving method for use in the aforementioned organic light emitting display having threshold voltage compensation mechanism is further provided. The driving method comprises providing the first scan signal with a first level to the input unit and the second reset unit, providing the second scan signal with the first level to the first reset unit, providing the emission signal with a second level different from the first level for disabling a voltage adjusting operation of the voltage adjustment unit and disabling a current furnishing operation of the emission enable unit, and providing the data signal to the input unit during a first interval; the input unit outputting the preliminary control voltage according to the data signal and the first scan signal during the first interval; the first reset unit resetting the driving voltage according to the second scan signal and the first reference voltage during the first interval; the second reset unit resetting the control voltage according to the first scan signal and the driving voltage during the first interval; switching the second scan signal from the first level to the second level for disabling a resetting

operation of the first reset unit during a second interval following the first interval; the second reset unit and the driving unit performing a threshold voltage compensation operation on the control voltage according to the first scan signal and the power voltage during the second interval; switching the first scan signal from the first level to the second level for disabling a resetting operation of the second reset unit and disabling an inputting operation of the input unit during a third interval following the second interval; switching the emission signal from the second level to the first level during a fourth interval following the third interval; the voltage adjustment unit adjusting the preliminary control voltage according to the emission signal and the second reference voltage during the fourth interval; the couple unit adjusting the control voltage through coupling a change of the preliminary control voltage during the fourth interval; the driving unit providing the driving current according to the control voltage and the power voltage during the fourth interval; the emission enable unit furnishing the driving current to the organic light emitting diode according to the emission signal during the fourth interval; and the organic light emitting diode generating output light according to the driving current during the fourth interval.

These and other objectives of the present invention will no doubt become obvious to those of ordinary skill in the art after reading the following detailed description of the preferred embodiment that is illustrated in the various figures and drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a structure diagram schematically showing a prior-art active matrix organic light emitting display.

FIG. 2 is a structure diagram schematically showing an organic light emitting display in accordance with a first embodiment.

FIG. 3 is a schematic diagram showing related signal waveforms regarding the operation of the organic light emitting display illustrated in FIG. 2 based on a preferred driving method, having time along the abscissa.

FIG. 4 is a structure diagram schematically showing an organic light emitting display in accordance with a second embodiment.

DETAILED DESCRIPTION

Hereinafter, preferred embodiments of the present invention will be described in detail with reference to the accompanying drawings. Here, it is to be noted that the present invention is not limited thereto.

FIG. 2 is a structure diagram schematically showing an organic light emitting display **200** in accordance with a first embodiment. As shown in FIG. 2, the organic light emitting display **200** comprises a plurality of first scan lines **201**, a plurality of second scan lines **202**, a plurality of transmission lines **203**, a plurality of data lines **204**, and a plurality of pixel units **210**. The first scan lines **201** include a first scan line SL1_n for transmitting a first scan signal SS1_n, the second scan lines **202** include a second scan line SL2_n for transmitting a second scan signal SS2_n, the transmission lines **203** include a transmission line EL_n for transmitting an emission signal EM_n, the data lines **204** include a data line DL_m for transmitting a data signal SD_m, and the pixel units **210** include a pixel unit PXn_m for performing a light-emitting operation according to the first scan signal SS1_n, the second scan signal SS2_n, the emission signal EM_n and the data signal SD_m. The pixel unit PXn_m includes an input unit **215**, a voltage adjustment unit **220**, a couple unit **225**, a driving unit **230**, a first reset unit **235**, a second reset unit **240**, an emission enable unit **250** and an organic light emitting diode **260**.

The input unit **215**, electrically connected to the data line DL_m and the first scan line SL1_n, is utilized for outputting a preliminary control voltage Vctr_p according to the data signal SD_m and the first scan signal SS1_n. The voltage adjustment unit **220**, electrically connected to the transmission line EL_n and the input unit **215**, is put in use for adjusting the preliminary control voltage Vctr_p according to the emission signal EM_n and the first power voltage Vdd. The couple unit **225**, electrically connected to the input unit **215** and the voltage adjustment unit **220**, is employed to adjust a control voltage Vctr through coupling a change of the preliminary control voltage Vctr_p. The driving unit **230**, electrically connected to the couple unit **225**, is utilized for providing a driving current Idr and a driving voltage Vdr according to the control voltage Vctr and the first power voltage Vdd. The first reset unit **235**, electrically connected to the driving unit **230** and the second scan line SL2_n, is used for resetting the driving voltage Vdr according to the second scan signal SS2_n and a first reference voltage Vref1. The second reset unit **240**, electrically connected to the driving unit **230**, the first reset unit **235** and the first scan line SL1_n, is used for resetting the control voltage Vctr according to the first scan signal SS1_n and the driving voltage Vdr. The emission enable unit **250**, electrically connected to the transmission line EL_n, the driving unit **230** and the organic light emitting diode **260**, is utilized for providing a control of furnishing the driving current Idr to the organic light emitting diode **260** according to the emission signal EM_n. The organic light emitting diode **260** is employed to generate output light based on the driving current Idr.

In the embodiment shown in FIG. 2, the input unit **215** comprises a first transistor **216**, the couple unit **225** comprises a capacitor **226**, the driving unit **230** comprises a second transistor **231**, the first reset unit **235** comprises a third transistor **236**, the second reset unit **240** comprises a fourth transistor **241**, the voltage adjustment unit **220** comprises a fifth transistor **221**, the emission enable unit **250** comprises a sixth transistor **251**, and the organic light emitting diode **260** comprises an anode electrically connected to the sixth transistor **251** and a cathode for receiving a second power voltage Vss. The first transistor **216** through the sixth transistor **251** may each be a P-type thin film transistor (TFT) or a P-type field effect transistor (FET). In another embodiment, the first transistor **216** and the third transistor **236** to the sixth transistor **251** may each be an N-type thin film transistor or an N-type field effect transistor, and the second transistor **231** may be a P-type thin film transistor or a P-type field effect transistor.

The first transistor **216** comprises a first end electrically connected to the data line DL_m, a gate end electrically connected to the first scan line SL1_n, and a second end electrically connected to the fifth transistor **221** and the capacitor **226**. The second transistor **231** comprises a first end for receiving the first power voltage Vdd, a gate end for receiving the control voltage Vctr, and a second end for outputting the driving current Idr and the driving voltage Vdr. The capacitor **226** is electrically connected between the second end of the first transistor **216** and the gate end of the second transistor **231**. The third transistor **236** comprises a first end for receiving the first reference voltage Vref1, a gate end electrically connected to the second scan line SL2_n, and a second end electrically connected to the second end of the second transistor **231**. The fourth transistor **241** comprises a first end electrically connected to the second end of the second transistor **231**, a gate end electrically connected to the first scan line SL1_n, and a second end electrically connected to the gate end of the second transistor **231**. It is noted that the second transistor **231** functions as a diode when the fourth transistor **241** is turned on. The fifth transistor **221** comprises a first end for receiving the first power voltage Vdd, a gate end electrically connected to the transmission line EL_n, and a second end electrically connected to the second end of the first transistor **216**. The sixth transistor **251** comprises a first end electrically connected to the second end of the second transistor **231**, a gate end electrically connected to the transmission line EL_n, and a second end electrically connected to the anode of the organic light emitting diode **260**.

FIG. 3 is a schematic diagram showing related signal waveforms regarding the operation of the organic light emitting display **200** illustrated in FIG. 2 based on a preferred driving method, having time along the abscissa. The signal waveforms in FIG. 3, from top to bottom, are the first scan signal SS1_n, the second scan signal SS2_n, the emission signal EM_n, and the data signal SD_m. Referring to FIG. 3 in conjunction with FIG. 2, during a first interval T1, the first scan line SL1_n transmits the first scan signal SS1_n with a first level to the input unit **215** and the second reset unit **240**, the second scan line SL2_n transmits the second scan signal SS2_n with the first level to the first reset unit **235**, the transmission line EL_n transmits the emission signal EM_n with a second level different from the first level for disabling the voltage adjusting operation of the voltage adjustment unit **220** and disabling the current furnishing operation of the emission enable unit **250**, and the data line DL_m transmits the data signal SD_m to the input unit **215**. At this time, the input unit **215** outputs the preliminary control voltage Vctr_p according to the data signal SD_m and the first scan signal SS1_n, the first reset unit **235** resets the driving voltage Vdr according to the second scan signal SS2_n and the first reference voltage Vref1, and the

second reset unit **240** resets the control voltage Vctr according to the first scan signal SS1_n and the driving voltage Vdr. In view of that, the driving operation of the driving unit **230** is reset for avoiding an occurrence of image retention phenomenon.

During a second interval T2 following the first interval T1, the second scan signal SS2_n is switched from the first level to the second level for disabling the resetting operation of the first reset unit **235**. At this time, the second reset unit **240** and the driving unit **230** perform a threshold voltage compensation operation on the control voltage Vctr according to the first scan signal SS1_n and the first power voltage Vdd. After the threshold voltage compensation operation, the control voltage Vctr can be expressed as Formula (1) listed below.

$V_{ctr}=V_{dd}-|V_{th}|$ Formula (1)

In Formula (1), Vth represents the threshold voltage of the second transistor **231**. In one embodiment, the length of the second interval T2 is greater than the length of the first interval T1, such that the threshold voltage compensation operation may be fully performed.

During a third interval T3 following the second interval T2, the first scan signal SS1_n is switched from the first level to the second level for disabling the resetting operation of the second reset unit **240** and disabling the inputting operation of the input unit **215**. At this time, the preliminary control voltage Vctr_p is substantially identical to the voltage level Vdata of the data signal SD_m. During a fourth interval T4 following the third interval T3, the emission signal EM_n is switched from the second level to the first level. At this time, the voltage adjustment unit **220** adjusts the preliminary control voltage Vctr_p according to the emission signal EM_n and the first power voltage Vdd, and the couple unit **225** adjusts the control voltage Vctr through coupling the change of the preliminary control voltage Vctr_p. After the voltage adjustment operation, the control voltage Vctr can be expressed as Formula (2) listed below.

$V_{ctr}=2V_{dd}-|V_{th}|-V_{data}$ Formula (2)

Thereafter, the driving unit **230** provides the driving current Idr according to the control voltage Vctr and the first power voltage Vdd, and the driving current Idr provided can be expressed as Formula (3) listed below.

$I_{dr}=\frac{\beta}{2}(V_{data}-V_{dd})^2$ Formula (3)

In Formula (3), β represents a proportional constant. At this time, the emission enable unit **250** furnishes the driving current Idr to the organic light emitting diode **260** according to the emission signal EM_n, such that the organic light emitting diode **260** is able to generate output light according to the driving current Idr. It is noted that the driving current Idr is not affected by the threshold voltage Vth of the second transistor **231**, and therefore the threshold voltage variation regarding the transistors in the driving units of the pixel units **210** has no effect on pixel brightness, thereby avoiding an occurrence of pixel brightness distortion. That is, through the aforementioned reset and threshold voltage compensation operation, occurrences of image retention phenomenon and pixel brightness distortion on the OLED screen can be avoided, for achieving high image display quality.

It is noted that, in the preferred driving method described above, if the first transistor **216** and the third transistor **236** to the sixth transistor **251** are P-type thin film transistors or P-type field effect transistors, the second level is greater than the first level. Alternatively, if the first transistor **216** and the third transistor **236** to the sixth transistor **251** are N-type thin film transistors or N-type field effect transistors, the first level is greater than the second level.

FIG. 4 is a structure diagram schematically showing an organic light emitting display **300** in accordance with a second embodiment. As shown in FIG. 4, the organic light emitting display **300** is similar to the organic light emitting display **200** shown in FIG. 2, differing in that the pixel units **210** are replaced with a plurality of pixel units **310**, wherein the pixel unit PXn_m is replaced with a pixel unit PYn_m. Further, the pixel unit PYn_m is similar to the pixel unit PXn_m, differing primarily in that the voltage adjustment unit **220** is replaced with a voltage adjustment unit **320**. The voltage adjustment unit **320**, electrically connected to the transmission line EL_n, the input unit **215** and the couple unit **225**, is utilized for adjusting the preliminary control voltage Vctr_p according to the emission signal EM_n and a second reference voltage Vref2. In the embodiment shown in FIG. 4, the voltage adjustment unit **320** includes a fifth transistor **321** which may be a thin film transistor or a field effect transistor. The fifth transistor **321** comprises a first end for receiving the second reference voltage Vref2, a gate end electrically connected to the transmission line EL_n, and a second end electrically connected to the second end of the first transistor **216**.

In the display operation of the organic light emitting display **300**, after the voltage adjustment unit **320** adjusts the preliminary control voltage Vctr_p according to the emission signal EM_n and the second reference voltage Vref2, and the couple unit **225** adjusts the control voltage Vctr through coupling a change of the preliminary control voltage Vctr_p, the control voltage Vctr adjusted can be expressed as Formula (4) listed below.

$V_{ctr}=V_{dd}-|V_{th}|+V_{ref2}-V_{data}$ Formula (4)

Thereafter, the driving unit **230** provides the driving current Idr according to the control voltage Vctr of Formula (4) and the first power voltage Vdd, and the driving current Idr provided can be expressed as Formula (5) listed below.

$I_{dr}=\frac{\beta}{2}(V_{data}-V_{ref2})^2$ Formula (5)

As shown in Formula (5), neither the threshold voltage Vth of the second transistor **231** nor the first power voltage Vdd has an effect on the driving current Idr. For that reason, the voltage drop occurring to a conductive line for transmitting the first power voltage Vdd has no effect on the driving current Idr, and therefore an occurrence of pixel brightness distortion on the OLED screen due to the trace resistance of aforementioned conductive line can also be avoided, for improving image display quality of large-size display panels.

To sum up, with the aid of the reset and threshold voltage compensation mechanism according to the present invention described above, occurrences of image retention phenomenon and pixel brightness distortion can be avoided in the operation of the organic light emitting display, thereby achieving high image display quality on the OLED screen.

The present invention is by no means limited to the embodiments as described above by referring to the accompanying drawings, which may be modified and altered in a variety of different ways without departing from the scope of the present invention. Thus, it should be understood by those skilled in the art that various modifications, combinations, sub-combinations and alternations might occur depending on design requirements and other factors insofar as they are within the scope of the appended claims or the equivalents thereof.

Patent Citations (11)

Publication number	Priority date	Publication date	Assignee	Title
US7038392B2	2003-09-26	2006-05-02	International Business Machines Corporation	Active-matrix light emitting display and method for obtaining threshold voltage compensation for same
US20070024541A1 *	2005-08-01	2007-02-01	Ryu Do H	Organic light emitting display

US20070024543A1 *	2005-08-01	2007-02-01	Chung Bo Y	Data driving circuit, light emitting display using the same, and method of driving the light emitting display
US7317435B2 *	2003-09-08	2008-01-08	Tpo Displays Corp.	Pixel driving circuit and method for use in active matrix OLED with threshold voltage compensation
US7411571B2 *	2004-08-13	2008-08-12	Lg Display Co., Ltd.	Organic light emitting display
US7773054B2	2004-09-08	2010-08-10	Samsung Mobile Display Co., Ltd.	Organic light emitting diode display
US7843442B2 *	2005-03-19	2010-11-30	Samsung Mobile Display Co., Ltd.	Pixel and organic light emitting display using the pixel
Family To Family Citations				
KR100767377B1 *	2001-09-28	2007-10-17	삼성전자주식회사	Organic EL display panel and organic EL display device having same
US20070273618A1 *	2006-05-26	2007-11-29	Toppoly Optoelectronics Corp.	Pixels and display panels
CN101714333B *	2009-12-18	2012-05-23	友达光电股份有限公司	Organic Light Emitting Diode Display and Its Driving Circuit
CN101866619B *	2010-05-06	2013-01-23	友达光电股份有限公司	Pixel circuit of organic light emitting diode, display and driving method thereof

* Cited by examiner, † Cited by third party

Cited By (47)

Publication number	Priority date	Publication date	Assignee	Title
US20160086536A1 *	2014-09-24	2016-03-24	Au Optronics Corporation	Pixel Circuit with Organic Light Emitting Diode
US9357603B2	2014-09-01	2016-05-31	Au Optronics Corp.	Driving method of light emitting diodes
US9779659B2	2014-09-15	2017-10-03	Au Optronics Corp.	Pixel architecture and driving method thereof
US10056035B2	2015-12-07	2018-08-21	Au Optronics Corp.	Pixel circuit and driving method thereof
US10483482B2	2016-08-05	2019-11-19	Tianma Microelectronics Co., Ltd.	Display apparatus
US10923029B2	2018-04-19	2021-02-16	Au Optronics Corporation	Pixel circuit
US11289013B2	2019-10-23	2022-03-29	Au Optronics Corporation	Pixel circuit and display device having the same
Family To Family Citations				
CN102411893B *	2011-11-15	2013-11-13	四川虹视显示技术有限公司	Pixel driving circuit
KR102093664B1 *	2012-11-20	2020-04-16	삼성디스플레이 주식회사	Display device and driving method of the same
CN103198788A	2013-03-06	2013-07-10	京东方科技集团股份有限公司	Pixel circuit, organic electroluminescence display panel and display device
CN104575367B *	2013-10-15	2017-10-13	昆山工研院新型平板显示技术中心有限公司	A kind of image element circuit and its driving method and application
TWI498873B *	2013-12-04	2015-09-01	Au Optronics Corp	Organic light-emitting diode circuit and driving method thereof
KR102192475B1 *	2013-12-24	2020-12-17	엘지디스플레이 주식회사	Display device
CN105225636B *	2014-06-13	2017-05-31	京东方科技集团股份有限公司	Pixel-driving circuit, driving method, array base palte and display device
CN103996379B *	2014-06-16	2016-05-04	深圳市华星光电技术有限公司	The pixel-driving circuit of Organic Light Emitting Diode and image element driving method
CN104157240A	2014-07-22	2014-11-19	京东方科技集团股份有限公司	Pixel drive circuit, driving method, array substrate and display device
CN104167173B *	2014-08-01	2017-05-17	上海和辉光电有限公司	Pixel circuit for active organic light-emitting diode displayer
CN104216737A *	2014-08-15	2014-12-17	英业达科技有限公司	Reset system of microcontroller and reset method thereof
CN105575320B	2014-10-15	2018-01-26	昆山工研院新型平板显示技术中心有限公司	Image element circuit and its driving method and OLED
TWI533278B *	2014-10-31	2016-05-11	友達光電股份有限公司	Pixel structure and driving method thereof
TWI556210B *	2014-11-26	2016-11-01	鴻海精密工業股份有限公司	Pixel unit and driving method thereof

CN104575386B *	2015-01-26	2017-01-11	深圳市华星光电技术有限公司	AMOLED pixel driving circuit and method
CN104575392B	2015-02-02	2017-03-15	京东方科技集团股份有限公司	Pixel-driving circuit and its driving method
CN104658485B *	2015-03-24	2017-03-29	京东方科技集团股份有限公司	OLED drives compensation circuit and its driving method
CN105161051A *	2015-08-21	2015-12-16	京东方科技集团股份有限公司	Pixel circuit and driving method therefor, array substrate, display panel and display device
CN105185304B *	2015-09-09	2017-09-22	京东方科技集团股份有限公司	A kind of image element circuit, organic EL display panel and display device
TWI571854B *	2015-12-30	2017-02-21	友達光電股份有限公司	Light-emitting diode device control method
CN105448244B *	2016-01-04	2018-04-06	京东方科技集团股份有限公司	pixel compensation circuit and AMOLED display device
CN105679250B *	2016-04-06	2019-01-18	京东方科技集团股份有限公司	A kind of pixel circuit and its driving method, array substrate, display panel and display device
KR102561294B1 *	2016-07-01	2023-08-01	삼성디스플레이 주식회사	Pixel and stage circuit and organic light emitting display device having the pixel and the stage circuit
CN107710317A *	2016-09-27	2018-02-16	深圳市柔宇科技有限公司	A kind of OLED screen curtain guard method and protection system
CN106504702A *	2016-10-18	2017-03-15	深圳市华星光电技术有限公司	AMOLED pixel-driving circuits and driving method
CN106558287B *	2017-01-25	2019-05-07	上海天马有机发光显示技术有限公司	Organic light-emitting pixel driving circuit, driving method and organic light-emitting display panel
CN109064969A *	2017-06-01	2018-12-21	群创光电股份有限公司	Light emitting diode display panel and driving method thereof
CN107452332B *	2017-08-28	2019-11-01	京东方科技集团股份有限公司	A kind of pixel-driving circuit and its driving method and display device
CN107346654B *	2017-08-29	2023-11-28	京东方科技集团股份有限公司	Pixel circuit, driving method thereof and display device
TWI662530B *	2018-06-08	2019-06-11	友達光電股份有限公司	Light-emitting diode apparatus and controlling method thereof
CN109243370B *	2018-11-22	2020-07-03	京东方科技集团股份有限公司	Display panel and pixel driving circuit of light emitting diode
CN109584795A	2019-01-29	2019-04-05	京东方科技集团股份有限公司	Pixel-driving circuit, image element driving method and display device
US20220335880A1 *	2019-12-19	2022-10-20	Chongqing Konka Photoelectric Technology Research Institute Co., Ltd.	Electroluminescence Display, Pixel Compensating Circuit and Voltage Compensating Method Based on Pixel Compensating Circuit
CN210896559U *	2019-12-26	2020-06-30	云谷（固安）科技有限公司	Pixel circuit and display panel
CN111445858B	2020-04-20	2024-09-03	昆山国显光电有限公司	Pixel circuit, driving method thereof and display device
CN111754921B *	2020-07-24	2023-09-26	武汉华星光电半导体显示技术有限公司	Pixel circuit
TWI773293B *	2021-04-30	2022-08-01	友達光電股份有限公司	Driving circuit
TWI773294B *	2021-04-30	2022-08-01	友達光電股份有限公司	Driving circuit and driving method thereof
CN115171608B *	2022-09-08	2022-12-23	惠科股份有限公司	Driving circuit, driving method and display panel
TWI826107B *	2022-11-09	2023-12-11	友達光電股份有限公司	Pixel circuit and driving method thereof

* Cited by examiner, † Cited by third party, ‡ Family to family citation

Similar Documents

Publication	Publication Date	Title
US8502757B2	2013-08-06	Organic light emitting display having threshold voltage compensation mechanism and driving method thereof
US11069297B2	2021-07-20	Pixel circuit and method of driving the same, display panel, and display apparatus
US10255859B2	2019-04-09	Pixel compensating circuit and driving method thereof, array substrate and display device
US10380941B2	2019-08-13	OLED pixel circuit and display device thereof
US20210327347A1	2021-10-21	Pixel circuit and driving method thereof, and display panel

US11087688B2	2021-08-10	Compensating method for pixel circuit
US7274345B2	2007-09-25	Electro-optical device and driving device thereof
CN103218970B	2015-03-25	Active matrix organic light emitting diode (AMOLED) pixel unit, driving method and display device
US8917224B2	2014-12-23	Pixel unit circuit and OLED display apparatus
US9734763B2	2017-08-15	Pixel circuit, driving method and display apparatus
US10916188B2	2021-02-09	Pixel compensation circuit, compensation method, and display device
JP2021510207A	2021-04-15	Pixel circuit, drive method, electroluminescent display panel and display device
US9269298B2	2016-02-23	Pixel driving circuits, pixel driving methods, display panels and electronic devices
US9437142B2	2016-09-06	Pixel circuit and display apparatus
US20090121985A1	2009-05-14	Organic light emitting display and driving method thereof
US11195464B2	2021-12-07	Display device and driving method thereof
CN103137067A	2013-06-05	Organic light emitting diode display device and method of driving the same
US10553159B2	2020-02-04	Pixel circuit, display panel and display device
CN110544458B	2021-08-06	Pixel circuit, driving method thereof and display device
US11688338B2	2023-06-27	Display device, luminance compensation circuit thereof and luminance compensation method
US8044891B2	2011-10-25	Systems and methods for providing threshold voltage compensation of pixels
US10957257B2	2021-03-23	Pixel circuit, driving method thereof and display panel
CN103971634A	2014-08-06	Pixel unit driving circuit, display substrate, display panel and display device
US20070146253A1	2007-06-28	Method and device for brightness stabilization in AMOLED display
US20210407415A1	2021-12-30	Pixel driving circuit and display device

Priority And Related Applications

Applications Claiming Priority (3)

Application	Filing date	Title
TW100109157A	2011-03-17	
TW100109157A	2011-03-17	Organic light emitting display having threshold voltage compensation mechanism and driving method thereof
TW100109157	2011-03-17	

Legal Events

Date	Code	Title	Description
2011-11-15	AS	Assignment	Owner name: AU OPTRONICS CORP., TAIWAN Free format text: ASSIGNMENT OF ASSIGNORS INTEREST;ASSIGNORS:LIU, CHUN-YEN;YEH, CHIA-YUAN;TSENG, CHENG-CHIEH;SIGNING DATES FROM 201111104 TO 201111109;REEL/FRAME:027225/0614
2013-07-17	STCF	Information on status: patent grant	Free format text: PATENTED CASE
2017-01-26	FPAY	Fee payment	Year of fee payment: 4
2020-09-28	MAFP	Maintenance fee payment	Free format text: PAYMENT OF MAINTENANCE FEE, 8TH YEAR, LARGE ENTITY (ORIGINAL EVENT CODE: M1552); ENTITY STATUS OF PATENT OWNER: LARGE ENTITY Year of fee payment: 8
2023-05-25	AS	Assignment	Owner name: AUO CORPORATION, TAIWAN Free format text: CHANGE OF NAME;ASSIGNOR:AU OPTRONICS CORPORATION;REEL/FRAME:066378/0830

			Effective date: 20220718
2023-08-21	AS	Assignment	Owner name: OPTRONIC SCIENCES LLC, TEXAS Free format text: ASSIGNMENT OF ASSIGNORS INTEREST;ASSIGNOR:AUO CORPORATION;REEL/FRAME:064658/0572 Effective date: 20230802
2025-01-07	MAFP	Maintenance fee payment	Free format text: PAYMENT OF MAINTENANCE FEE, 12TH YEAR, LARGE ENTITY (ORIGINAL EVENT CODE: M1553); ENTITY STATUS OF PATENT OWNER: LARGE ENTITY Year of fee payment: 12
2025-05-06	IPR	Aia trial proceeding filed before the patent and appeal board: inter partes review	Free format text: TRIAL NO: IPR2025-00239 Opponent name: BOE TECHNOLOGY GROUP CO., LTD. Effective date: 20250307

Concepts

machine-extracted

[Download](#) [Filter table](#)

Name		Image	Sections	Count	Query match
method	title,claims,description	12	0.000		
mechanism	title,description	5	0.000		
change	claims,abstract,description	9	0.000		
coupling	claims,abstract,description	9	0.000		
coupling process	claims,abstract,description	9	0.000		
coupling reaction	claims,abstract,description	9	0.000		
biological transmission	claims,description	18	0.000		
field effect	claims,description	12	0.000		
thin film	claims,description	12	0.000		
capacitor	claims,description	5	0.000		
maintenance of location	abstract,description	5	0.000		
Show all concepts from the description section					

Data provided by IFI CLAIMS Patent Services