FILE HISTORY US 5,652,544

5,652,544 PATENT: INVENTORS: Fink, Dennis

Apparatus and method for programming an TITLE:


amplifier

NO:

APPLICATION US1995558344A

FILED: 16 NOV 1995 29 JUL 1997 ISSUED:

COMPILED: 24 OCT 2013



Class Subclass SSUE CLASSIFICATION				W. GATTER TAX PRINTED THAT THE PRINTED THE
	PATENT DATE	HOA	MUDIC	
SERIAL NUMBER 1 337157	PATENT DATE	PATENT NUMBER		
	B	M		1
serial number Filing da 08/337,157 11/09/9	1	207	2562	EXAMINER Wille
DENNIS FINK, WARWICK	, NY.	. ,		
CONTINUING DATA* VERIFIED	李泽水水水水水水水水水水水水水水水水			
Mrul frym				
FOREIGN/PCT APPLICATION VERIFIED	TIONS*******	,		
none from				
FOREIGN FILING LICENS		20	* SMALL EN	!!!!TY *****
5 USC 119 conditions met yes of		S. CLAIMS CLAIMS	FILING FEE	ATTORNEY'S DOCKET NO.
OSTRULENK FABER GERI 1180 AVENUE OF THE A NEW YORK NY 10036-6	8 & SOFFEN MERICAS	1 20	3 \$365.0	0 P21426
APPARATUS AND METHOD	FOR PROGRAMMING A		MMPat. & TM Offic	e — PTO-436L (rev. 10-78
PARTS OF APPLICATION FILED SEPARATELY			Annlicati	ons Examiner
NOTICE OF ALLOWANCE MAILED				LLOWED
at .		Tota	l Claims	Print Claim
ISSUE FEE	Assistant Examiner		DRA	WING
Amount Due Date Paid			ets Drwg. Figs. D	Drwg. Print Fig.
Label	PREPARED FOR IS	imary Examiner NUI	UE CCH MBER	
Area	WARNING: The information disclosion by the United States C		2, 181 and 368. Pos	ssession outside the U.S.

Form PTO-436A (Rev. 8/92)

08/337,157

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Transaction History

Date	Transaction Description
11-09-1994	Information Disclosure Statement (IDS) Filed
11-09-1994	Information Disclosure Statement (IDS) Filed
01-03-1995	Application Captured on Microfilm
04-12-1995	Case Docketed to Examiner in GAU
05-10-1995	Non-Final Rejection
05-17-1995	Mail Non-Final Rejection
11-16-1995	Request for Extension of Time - Granted
01-16-1996	Aband. for Failure to Respond to O. A.
01-23-1996	Mail Abandonment for Failure to Respond to Office Action
02-07-1996	Abandonment for Purposes of Filing an FWC - File Combined with Child
	Application

5,652,544

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Transaction History

Date	Transaction Description
11-16-1995	Preliminary Amendment
12-18-1995	Initial Exam Team nn
01-18-1996	Application Captured on Microfilm
02-07-1996	Case Docketed to Examiner in GAU
02-12-1996	Non-Final Rejection
02-14-1996	Mail Non-Final Rejection
07-19-1996	Information Disclosure Statement (IDS) Filed
07-19-1996	Information Disclosure Statement (IDS) Filed
07-19-1996	Response after Non-Final Action
07-19-1996	Request for Extension of Time - Granted
08-14-1996	Date Forwarded to Examiner
09-09-1996	Final Rejection
09-17-1996	Mail Final Rejection (PTOL - 326)
12-19-1996	Response after Final Action
12-30-1996	Date Forwarded to Examiner
01-07-1997	Mail Notice of Allowance
01-07-1997	Notice of Allowance Data Verification Completed
03-17-1997	Issue Fee Payment Verified
03-17-1997	Mailroom Date of Drawing(s)
04-17-1997	Drawing(s) Matched to Application
04-17-1997	Drawing(s) Received at Publications
04-21-1997	Drawing(s) Processing Completed
06-23-1997	Issue Notification Mailed
07-29-1997	Recordation of Patent Grant Mailed

APPROVED FOR LICENSE NITIAL 9160 19446 Date G Received D or O Mailed UP 2500 Date Entered or Counted **CONTENTS** 1. Application __ 15. __ ___ 16. __ _ 17. _ ___ 18. ____ 19. 23.

> 30. _ 31. _

(FRON DSC Audio Products Exhibit 1002 Page 6

APPROVED FOR LICENSE 08/558344 PATENT APPLICATION INITIALS 08558344 Date Entered or Counted Date Received **CONTENTS** or Mailed 1. Application papers. Formal Drawings (shts) set PTO Grant JUL 2 9 1997 19 20 21 23 24 25 26 27 28 29 30 3/

32 33 34

TENT NUMBER		l oi	RIGINAL CLASSIF	1			
	Soprati.	CLASS	SUBCL	ASS	The second second		
PLICATION SERIAL NUME	acp.	337		65			
~ 0.6	8,344		CROSS	S REFERENC			
PLICANT'S NAME (PLEAS		CLASS	1000	ONE SUBCLAS		-	
		330	129	120	30)	-	{
FINK	-	201	1000	1 20			\dashv
REISSUE, ORIGINAL PATI	ENT NUMBER	1	/ · · · ·				$\neg \dagger$
INTERNATION	IAL CLASSIFICATION	/					
D 3 F	L L OO						
101717	7700						
	//	ART UNIT	ASSISTANT EXAMINER (.:		
		2515	PRIMARY EXAMPLES B.		PRINT FULL NA	(ME)	
D 270 EV. 5-91)	l:	SSUE CLASS	IFICATERN PLIRE	UNIT 252		MENT OF COMM	MERCE OFFICE
Claim	Date		diloo, in-	Claim		e	
Final	6 80			Final			
100	769	_		51			
2 2 1				52			
W 4				54			
8 6				56			
3 7	1/2	-		57			
-		_		59 60			
1011	4			61 62			
12 13				63			
13 14 15 1	4		₹.	65			上
(19)	9		•	66			+
17	V	_		68			_
19 1				70			
13 21 22	4		o	71 72	+		
23	V	=		73		+++-	+
19 25	V			75 76			-
20 26 27 27	V // V //		*	77			1
29 28 29	V 7 V 3			78			
16 30 30			SYMBOLS Rejected Allowed	80		+	+
32		- (Thro	ugh numberal) Canceled Restricted	82			_
83		A	Non-elected Interference Appeal	84			1
35 36	V	0	Objected	85			
37				87 88			+
98 93 39	7			89			-
24 40				90			
75 41 70 42 17 43				92		+	+
17.43				94			#
45				95			+-
				96			
46 47 48				96 97 98			+

Staple Issue Slip Here

POSITION		ID N	10	DATE
CLASSIFIER		//		12-1-94
EXAMINER		34	()	12/14/84
TYPIST			503	12/16
VERIFIER		$ \hspace{.05cm} $	(XV)	MABILON
CORPS CORR.				\ \
SPEC. HAND				
FILE MAINT				
DRAFTING	Programme area area area			

INDEX OF CLAIMS

	-	-				<u> </u>	<u> </u>		15
- CI	aim	5	-		Dat	e		·	
Final	Original	2							
	0	91					L		
	D	1	r						100
	2				*				٠.
	3								
	4					_	_		_
-	5	1							74 .
	6			_	_	-	-		
	7	-	-				-		
10	8	1			-	-			-
1	9	+		-			-		777
15	10	+	-		<u> </u>		-	-	-
-	11	+	 	-	-	-		-	
-	12	-			<u></u>	-		-	
-	13	++		ļ			-		
-		+	-	-	-		-	-	
-	14	+							
}	15	H	<u> </u>			ļ			<u> </u>
-	16	1		<u></u>		-			
-	17	1							
	1/8	1	ļ						ļ
-	1,9	1						-	
<u> </u>	20	/				L			
-	21								
	22								
	23					-			
	24								٠.
	25								
	26		l						
	27								
	28								
	29								
	30								
	31								
	32						-		
	33								
	34				1				
	35								
	36		7 -					-	
	37.			., .			,.		70 E 3
	38		14 3	1		-	1. 1, 1		7
	39								
	40								
	41		 	_	_	 			
-	42	-	-	-	-		-	-	
-	43	-	-	-	-	-			
-	44	-	-		-			-	-
-	45	-	-				-		-
-	46	-	-	-	-	-		-	
-	47	-	-				-	-	
-	48	-	-			-	-		-
-		-	-		-	-			
-	49					-	-		
1	50			{·	1	(ĺ	ĺ	1

SYMBOLS	
·	Rejected
	Allowed
(Through numberal)	Canceled
	Restricted
	Non-elected
	Interference
	Appeal
)	Objected

	aiiii					<u> </u>			
Final	Onginal								
	51		_						
	52					-			-
	53			-		-			
1	54				_	-		-	
	55		<u> </u>	-		_		-	
	56		_	_	-	<u> </u>	_	-	-
-	57								
\vdash	58			-		-		-	
-	59	· · ·	-	-	-	-	-	-	
	60		-	-			-	-	-
-	61				-	-		-	
-	62		-	-		-			<u> </u>
-	63				-	-			
-	64			-	-		-		
-	65	-	-	-	-				<u> </u>
-			-		-	-	-		
-	66					-			
-	67		-						
-	68					-			
-	69			_	-				-
	70								
	71			_					
	72				_		L		
	73					L	<u></u>		
	74		Ĺ					<u></u>	
	75		Ŀ				<u> </u>		
	76			<u> </u>		L			
	77				Ŀ				
L	78			· .					
	79								
	80								
	81								
	82								
	.83.								
	84								
	85		`						
	86								
	87							·	
	88								
	89	7-7-1							
	90								
	91								
	92								
	93			_	<u> </u>				
	94			-	-				
\vdash	.95			-	-				
H	96			-	-				
-	97	-	-	-	-		-		
-	98			-	-	-			
-	99			-	-	-			
-	100				-	-		-	
	100		L	L	L	L			<u> </u>

POSITION	ID NO.	DATE
CLASSIFIER		
EXAMINER	264	12-26-95
TYPIST	184	1/16
VERIFIER	20	1/10/96
CORPS CORR.		,
SPEC. HAND		
FILE MAINT.		
DRAFTING		


INDEX OF CLAIMS


CI	aim				Date	 e			
	original mis	1/0/00	01	1000					
Final	gi	9_	6	W.					
ίĒ	Ĭ.	100	Cil	0	7		Ì		
	(4)		7	1					
14	\ <u>'</u>	4	1/	-					
12	2	4	14	4					
3577854	3		1/	1/					
10	4		1	1					
17	5	\top	1/	1					
0	6 7 8		1/	1					
2	7	+	1	1	_				
17	,	+	4					-	
14	-0	1	1	1			_		
	130	L							
9	(10)		V	0					
10	11		V	//					
1	12		レレレ	1					
1/2	13	+	-	1			-		
13	1.4	+	4	-					
12	14	4	1	12					
14	15	1	7777	1					
L	(16)		L						
	11 12 13 14 15 6 12 18 19 20 21 22 23 23 23 24 25 25 25 25 25 25 25 25 25 25 25 25 25	T							
	18	1	レレ						
-	10		-		_				
	13	4		_	-		-		
_	40	V	سراً ا						
13	21	,	<u></u>	1					
	22		レンレンシン						
	23		1,	i					
	24		1		_		-		
- (24 25 26 27 28		-	_					
190	25		<u>رن</u>	'					
10	26		رنا	1					
12/	27		V	17					
12	28		V	17					
15/16	20			-			-		
12	29 30		1	-		-	-		
110	30		1	//			-	-	-
L	An		1			L			
	32		レンレン				L		
	83		11						
	34		1	-					
-	35		W		-	<u> </u>	-		
-	35 36		1				-		
-	100		VV		-				ļ
	37		1V						
	38 39		V						
27	39			1					
216	40			1					
127	41			1		-	_		
1220	41			12	-				
20	42			1					
17	43.	WENNE .		1					
	44								
-	45	-			_	 	_		1-
-	46		-						
\vdash	40	-		-			-	-	
_	47		_						-
	48			1					
	49								
	50	-	\vdash						
1	1		i	1	1	1			

	SYMBOLS
= . +N	Rejected Allowed (Through numberal) Canceled Restricted Non-electe Interferen Appeal Objected

51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 75 76 77 78 79 80 81 82 83 84 85 86 86 87 88 89 90 91 92 93 94 95 96 97 98 99 99 99 100	-a	ına								
51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	Final	rig								
52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-					-	-			
53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 99	-			_						<u> </u>
54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100					-				-	
55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 80 81 82 83 84 85 86 87 88 89 90 91 91 92 93 94 95 96 97 98 99 100	-							-		
56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-					-			-	
57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-				-	-	-	-		
58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-			_						
59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 80 81 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-				-			-		-
60 61 62 63 64 65 66 66 67 68 68 69 70 71 72 73 74 75 75 76 77 78 78 79 80 81 81 82 83 84 85 86 86 88 89 99 90 91 91 92 93 94 95 96 97 98 99 99 1000	-				-	-				\vdash
61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-	_			-			├		
62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	┝			<u> </u>						
63 64 65 66 67 68 69 70 71 72 73 74 75 76 76 77 78 79 80 81 82 83 84 4 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	\vdash			-	-					
64 65 66 66 67 68 68 69 70 70 71 72 73 74 75 75 76 77 77 78 78 79 80 81 82 83 84 85 88 89 90 90 91 91 92 93 93 94 95 96 97 98 99 99 1000	-			-		-				-
65 66 67 68 69 70 71 72 73 74 75 76 77 78 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-					-		├		
66 67 68 68 69 70 70 71 71 72 73 74 75 76 77 77 78 8 79 80 80 81 82 83 84 85 86 86 87 88 88 89 90 90 91 92 92 93 93 94 4 95 95 96 97 98 99 99 1100	<u>-</u>				-				-	
67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	-	-		-	-		-	-	-	
68 69 70 70 71 72 73 74 72 73 74 75 76 76 77 78 78 79 80 81 82 83 84 85 85 86 87 88 89 90 90 91 91 92 93 94 4 95 96 97 98 99 90 100 100 100 100 100 100 100 100 1	-		-	-	+-	├	-	-		
69 70 71 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 91 92 93 94 95 96 97 98 99 100	-		-	-	-	-	-	-		
70 71 71 72 73 74 75 76 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 91 92 93 94 95 96 97 98 99 100	-	-	-	-	-		-	-		
71 72 73 74 75 75 76 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 91 92 93 94 95 96 97 98 99 100	-	1		-	-	-	-			
72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	\vdash					_		ļ		ļ
73 74 75 76 77 78 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_		ļ		<u> </u>	<u> </u>	_	ļ		<u> </u>
74 75 76 77 78 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	\vdash					ļ				
75 76 77 78 77 78 79 80 81 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	<u></u>		L	_	_	_			ļ	
76 77 78 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_		_	<u></u>	_	-				
77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_		_			<u> </u>	_		L	ļ
78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	<u></u>			_	_	_	_			
79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_				-	_				
80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_	+			ļ	<u> </u>	<u> </u>		<u> </u>	
81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_		ļ	_	_	_	ļ		L	
82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_	-	_	<u></u>			ļ.,	_		
83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100				_	_	_	_		_	
84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100	_	+					<u> </u>	<u> </u>	ļ	
85 86 87 88 89 90 91 92 93 94 95 96 97 98 99	L		<u> </u>	_	_	<u> </u>	<u> </u>		<u> </u>	
86 87 88 89 90 91 92 93 94 95 96 97 98 99		-			_	1	<u></u>			
87 88 89 90 91 92 93 94 95 96 97 98 99 100				L.			_			ļ
88 89 90 90 91 91 92 93 94 95 96 97 98 99 99 1000	_	86	_	<u>_</u>	<u> </u>				_	
89 90 91 92 93 94 95 96 97 98 99 100	L									
90 91 92 93 94 95 96 97 98 99 100		-	_	_			<u></u>		_	
91 92 93 94 95 96 97 98 99 100		89								
92 93 94 95 96 97 98 99 100		90]			ļ.				
93 94 95 96 97 98 99 100		91				Π.	T	Π		T
93 94 95 96 97 98 99 100		92				1		1		
94 95 96 97 98 99 100				Г	T	1	1			T
95 96 97 98 99 100						1	Г	1		T
96 97 98 99 100								Т	1	
97 98 99 100		-	1	П	1					T
98 99			1		\top	T	\top			T .
99							Т		1	
100	-	-	1-	 	_	1	_	1	1	
			1	 	-	1-	-		 	1
udia Draduata Ershihit 1002	L		-		<u> </u>					

(LEFT INSIDE) OSC Audio Products Exhibit 1002 Page 10





	SEAR	CHED)
Class	Sub.	Date	Exmr.
) .		
-			
		,	:
	;		:
	,		
		,	

INTER	FERENC	E SEARC	CHED
Class	Sub.	Date	Exmr.
	·		
	ļ		

SEARCH N	OTES	
	Date	Exmr.
	·	
,		
		-
	ļ	

(RIGHT OURSE) Audio Products Exhibit 1002 P

NOTICE ERRORS IN THE 5-APR-94 ISSUE ARE BEING CORRECTED AND CLEAN PATENTS FOR THIS ISSUE WILL BE AVAILABLE SHORTLY * * NOTICE: THE UPDATE FOR USPAT 3-MAY-94 ISSUE IS NOW COMPLETE* The USPTO production files are current through: 09 MAY 1995 for U.S. Patent Text Data. 09 MAY 1995 for U.S. Current Classification data. 09 MAY 1995 for U.S. Patent Image Data. * PLEASE USE 305-9000 FOR NEW TELEPHONE NUMBER * DISCLAIMER: Neither the United States Government, nor any agency thereof, nor any of their contractors, subcontractors or employees make any warranty, expressed or implied, including any warranty of marketability of fitness for a particular purpose; nor assumes any legal liability or responsibility for any party's use, or the results of such, of the data. Help Desk --> 703-305-9000 The Help Desk is staffed for APS support 7 days/week. Monday through Friday: 6:30am - 9:00pm Saturday, Sunday, Holidays: 8:30am - 5:00 pm The Help Desk staff at this number will handle all APS related questions. >>>>>> NEW SUNDAY HOURS !!! <<<<<< The APS is available: 6:30am - 9:00pm Monday through Friday 7:30am - 5:00pm Saturday, Sunday, Holidays APS is unavailable Thanksgiving Day, Christmas Day, and New Year's Day. FILE 'USPAT' ENTERED AT 13:24:06 ON 09 MAY 95 * * * * * * * * * * * * * * * * * * WELCOME TO THE => s amplifier and program? 153499 AMPLIFIER 177801 PROGRAM? 41137 AMPLIFIER AND PROGRAM? L1 => s l1 and microprocessor 57509 MICROPROCESSOR 12862 L1 AND MICROPROCESSOR 1.2

```
=> s 12 and housing
          353325 HOUSING
            3204 L2 AND HOUSING
 => s 13 amd 330/clas
MISSING OPERATOR 'L3 AMD'
=> s 13 and 330/clas
           19491 330/CLAS
                7 L3 AND 330/CLAS
 => d 14 -17
       7 ANSWERS ARE AVAILABLE. SPECIFIED ANSWER NUMBER EXCEEDS ANSWER SET
SIZE
ENTER ANSWER NUMBER OR RANGE (1):1-7
1. 5,268,601, Dec. 7, 1993, Logarithmic **amplifier** circuit with
temperature compensation; Peter A. Cossins, 327/350, 362; **330/289**
 [IMAGE AVAILABLE]
2. 4,945,316, Jul. 31, 1990, Voltage follower with pull-apart conector; Mark D. Sebald, et al., **330/110**; 327/91; **330/51** [IMAGE AVAILABLE]
03. 4,939,786, Jul. 3, 1990, Adaptive thermal protection for a power
 **amplifier** by remote sense; Kevin J. McCallum, et al., 455/67.1;
 **330/207P**; 455/115, 117, 127 [IMAGE AVAILABLE]
4,924,193, May 8, 1990, Volume control circuit for use in portable
telephone or the like; Akio Saito, et al., **330/284**; 379/58; 381/86
 [IMAGE AVAILABLE]
5. 4,747,296, May 31, 1988, Electronic tonometer with baseline nulling
system; Steven E. Feldon, et al., 73/4R, 753; 128/652; 324/130;
**330/9**; 364/558 [IMAGE AVAILABLE]
6. 4,628,397, Dec. 9, 1986, Protected Input, California (1986) **programmable** controller; Ronald E. Gareis, et al., 361/98; **programmable** controller; Ronald E. Gareis, et al., 361/98; **programmable** controller; Ronald E. Gareis, et al., 361/98;
   4,628,397, Dec. 9, 1986, Protected input/output circuitry for a
**330/207P**, **298**; 361/57, 97, 101, 103; 364/483 [IMAGE AVAILABLE]
4,223,272, Sep. 16, 1980, Four-terminal network of adjustable
transfer function; Karl H. Feistel, **330/51**, **65**, **107**, **148**
[IMAGE AVAILABLE]
=> s 12 and display
         163061 DISPLAY
           6904 L2 AND DISPLAY
=> s 15 and 330/clas
           19491 330/CLAS
              28 L5 AND 330/CLAS
=> d 16 1-28
1. 5,412,336, May 2, 1995, Self-biasing boot-strapped cascode
**amplifier**; Raymond L. Barrett, Jr., et al., 327/560, 545, 561;
**330/288**, **310** [IMAGE AVAILABLE]
2. 5,410,282, Apr. 25, 1995, Wide dynamic range **amplifier** with error correction; Ronald J. Larrick, et al., **330/149**, **59**, **151**,
**308**; 359/189 [IMAGE AVAILABLE]
3. 5,382,916, Jan. 17, 1995, Differential voltage follower; Ken R. King,
```

- et al., **330/253**, **257**, **301** [IMAGE AVAILABLE]
- 4. 5,373,249, Dec. 13, 1994, Complementary cascode push-pull **amplifier**; Raymond L. Barrett, Jr., et al., **330/264**, **267** [IMAGE AVAILABLE]
- 5,363,061, Nov. 8, 1994, Operational transconductance **amplifier** with matched outputs; Raymond L. Barrett, Jr., et al., **330/288**, **295**, **310** [IMAGE AVAILABLE]
- 6. 5,175,533, Dec. 29, 1992, TO-CMOS buffers, comparators, folded cascode amplifiers, systems and methods; William R. Krenik, 345/199; 326/71, 73; **330/253**, **258** [IMAGE AVAILABLE]
- 7. 5,155,614, Oct. 13, 1992, Low-power demodulating receiver with **amplifier** stages sharing the same bias current; Ralph H. Carmen, et al., 359/189; **330/59**; 359/154 [IMAGE AVAILABLE]
- 8. 8,107,140, Apr. 21, 1992, Anticipatory automatic gain control
 circuit; David M. Sherman, 327/331, 65, 72, 306, 309, 334; **330/85**,
 136, **279** [IMAGE AVAILABLE]
- 9. 5,049,834, Sep. 17, 1991, **Amplifier** having a constant-current bias circuit; Takafumi Kasai, **330/255**, **264**, **265**, **268** [IMAGE AVAILABLE]
- 10. 5,045,802, Sep. 3, 1991, Frequency characteristic setting circuitry for an **amplifier**; Takashi Miyake, et al., **330/2**; 327/44 [IMAGE AVAILABLE]
- 11. 5,027,656, Jul. 2, 1991, Fuel gauge damper circuit with a return to zero gauge circuit; James R. Garrison, 73/313, 113; 324/154R; **330/253** [IMAGE AVAILABLE]
- 12. 4,945,316, Jul. 31, 1990, Voltage follower with pull-apart conector; Mark D. Sebald, et al., **330/110**; 327/91; **330/51** [IMAGE AVAILABLE]
 - 13 4,904,954, Feb. 27, 1990, Ultrasonic signal **amplifier** circuit and system of gain control thereof; Kan Otake, et al., **330/281**, **141** [IMAGE AVAILABLE]
- 14. 4,882,547, Nov. 21, 1989, Linearizer control system; Allen Katz, **330/149**; 327/100 [IMAGE AVAILABLE]
- 15. 4,864,639, Sep. 5, 1989, Self-test device and method having an **amplifier** converted into an oscillator; Mark A. Dapore, et al., 455/226.4; 324/76.77, 76.79; **330/112**; 331/59; 455/67.7, 341 [IMAGE AVAILABLE]
- 16. 4,838,082, Jun. 13, 1989, Fuel gauge damper circuit; Blane K. McCoy, et /al., 73/313, 113; **330/253**; 377/21 [IMAGE AVAILABLE]
- 17. 4,803,476, Feb. 7, 1989, Video terminal for use in graphics and alphanumeric applications; Edward Knapton, et al., 345/189; **330/51** [IMAGE AVAILABLE]
- 18. 4,747,296, May 31, 1988, Electronic tonometer with baseline nulling system; Steven E. Feldon, et al., 73/4R, 753; 128/652; 324/130;

- **330/9**; 364/558 [IMAGE AVAILABLE]
- 19. 4,743,860, May 10, 1988, Audio power **amplifier**; James M. Dziagwa, **330/251**, **264** [IMAGE AVAILABLE]
- 10 4,628,397, Dec. 9, 1986, Protected input/output circuitry for a **programmable** controller; Ronald E. Gareis, et al., 361/98; **330/207P**, **298**; 361/57, 97, 101, 103; 364/483 [IMAGE AVAILABLE]
- 21. 4,627,098, Dec. 2, 1986, Automatic gain control for a remote control system having symmetrical send/receive signaling circuits; Arman V. Dolikian, et al., 455/70; **330/86**, **281**; 340/825.48; 379/58, 102; 455/244.1 [IMAGE AVAILABLE]
- 22. 4,598,253, Jul. 1, 1986, JFET ohmic differential **amplifier**; Kenneth A. Reindel, et al., **330/253**, **261** [IMAGE AVAILABLE]
- 23. 4,574,801, Mar. 11, 1986, Electrosurgical unit with regulated output; Michael R. Manes, 606/38; **330/59**; 331/186 [IMAGE AVAILABLE]
- 24. 4,550,276, Oct. 29, 1985, Buss structures for multiscene manual lighting consoles; Michael Callahan, et al., 315/312, 294, 299, 314, 316; **330/298**; 361/18 [IMAGE AVAILABLE]
- 25 4,525,789, Jun. 25, 1985, **Programmable** network tester with data formatter; Kyran B. Kemper, et al., 364/481; **330/278**; 364/550; 370/15; 371/26 [IMAGE AVAILABLE]
- 26 4,494,212, Jan. 15, 1985, Variable gain **amplifier**; William C. Muellner, 364/571.07; 327/306; **330/278** [IMAGE AVAILABLE]
- 4,484,295, Nov. 20, 1984, Control circuit and method for varying the output of a waveform generator to gradually or rapidly vary a control signal from an initial value to a desired value; James F. Bedard, et al., 364/607; 323/322, 350, 354; **330/282**; 363/16; 364/480 [IMAGE AVAILABLE]
- (28. 4,447,783, May 8, 1984, **Programmable** RF power regulator (stabilizer); Donald L. Quick, 323/275, 280; **330/207P**; 455/115, 117 [IMAGE AVAILABLE]
- => s 15 and 381/clas
 - 15172 381/CLAS
- 7 140 L5 AND 381/CLAS
- => s 13 and 381/clas
 - 15172 381/CLAS
- L8 34 L3 AND 381/CLAS
- => d 18 1-34
- 1. 5,402,501, Mar. 28, 1995, Automated audio mixer; Scott W. Silfvajt, et al., **381/119** [IMAGE AVAILABLE]
- 2. 5,384,854, Jan. 24, 1995, Co-processor controlled switching apparatus and method for dispatching console; Stephen R. Downs, et al., **381/81**; 379/203, 211, 267, 269; **381/123** [IMAGE AVAILABLE]
- 3. 5,326,349, Jul. 5, 1994, Artificial larynx; David R. Baraff, 623/9; **381/70**; 433/167 [IMAGE AVAILABLE]

- 4. 5,263,199, Nov. 16, 1993, Vehicle accessory having integrally contained radio receiver and recording means; Ronald P. Barnes, et al., 455/344; 360/137; 369/7; **381/86**; 455/345 [IMAGE AVAILABLE]
- 5. 5,175,759, Dec. 29, 1992, Communications device with movable element control interface; Michael P. Metroka, et al., 379/58, 61, 63; **381/43**; 455/89 [IMAGE AVAILABLE]
- 6. 5,095,798, Mar. 17, 1992, Electronic gaming device with pseudo-stereophonic sound generating capabilities; Saturo Okada, et al., 84/609, DIG.27; 273/85G, 435; 364/410; **381/17** [IMAGE AVAILABLE]
- 7. 5,083,312, Jan. 21, 1992, **Programmable** multichannel hearing aid with adaptive filter; James R. Newton, et al., **381/68.4**, **68**, **68.2** [IMAGE AVAILABLE]
- 8. 5,052,685, Oct. 1, 1991, Sound processor for video game; Danny D. Lowe, et al., 273/460, 85G, DIG.28; **381/17** [IMAGE AVAILABLE]
- 9. 5,051,799, Sep. 24, 1991, Digital output transducer; Jon D. Paul, et al., 375/242, 247; **381/168** [IMAGE AVAILABLE]
- 10. 5,029,477, Jul. 9, 1991, Integrity test for acoustic bearing defect detector; Joseph E. Bambara, 73/660; 246/169S; **381/56**, **58** [IMAGE AVAILABLE]
- 11. 4,970,659, Nov. 13, 1990, Learning aid or game having miniature electronic speech synthesis chip; Paul S. Breedlove, et al., 395/2.79; **381/51** [IMAGE AVAILABLE]
- 12. 4,947,432, Aug. 7, 1990, **Programmable** hearing aid; Jan Topholm, **381/68.2**, **68.4** [IMAGE AVAILABLE]
- 13. 4,926,159, May 15, 1990, Apparatus and method for the generation of directionally perceptible sound; Alan L. Bartlett, 340/384.6; 310/317, 321, 324; 340/384.71; **381/68.1**, **68.2** [IMAGE AVAILABLE]
- 14. 4,924,193, May 8, 1990, Volume control circuit for use in portable telephone or the like; Akio Saito, et al., 330/284; 379/58; **381/86** [IMAGE AVAILABLE]
- 15. 4,907,079, Mar. 6, 1990, System for monitoring and control of home entertainment electronic devices; Lester Turner, et al., 348/2; 379/92; **381/42**; 395/2; 455/2 [IMAGE AVAILABLE]
- 16. 4,905,289, Feb. 27, 1990, Apparatus for the digital storage of audio signals employing read only memories; Ljubomir Micic, et al., 395/2.78; 365/45; **381/51**; 395/2.67 [IMAGE AVAILABLE]
- 17. 4,897,630, Jan. 30, 1990, **Programmable** alarm system having proximity detection with vocal alarm and reporting features; Michael Nykerk, 340/426, 309.15, 429, 430, 460, 531, 539, 551, 561, 565, 692; 379/40; **381/51**; 395/2 [IMAGE AVAILABLE]
- 18. 4,791,672, Dec. 13, 1988, Wearable digital hearing aid and method for improving hearing ability; James A. Nunley, et al., **381/68.2**; 364/178, 572; **381/68**, **94** [IMAGE AVAILABLE]

- 19. 4,777,474, Oct. 11, 1988, Alarm system for the hearing impaired; Jack A. Clayton, 340/539, 407.1, 531, 573, 825.19; 379/38, 52; **381/23.1**, **42**, **60**, **68**; 395/2 [IMAGE AVAILABLE]
- 20. 4,776,016, Oct. 4, 1988, Voice control system; Per K. Hansen, **381/42**, **43**, **51**, **110**; 395/2 [IMAGE AVAILABLE]
- 21. 4,675,835, Jun. 23, 1987, Device for compensating reproduction errors in an electroacoustic transducer; Peter Pfleiderer, 364/571.06; 73/647; 364/571.02; **381/117**, **121** [IMAGE AVAILABLE]
- 22. 4,639,877, Jan. 27, 1987, Phrase-**programmable** digital speech system; William J. Raymond, et al., 395/2; **381/51** [IMAGE AVAILABLE]
- 23. 4,618,985, Oct: 21, 1986, Speech synthesizer; J. David Pfeiffer, **381/51**; 395/2.7, 2.77 [IMAGE AVAILABLE]
- 24. 4,605,080, Aug. 12, 1986, Speech recognition control system and method; Jerome H. Lemelson, 177/4, 25.13, 245; 346/9; 364/567; **381/43**; 395/2 [IMAGE AVAILABLE]
- 25. 4,589,133, May 13, 1986, Attenuation of sound waves; Malcolm A. Swinbanks, **381/71** [IMAGE AVAILABLE]
- 26. 4,560,978, Dec. 24, 1985, Communication system and method; Jerome H. Lemelson, 340/539, 531, 534, 692; **381/51**; 395/2 [IMAGE AVAILABLE]
- 27. 4,528,689, Jul. 9, 1985, Sound monitoring apparatus; Hart V. Katz, **381/67**; 128/715; 360/32; **381/34**, **38**, **56**; 395/2.16, 2.2, 2.79 [IMAGE AVAILABLE]
- 28. 4,525,793, Jun. 25, 1985; Voice-responsive mobile status unit; Bill L. Stackhouse, 395/2.79; **381/36** [IMAGE AVAILABLE]
- 29. 4,516,260, May 7, 1985, Electronic learning aid or game having synthesized speech; Paul S. Breedlove, et al., **381/51**; 434/169 [IMAGE AVAILABLE]
- 30. 4,455,551, Jun. 19, 1984, Synthetic speech communicating system and method; Jerome H. Lemelson, 340/539, 534, 692, 870.09; **381/51**; 395/2 [IMAGE AVAILABLE]
- 31. 4,380,185, Apr. 19, 1983, Talking metronome; Gayle Holcomb, 84/714; 29/523; 84/470R, 484, DIG.12; **381/51**; 968/820, 968, DIG.1 [IMAGE AVAILABLE]
- 32. 4,335,276, Jun. 15, 1982, Apparatus for non-invasive measurement and display nasalization in human speech; Glen L. Bull, et al., 395/2.85; **381/48**; 395/2.12, 2.19 [IMAGE AVAILABLE]
- 33. 4,326,710, Apr. 27, 1982, Talking electronic game; Jeffrey D. Breslow, et al., 273/460, 429; **381/51**; 395/2; 434/321 [IMAGE AVAILABLE]
- 34. 4,295,471, Oct. 20, 1981, Non-invasive vascular waveform transducer and apparatus; William J. Kaspari, 128/675; 73/774; 128/687, 715; **381/67** [IMAGE AVAILABLE]

```
=> file jpoabs
FILE 'JPOABS' ENTERED AT 13:32:15 ON 09 MAY 95
 * CURRENTLY, DATA IS LOADED THROUGH THE ABSTRACT PUBLICATION *
 => s 134
'L34' NOT FOUND
=> s 13
     77969 AMPLIFIER
     70729 PROGRAM?
     11534 MICROPROCESSOR
     46744 HOUSING
       0 L2 AND HOUSING
=> file uspat
U. S. PATENT TEXT FILE
```



United States Patent [19]

Fink

5,652,544

[11] Patent Number: Date of Patent:

Jul. 29, 1997

[54] APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

[75] Inventor: Dennis Fink, Warwick, N.Y.

[73] Assignee: Crest Audio Inc., Paramus, N.J.

[21] Appl. No.: 558,344

Nov. 16, 1995 [22] Filed:

Related U.S. Application Data

[63]	Continuation of Ser. No. 337	,157, Nov. 9, 1994, abandoned
		H03F 1/00
[52]	U.S. Cl	330/65 ; 330/129; 330/279 330/305; 381/88; 381/120

[58] Field of Search 330/2, 65, 66, 330/129, 279, 305; 381/87, 88, 105, 120,

[56] References Cited

U.S. PATENT DOCUMENTS

3,769,606	10/1973	Henegar 330/66
3,974,438	8/1976	Alves, III .
4,000,425	12/1976	Oiwa 330/66
4,079,334	3/1978	Hamilton 330/279
4,223,272	9/1980	Feistel 330/51
4,335,384	6/1982	Roos .
4,494,212	1/1985	Muellner 330/278 X
4,510,454	4/1985	Sherman .
4,547,740	10/1985	Nilsson .
4,556,841	12/1985	Carlson .
4,785,419	11/1988	Huffman .
4,868,516	9/1989	Henderson et al
4,924,192	5/1990	Sasaki
4,987,385	1/1991	Engelmann .
4,991,221	2/1991	Rush .
5,006,812	4/1991	Erickson .
5,015,969	5/1991	Barclay et al 330/2 X
5,045,802	9/1991	Miyake et al 330/2

5,059,923	10/1991	Petty et al
5,127,059	6/1992	Elion et al
5,153,528	10/1992	Back 330/279 X
5,285,500	2/1994	Mantz.
5,314,524	5/1994	Van Hulle et al
5,339,362	8/1994	Harris .

FOREIGN PATENT DOCUMENTS

54-10648 1/1979 Japan .

OTHER PUBLICATIONS


Co-pending Application No. 08/546,839 "Digital Signal Processor for Amplifier" filed Oct. 23, 1995.


Primary Examiner-James B. Mullins Attorney, Agent, or Firm-Ostrolenk, Faber. Gerb & Soffen.


ABSTRACT [57]


An apparatus and method for programming an amplifier includes an amplifier and a portable programmer that is removably connectable to the amplifier. The portable programmer includes a microprocessor, a keypad, and a display screen. The amplifier includes a programming input port, a signal processing circuit, a power amplifier and a control circuit. When the portable programmer is connected to the amplifier, information relating to parameter of various signal processing circuit elements can be read and modified through the programmer. The information input via the keypad and displayed on the display screen is transmitted from the programmer via the microprocessor to the signal processing control circuit to change signal processing functions and/or signal process function parameters of at least one of the signal processing circuit elements. As a result, processing of a signal transmitted through the amplifier is changed so that a sound produced by the signal can be modified. The signal processing circuit elements remain programmed when the programmer is removed and/or power is disconnected.

26 Claims, 1 Drawing Sheet









APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

This is a continuation of application Ser. No. 08/337,157, filed on Nov. 9, 1994 now abandoned.

BACKGROUND OF THE INVENTION

A. Field of the Invention

The present invention relates to an apparatus and method for programming a signal processing circuit of an amplifier. and more particularly, to an amplifier and a portable amplifier programmer capable of being removably connected to the amplifier to read and/or change various parameters of an amplifier signal processing circuit to thereby modify a signal output from the amplifier.

B. Description of the Prior Art

Amplifiers typically have an input port for being connected to an input device such as a musical instrument, a sound system, a public address system, etc. and for receiving audio signals from the input device. The amplifier is also connected to and drives a load or output device such as a loudspeaker. The amplifier includes a signal processing circuit for modifying and amplifying input signals and transmitting the modified signals as output signals to the 25 load.

The signal processing circuits include several resistive elements, capacitive elements, switching elements, operational amplifiers and other suitable devices which are selected to modify an input signal in a desired manner. The various elements of the signal processing circuit define a plurality of sound processing parameters such as a frequency and an amplitude of a cross-over function, relative levels and routing in a mixer, response times, ratios and thresholds in a compressor and frequency, gain and bandwidth in an equalizer.

Thus, when an input signal is transmitted through the various elements of the signal processing circuit, the resultant output signal will have a desired frequency and amplitude in accordance with a signal processing function set in the amplifier.

Users of amplifiers and sound systems often want to modify the signal processing parameters to alter a sound produced by the signals output from the amplifiers. However, it is difficult and time consuming to change the signal processing functions and function parameters in conventional amplifiers for reasons discussed below.

A conventional amplifier 10 is shown in FIG. 3. The amplifier is mounted within an amplifier housing 12 and 50 includes an input port 14 and an output port 16. A load such as a loudspeaker 20 is connected to the output port 16 so that the amplifier 10 drives the loudspeaker 20. A signal processing circuit 30 of the amplifier 10 is located within the amplifier housing 12. The signal processing circuit 30 includes a plurality of signal processing circuit elements which may include a plurality of switches 32, resistors 34 and capacitors 36 and other suitable signal modifying devices (not shown). The signal processing function and function parameters of the amplifier 10 are determined by 60 the plurality of signal processing circuit elements.

The signal processing function and parameters of the amplifier 10 can only be modified by setting one of the switches 32 or removing and/or replacing one or more of the resistors 34 and capacitors 36. However, the amplifier housing 12 must be opened and a signal processing circuit support (not shown) must be removed from the amplifier

2

housing 12 before any of the switches 32, resistors 34 or capacitors 36 can be modified or replaced. After modifying the circuit elements, the signal processing circuit support must be re-inserted into the amplifier housing 12 and the amplifier housing 12 must be closed.

The opening and closing of the amplifier housing 12 and removal of the signal processing circuit support is time consuming and does not allow a user to immediately sound check the results of the modification of the signal processing parameters. Instead, the signal processing circuit support must be reinserted in the amplifier housing 12 to be plugged back into the signal path before the amplifier 10 can be operated. In addition, the modification, removal and/or replacement of the various circuit elements to modify the parameters is a time consuming and difficult process because the signal processing control circuit elements are typically plug-in or solderable components. Also, because anyone is capable of opening the amplifier housing 12 and modifying the signal processing circuit 30, there is no way to prevent an unauthorized modification of the amplifier signal processing parameters.

The conventional amplifier 10 may include a controller 40 for receiving input command signals for modifying the signal processing parameters. The controller 40 can be connected to either manually controllable knobs 50 located on an amplifier control plate (not shown) or to a network 60 comprised of several interconnected amplifiers. If the controller 40 is connected to the knobs 50, any person can make unauthorized modifications to the signal processing parameters by simply turning one of the knobs 50. Also, to repeat the desired settings in a number amplifiers connected in a network, all of the knobs of each of the amplifiers must be individually and manually set to be at the exact same values. If the controller 40 is connected to the network 60, a computer or similar input device must be provided to input control signals through the network 60 to the controller 40 which increases the cost and complexity of the amplifier

Also, the presence of the controller 40 in the amplifier 10 introduces noise into the signal path caused by a digital/analog converter required for the controller 40. Further, the amplifier 10 must be provided with a battery backup or other suitable device to provide non-volatility required in digitally controlled systems.

SUMMARY OF THE INVENTION

A preferred embodiment of the present invention provides an amplifier and amplifier programmer capable of being removably connected to the amplifier to quickly and easily change signal processing functions and/or parameters of the amplifier without providing a conventional controller in the amplifier and without modifying signal processing circuit elements. The preferred embodiment of the present invention includes a portable amplifier programmer that is capable of receiving input information and transmitting the input information to an amplifier signal processing circuit to modify signal processing functions and/or parameters.

Another feature of the preferred embodiment relates to an amplifier having a data port for being connected to the portable amplifier programmer and receiving control signals from the programmer. The amplifier also includes a control circuit connected between the data port and a signal processing circuit for performing an interface function between the command signals input from the portable programmer and the signal processing circuit. The control circuit electrically isolates the control elements from the programmer

port. It also provides the optional connections required when programming elements over a network.

The control circuit may be preferably located outside of the signal path but connected to the signal processing circuit within the amplifier housing. The control circuit isolates the incoming command signals from the signal processing circuit elements to allow the parameters of the signal processing circuit elements to be modified as desired.

In an alternative embodiment, the control circuit and the signal processing circuit of the amplifier may be formed by a digital signal processor, described in U.S. patent application Ser. No. 08/546,839, which is a continuation application of U.S. patent application Ser. No. 08/336,481, entitled "DIGITAL SIGNAL PROCESSOR FOR AMPLIFIER," filed on Nov. 9, 1994, in the name of the same Applicant as in the present application, the disclosure of which is hereby incorporated by reference. If such a digital signal processor is provided in the amplifier, both signal processing functions and function parameters can be changed by inputting control information from the portable programmer to the amplifier.

The signal processing circuit elements are preferably provided with a memory or storage device for storing a set parameter value so that the set parameter value is not changed or deleted upon an off-on operation of the amplifier. For example, a conventional digitally programmable resistor can be used for one or more of the circuit elements. As is known, such a digitally programmable resistor stores a set resistance to provide a desired non-volatility. In addition, other known storage means such as an on board logic circuit or programmable gate array can be used to store the set parameter values.

The portable amplifier programmer according to the preferred embodiment includes a microprocessor, a keypad, a display screen and a connecting member for connecting the portable amplifier programmer to an amplifier to download signal processing parameters to the amplifier control circuit.

The keypad can be used to input either a desired modification to an output signal or a desired parameter value for a specific signal processing circuit element. An example of the input desired signal modification is a boost of 5 dB in the output signal is desired. The desired signal modification may be preferably displayed on the display screen. The microprocessor receives the desired signal modification and determines which control elements in the signal processing circuit must be modified and to what extent the performance characteristics of the selected control elements must be modified. The microprocessor then generates control signals for modifying the control elements and outputs the control signals to the amplifier to modify the signal processing parameters of the amplifier. More specifically, the control signals are transmitted from the microprocessor through the input port of the amplifier to the control circuit. The control circuit then sends the control signals to the signal processing circuit to modify the signal processing parameters.

When the keypad is used to input a parameter value for one or more of the signal processing circuit elements, the input desired parameter values are received by the microprocessor and converted to a command signal to be downloaded to the control circuit through the portable programmer.

Thus, the microprocessor is programmed to convert the input desired signal modification or desired parameter into a preferably digital command signal for changing the parameters of the amplifier signal processing circuit elements to 65 produce the desired signal modification or desired circuit element parameter value.

4

If a digital signal processor is provided in the amplifier, programs and program data for defining a plurality of signal processing functions and function parameters may be entered into the portable programmer and downloaded from the portable programmer to the amplifier.

The signal processing circuit may preferably have a memory or storage means for storing the information input from the portable amplifier programmer so that the portable amplifier programmer can be disconnected from the amplifier after inputting the desired signal modification or signal processing function and parameter program.

The programmer is also capable of reading the previously set parameters and functions stored in the signal processing circuit. A portable programmer user can select a reading mode wherein the programmer sends an inquiry signal to the signal processing circuit and outputs to the programmer a set value for each of the signal processing circuit elements. The parameter values for each of the circuit elements may be preferably displayed in numerical form on the programmer display.

The microprocessor in the portable programmer is capable of receiving the previously set parameters of the circuit elements and transfers these parameter values to the display screen to enable a portable programmer operator to decide if a given parameter value should be changed. The keypad can be used to scroll through the parameter values for each of the circuit elements so that each of the parameters for the circuit elements is displayed on the display screen. Because the portable amplifier programmer can read a parameter for each of the circuit elements, the programmer can prompt a portable programmer user to accept or change a parameter for each of the plurality of signal processing circuit elements.

The portable amplifier programmer may preferably include a memory or suitable storage device for storing a plurality of preset signal processing parameters and desired parameter values input through the keypad. The preset signal processing parameters may be stored in a plurality of different groups each of which contains a desired parameter for each of the signal processing circuit elements. For example, if a desired operation of a stereo sound system or public address system varies according to the time of day or the type of event being conducted, the signal processing parameters of an amplifier can be modified by selecting a preset group for that particular time of day or type of event. Thus, the user of the portable amplifier programmer only has to select a single group from a menu and the programmer will input that stored group to the control circuit of the amplifier.

The embodiments of the present invention provide several advantages. Because the programmer can be quickly and easily connected via a data port in the amplifier, there is no need to open the amplifier housing and remove a signal processing circuit support to change the circuit parameters. Also, there is no need to physically modify the circuit elements by setting a switch or removing and/or replacing a capacitor, resistor, operational amplifier or other suitable circuit element. In addition, the amplifier programmer allows changes in the signal processing circuitry of the amplifier to be made while the amplifier is in operation to thereby allow the results achieved by the modification of the signal processing parameters to be evaluated immediately.

Further, because the programmer contains a microprocessor, this eliminates the need for a microprocessor in the amplifier. Accordingly, the complexity and noise produced by a analog/digital converter required with the

5

microprocessor located within the amplifier is eliminated. Also, if a plurality of amplifiers are provided in a network, a substantial savings in amplifier cost is achieved because only one microprocessor is necessary and provided in the portable amplifier programmer instead of a microprocessor being provided in each amplifier.

An improved security feature is provided by the preferred embodiment of the invention. Because the parameters of the signal processing circuit elements cannot be changed without using the portable amplifier programmer, no unauthorized modification of the signal processing circuit elements is possible.

Further, non-volatility is achieved without battery backup, RAM or ROM so that when the control signals for the signal processing circuit elements in the amplifier are input from the programmer, the circuit elements remain programmed whether the power to the amplifier is on or off. In addition, the amplifier circuitry can be programmed by either the portable programmer or a standard computer which is connected to a network of amplifiers which allows for maximum flexibility.

Also, the programmer can easily download the same parameter settings via the network to a number of amplifiers ensuring identical setup. This eliminates the need to independently and manually change the knobs on each of a plurality of amplifiers.

Other features and advantages of the present invention will become apparent from the following description of the invention which refers to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic view showing a preferred embodiment of a portable amplifier programmer and amplifier of the present invention;

FIG. 2 is a schematic view of the control circuit of the programmer and amplifier shown in FIG. 1: and

FIG. 3 is a schematic view of a conventional amplifier circuit having a conventional signal processing parameter programmer. $_{40}$

DETAILED DESCRIPTION OF A PREFERRED EMBODIMENT

An amplifier 100 according to one aspect of a preferred embodiment of the invention is shown in FIG. 1. The amplifier includes an amplifier housing 110 which includes a control panel 112 having a plurality of control elements and ports. Input ports 114 for receiving connectors from one or more input devices are provided on the control panel 112. Also, a plurality of control knobs 116 for controlling gain, volume, an equalizer circuit, a level threshold, etc. are provided on the control panel 112 as is conventional, A plurality of output ports 118 and an AC power connector 119 are also provided on the control panel 112.

The control panel 112 also includes a programming port 120 for receiving a connector from the portable amplifier programmer described below. This programming port may also be connected to a data bus of a network of interconnected amplifiers. The network is connected to a computer or other similar device and control information can be input from the computer to the amplifier via the programming port 120.

A preferred embodiment of a portable amplifier programmer 200 is also shown in FIG. 1. The programmer 200 is 65 removably connectable to the amplifier 100 through a connector 300 which is connected to the programming port 120

6

of the amplifier 100 and an output port 210 of the portable programmer 200. The programmer 200 preferably includes a display screen 220 for displaying parameter values, desired signal modifications and other suitable information. The portable programmer 200 also includes an input device such as keypad 230 for entering parameter and signal modification information, signal processing function programs and program data.

The portable programmer 200 allows a user to modify parameters of amplifier circuit elements inside the amplifier, modify signal processing functions set by the signal processing circuit, read back previously set parameter values and store a group of input parameter values for future use as will be explained in greater detail below.

FIG. 2 shows an amplifier circuit 150 of the amplifier 100 shown in FIG. 1 and an operational circuit 250 of the portable programmer 200.

The amplifier circuit 150 of the amplifier 100 includes an input interface 152 connected to the input port 116. The input interface 152 provides audio signals from an input device (not shown) such as a musical instrument, public address system, sound system, etc. to a signal processing circuit 154 which is connected to a power amplifier 156. The amplifier circuit 150 is connected to a load 400 such as a loudspeaker.

The signal processing circuit **154** and power amplifier **156** are preferably located within the amplifier housing **110**. The amplifier housing **110** also has a control circuit **158** located therein. The control circuit is preferably connected to the programming port **120** and the signal processing circuit **154**.

The amplifier circuit 150 may be provided with a memory or storage device 159 for storing input command signals therein. As soon as the command signals have been input 5 from the programmer 200 through the connector 300 to the programming port 120, the programmer 200 can be disconnected from the amplifier 100 because the input commands are stored in the storage device 159. Alternatively, the storage device can be provided in the signal processing circuit 154.

Programming information is input from the portable programmer 200 through the connector 300 and the programming port 120 to the control circuit 158. This programming information may comprise signal processing function programs and program data for defining function parameters, parameter modification requests, new parameters, and other suitable control information.

The control circuit 158 preferably comprises a programmable microprocessor for performing an interface function between the command signals input from the portable programmer 200 and the signal processing circuit 154. In an alternative embodiment, the control circuit and the signal processing circuit of the amplifier may be formed by a digital signal processor, described in U.S. patent application Ser. No. 08/336.481 mentioned above. If such a digital signal processor is provided in the amplifier 100, both signal processing functions and function parameters can be changed by inputting control information from the portable programmer 200 to the amplifier 100.

The elements of the signal processing circuit 154 are preferably provided with a memory or storage device for storing a set parameter value so that the set parameter value is not changed or deleted upon an off-on operation of the amplifier. For example, a conventional digitally programmable resistor can be used for one or more of the circuit elements. As is known, such a digitally programmable resistor stores a set resistance to provide a desired non-

7

volatility. In addition, other known storage means such as an on board logic circuit or programmable gate array can be used to store the set parameter values.

In the programmer circuit 250, a microprocessor 252 is provided and has an output end connected to the connector 300. The keypad 230 and display 220 are connected to an input end of the microprocessor 252. A memory or storage device 254 may be provided in the portable programming circuit. The microprocessor 252 receives information from the keypad 230 and may store the input information in the memory 254. The memory may also store previously set parameter values, a menu and plurality of groups of parameter values, signal processing function programs and program data and other suitable control information. The microprocessor 252 also controls the display screen 220 to display parameter values and various read and input information.

The operation of the preferred embodiment of the invention will be described in the following paragraphs. At least one audio signal input device such as those described above is connected to the input port 114 of the amplifier 100. At least one output device or load such as a loudspeaker 400 is 20 connected to the output port 118.

A programming operation can be conducted while the amplifier is powered through the AC adapter 119 and functioning or while the amplifier 100 is not operating and receiving power. However, it is preferable to perform the amplifier programming operation while the amplifier 100 is receiving and outputting signals to hear the effects of parameter modifications.

The connector 300 is inserted into the programming port 120 of the amplifier 100 to connect the portable programmer 200 to the amplifier 100. A user can select a diagnostic mode by activating an appropriate key on the keypad 230. In the diagnostic mode, a parameter value for each of the signal processing circuit elements is read by the microprocessor 252 and displayed on the display 220 for operator verification. The microprocessor 252 converts the read data to a numerical value so that each parameter is displayed numerically.

The microprocessor 252 may preferably be programmed to request that a user confirm a read parameter value or change the parameter to a desired value by using an appropriate key on the keypad 230.

The information input via the keypad 230 is converted to control signals by the microprocessor 252. These control signals are preferably digital control signals for modifying the control elements of the signal processing circuit 154.

Once all of the signal processing function programs and/or function parameter values have been input to the programmer 200 and the microprocessor 252 has converted the input control information to control signals, the user can actuate a send key on the keypad 230 to transmit the new signal processing function and/or parameter information to input port 120 of the amplifier.

If a storage device 159 is provided, the input command signals are stored in 159 which allows the programmer 200 to be immediately removed after transmission of the command signals.

The control signals are transmitted from the input port 120 or storage device 159 to the control circuit 158. The control circuit 158 then sends control signals to the signal processing circuit to modify the performance characteristics of various control elements of the signal processing circuit 154 to achieve a desired modification of a signal processing function and/or function parameters.

As discussed above, the signal processing circuit elements are preferably provided with storage means for storing the

8

set parameters to maintain the set parameters despite power up and power down of the amplifier 100.

If the user dislikes the sound produced by the modification of the signal processing function and/or function parameters, the user can modify any one or all of the parameters of the signal processing circuit elements by either individually changing each parameter or selecting the previously set groups of parameter values which are stored in the memory 254. Preferably, the user can select a menu mode in which the programmer displays on the display screen 220 a menu of various groups of previously set parameters. The user can then select one of the groups by actuating an appropriate key on the keypad 230. Then, the stored group of parameter values is input to the amplifier as described above.

Although the present invention has been described in relation to particular embodiments thereof, many other variations and modifications and other uses will become apparent to those skilled in the art. It is preferred, therefore, that the present invention be limited not by the specific disclosure herein, but only by the appended claims.

What is claimed is:

1. An amplifier comprising:

an input port for receiving an input signal;

- a signal processing circuit comprising a digital signal processor capable of receiving at least one of a signal processing function and a signal processing function parameter, wherein the signal processing circuit receives the input signal from the input port and modifies the input signal;
- a power amplifier for amplifying the modified input signal received from the signal processing circuit and outputting an amplified signal to an output device;

an external programmer; and

- a programming signal input port for receiving at least one programming signal from the external programmer, the external programmer being removably connectable to the programming signal input port for modifying at least one of a signal processing function and a signal processing function parameter defined in said signal processing circuit.
- 2. The amplifier of claim 1, further comprising a control circuit for receiving the programming signal and converting the programming signal to a control signal to be sent to the signal processing circuit for modifying at least one of the signal processing function and the signal processing function parameter defined in said signal processing circuit.
- 3. The amplifier of claim 2, wherein the signal processing circuit comprises a storage device for storing at least one of the signal processing function and the signal processing function parameter produced by the control circuit.
- 4. The amplifier of claim 2, wherein the control circuit comprises a programmable microprocessor.
- 5. The amplifier of claim 1, further comprising a storage device for storing said at least one programming signal.
- 6. The amplifier of claim 1, further comprising an amplifier housing, the signal processing circuit and power amplifier being located in said amplifier housing.
- 7. The amplifier of claim 1, further comprising a control panel, wherein said programming signal input port is provided on the control panel.
- 8. The amplifier of claim 1, wherein the signal processing circuit further comprises a plurality of electronic components and a non-volatile storage means for storing a set performance characteristics.
- 9. The amplifier of claim 1, wherein the external programmer comprises:

10

- an input/output port for sending and receiving control information;
- a data input device for allowing input of programming information to the programmer; and
- a controller for receiving the input programming 5 information, generating programming signals from the input programming information and transmitting the programming signals through the input/output port to the amplifier for modifying at least one of a signal processing function and a signal processing function 10 parameter of the amplifier.
- 10. The amplifier of claim 9, wherein the external programmer further comprises a display screen for displaying input programming information and information read by the controller.
- 11. The amplifier of claim 9, wherein the external programmer further comprises a storage device for storing the input programming information and previously selected control signals.
- 12. The amplifier of claim 9, wherein the data input device comprises a keypad having a plurality of keys.
- 13. The amplifier of claim 9, wherein the controller comprises a microprocessor for receiving programming information from at least one of the input device and a control circuit of the amplifier.
- 14. The amplifier of claim 9, wherein the controller 25 comprises a connector for removably connecting the programmer to the amplifier.
- 15. The amplifier programmer of claim 9, wherein said programmer a standard computer.
- 16. The amplifier programmer of claim 9, wherein said programmer stores in groups said at least one of a signal processing function and a signal processing function parameter according to the time of day during which said amplifier is to operate.
- 17. The amplifier programmer of claim 9, wherein said programmer stores in groups said at least one of a signal processing function and a signal processing function parameter according to the type of event for which said amplifier is to operate.

- 18. The amplifier of claim 1, wherein said amplifier executes operation according to said at least one of a signal processing function and a signal processing function parameter after said external programmer is disconnected from said amplifier.
- 19. The amplifier of claim 1, wherein said external programmer is a standard computer.
- 20. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for a crossover function.
- 21. The amplifier of claim 1, wherein said digital signal processor receives and stores a combination of at least two signal processing functions.
- 22. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter which automatically vary the operation of said amplifier 20 according to the time of day.
 - 23. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for a volume control function.
 - 24. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for an equalizing function.
 - 25. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for a compression function.
 - 26. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for a level threshold function.

* * * * *

PATENT APPLICATION SERIAL NO. 08/337157

U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE FEE RECORD SHEET

000 AA 11/75/9% 033%7)5

a 201 - 365.00 CK

PTO-1556 (5/87)



OSTROLLINK, FABER, GERB & SOFFEN Attorneys at Law 1180 Avenue of the Americas New York, New York 10036-8403

(212) 382-0700

Telex 23 6925

Facsimile (212) 382-0888

Cable Ostrofaber NewYork

Express Mail #RB885681423US

Hon. Commissioner of Patents and Trademarks Washington, DC 20231

> OFGS File No. : Inventor

P/214-26 Dennis Fink

Title

Assignee

APPARATUS AND METHOD FOR PROGRAMMING

1180 Avenue of the Americas New York, New York 10036-8403 Telephone: (212) 382-0700

Joseph W. Keating Registration No.: 37,368 OSTROLENK, FABER, GERB & SOFFEN

AN AMPLIFIER Crest Audio Inc.

Enclosed herewith please find the following documents in the above-identified application for United States Letters Patent:

х	Abstract
20	Pages of Specification
20	
1	Sheets of Drawing Containing Figures 1 to 3. (Informal)
×	Declaration and Power of Attorney
_	Priority is Claimed under 35 U.S.C. §119:
Convent	ion Date for Appln. S.N
-	Certified Priority Application
×	Verified Statement Claiming Small Entity Status under 37 C.F.R. §1.27
×	Assignment
X	Return-Addressed Post Card
	neck No. 43786, which includes the fee of \$405, calculated as follows:
E	Basic Filing Fee:
I	Additional Filing Fees:
	Total Number of Claims in Excess of 20, times \$22:
	Number of Independent Claims in Excess of 3, times \$76
	One or More Multiple Dependent Claims: Total \$240
3	Total Filing Fees or
7	Total Filing Fee Reduced 50% for Small Entity:
7	Assignment Recording Fee: \$40 40.00
7	TOTAL Filing Fee and Assignment Recording Fee: <u>\$ 405.00</u>
In the	event the actual fee is greater than the payment submitted or is
inadver	tently not enclosed, or if any additional fee during the prosecution o
	ase is not paid, the Patent and Trademark Office is authorized to charg
	derpayment to Deposit Account No. 15-0700.
	EXPRESS MAIL CERTIFICATE Respectfully submitted,

I hereby certify that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee (mail label #RB85681423US) in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on November 9, 1994

DOROTHY JENKINS

Name of Person Mailing Correspondence

Signature November 9, 1994

Date of Signature

JRK:cfc

331,157 P/214-26

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

ABSTRACT OF THE DISCLOSURE

An apparatus and method for programming an amplifier includes an amplifier and a portable programmer that is removably connectable to the amplifier. The portable programmer includes a microprocessor, a keypad, and a display screen. The amplifier includes a programming input port, a signal processing circuit, a power amplifier and a control circuit. When the portable programmer is connected to the amplifier, information relating to parameter of various signal processing circuit elements can be read and modified through the programmer. The information input via the keypad and displayed on the display screen is transmitted from the programmer via the microprocessor to the signal processing control circuit to change signal processing functions and/or signal process function parameters of at least one of the signal processing circuit elements. As a result, processing of a signal transmitted through the amplifier is changed so that a sound produced by the signal can be modified. The signal processing circuit elements remain programmed when the programmer is removed and/or power is disconnected.

SPEC\95928

M

365 201 A

08/337157

P/214-26

mail

10

15

20

25

- 1 -

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

I. BACKGROUND OF THE INVENTION

A. Field Of the Invention

The present invention relates to an apparatus and method for programming a signal processing circuit of an amplifier, and more particularly, to an amplifier and a portable amplifier programmer capable of being removably connected to the amplifier to read and/or change various parameters of an amplifier signal processing circuit to thereby modify a signal output from the amplifier.

B. Description of the Prior Art

Amplifiers typically have an input port for being connected to an input device such as a musical instrument, a sound system, a public address system, etc. and for receiving audio signals from the input device. The amplifier is also connected to and drives a load or output device such as a loudspeaker. The amplifier includes a signal processing circuit for modifying and amplifying input signals and transmitting the modified signals as output signals to the load.

The signal processing circuits include several resistive elements, capacitive elements, switching elements, operational amplifiers and other suitable devices which are selected to modify an input signal in a desired manner. The various elements of the signal processing circuit define a plurality of sound processing parameters such as a frequency and an amplitude of a

SPEC\95928

- 2 -

cross-over function, relative levels and routing in a mixer, response times, ratios and thresholds in a compressor and frequency, gain and bandwidth in an equalizer.

Thus, when an input signal is transmitted through the various elements of the signal processing circuit, the resultant output signal will have a desired frequency and amplitude in accordance with a signal processing function set in the amplifier.

Users of amplifiers and sound systems often want to modify the signal processing parameters to alter a sound produced by the signals output from the amplifiers. However, it is difficult and time consuming to change the signal processing functions and function parameters in conventional amplifiers for reasons discussed below.

A conventional amplifier 10 is shown in Fig. 3. The amplifier is mounted within an amplifier housing 12 and includes an input port 14 and an output port 16. A load such as a loudspeaker 20 is connected to the output port 16 so that the amplifier 10 drives the loudspeaker 20. A signal processing circuit 30 of the amplifier 10 is located within the amplifier housing 12. The signal processing circuit 30 includes a plurality of signal processing circuit elements which may include a plurality of switches 32, resistors 34 and capacitors 36 and other suitable signal modifying devices (not shown). The signal processing function and function parameters of the amplifier 10 are determined by the plurality of signal processing circuit elements.

The signal processing function and parameters of the amplifier 10 can only be modified by setting one of the switches 32 or removing and/or replacing one or

SPEC\95928

5

10

15

20

25

- 3 -

more of the resistors 34 and capacitors 36. However, the amplifier housing 12 must be opened and a signal processing circuit support (not shown) must be removed from the amplifier housing 12 before any of the switches 32, resistors 34 or capacitors 36 can be modified or replaced. After modifying the circuit elements, the signal processing circuit support must be re-inserted into the amplifier housing 12 and the amplifier housing 12 must be closed.

The opening and closing of the amplifier housing 12 and removal of the signal processing circuit support is time consuming and does not allow a user to immediately sound check the results of the modification of the signal processing parameters. Instead, the signal processing circuit support must be reinserted in the amplifier housing 12 to be plugged back into the signal path before the amplifier 10 can be operated. In addition, the modification, removal and/or replacement of the various circuit elements to modify the parameters is a time consuming and difficult process because the signal processing control circuit elements are typically plug-in or solderable components. Also, because anyone is capable of opening the amplifier housing 12 and modifying the signal processing circuit 30, there is no way to prevent an unauthorized modification of the amplifier signal processing parameters.

The conventional amplifier 10 may include a controller 40 for receiving input command signals for modifying the signal processing parameters. The controller 40 can be connected to either manually controllable knobs 50 located on an amplifier control plate (not shown) or to a network 60 comprised of several interconnected amplifiers. If the controller 40 is

SPEC\95928

5

10

15

20

25

- A -

connected to the knobs 50, any person can make unauthorized modifications to the signal processing parameters by simply turning one of the knobs 50. Also, to repeat the desired settings in a number amplifiers connected in a network, all of the knobs of each of the amplifiers must be individually and manually set to be at the exact same values. If the controller 40 is connected to the network 60, a computer or similar input device must be provided to input control signals through the network 60 to the controller 40 which increases the cost and complexity of the amplifier system.

Also, the presence of the controller 40 in the amplifier 10 introduces noise into the signal path caused by a digital/analog converter required for the controller 40. Further, the amplifier 10 must be provided with a battery backup or other suitable device to provide non-volatility required in digitally controlled systems.

SUMMARY OF THE INVENTION

A preferred embodiment of the present invention provides an amplifier and amplifier programmer capable of being removably connected to the amplifier to quickly and easily change signal processing functions and/or parameters of the amplifier without providing a conventional controller in the amplifier and without modifying signal processing circuit elements. The preferred embodiment of the present invention includes a portable amplifier programmer that is capable of receiving input information and transmitting the input information to an amplifier signal processing circuit to modify signal processing functions and/or parameters.

SPEC\95928

30

10

15

20

Another feature of the preferred embodiment relates to an amplifier having a data port for being connected to the portable amplifier programmer and receiving control signals from the programmer.

The amplifier also includes a control circuit connected between the data port and a signal processing circuit for performing an interface function between the command signals input from the portable programmer and the signal processing circuit. The control circuit electrically isolates the control elements from the programmer port. It also provides the optional connections required when programming elements over a network.

The control circuit may be preferably located outside of the signal path but connected to the signal processing circuit within the amplifier housing. The control circuit isolates the incoming command signals from the signal processing circuit elements to allow the parameters of the signal processing circuit elements to be modified as desired.

In an alternative embodiment, the control circuit and the signal processing circuit of the amplifier may be formed by a digital signal processor, described in U.S. Patent Application No. 18 Action of Attorney printing of W.S. Patent Application No. 18 Action of Manual Application N

FOR AMPLIFIER," filed on November 9, 1994, in the name of the same Applicant as in the present application, the disclosure of which is hereby incorporated by reference. If such a digital signal processor is provided in the amplifier, both signal processing functions and function parameters can be changed by inputting control information from the portable programmer to the amplifier.

SPEC\95928

5

10

15

20

25

The signal processing circuit elements are preferably provided with a memory or storage device for storing a set parameter value so that the set parameter value is not changed or deleted upon an off-on operation of the amplifier. For example, a conventional digitally programmable resistor can be used for one or more of the circuit elements. As is known, such a digitally programmable resistor stores a set resistance to provide a desired non-volatility. In addition, other known storage means such as an on board logic circuit or programmable gate array can be used to store the set parameter values.

The portable amplifier programmer according to the preferred embodiment includes a microprocessor, a keypad, a display screen and a connecting member for connecting the portable amplifier programmer to an amplifier to download signal processing parameters to the amplifier control circuit.

The keypad can be used to input either a desired modification to an output signal or a desired parameter value for a specific signal processing circuit element. An example of the input desired signal modification is a boost of 5 dB in the output signal is desired. The desired signal modification may be preferably displayed on the display screen. The microprocessor receives the desired signal modification and determines which control elements in the signal processing circuit must be modified and to what extent the performance characteristics of the selected control elements must be modified. The microprocessor then generates control signals for modifying the control elements and outputs the control signals to the amplifier to modify the signal processing parameters of the

SPEC\95928

5

10

15

20

25

- 7 -

amplifier. More specifically, the control signals are transmitted from the microprocessor through the input port of the amplifier to the control circuit. The control circuit then sends the control signals to the signal processing circuit to modify the signal processing parameters.

When the keypad is used to input a parameter value for one or more of the signal processing circuit elements, the input desired parameter values are received by the microprocessor and converted to a command signal to be downloaded to the control circuit through the portable programmer.

Thus, the microprocessor is programmed to convert the input desired signal modification or desired parameter into a preferably digital command signal for changing the parameters of the amplifier signal processing circuit elements to produce the desired signal modification or desired circuit element parameter value.

If a digital signal processor is provided in the amplifier, programs and program data for defining a plurality of signal processing functions and function parameters may be entered into the portable programmer and downloaded from the portable programmer to the amplifier.

The signal processing circuit may preferably have a memory or storage means for storing the information input from the portable amplifier programmer so that the portable amplifier programmer can be disconnected from the amplifier after inputting the desired signal modification or signal processing function and parameter program.

The programmer is also capable of reading the previously set parameters and functions stored in the

SPEC\95928

30

5

10

15

20

signal processing circuit. A portable programmer user can select a reading mode wherein the programmer sends an inquiry signal to the signal processing circuit and outputs to the programmer a set value for each of the signal processing circuit elements. The parameter values for each of the circuit elements may be preferably displayed in numerical form on the programmer display.

The microprocessor in the portable programmer is capable of receiving the previously set parameters of the circuit elements and transfers these parameter values to the display screen to enable a portable programmer operator to decide if a given parameter value should be changed. The keypad can be used to scroll through the parameter values for each of the circuit elements so that each of the parameters for the circuit elements is displayed on the display screen. Because the portable amplifier programmer can read a parameter for each of the circuit elements, the programmer can prompt a portable programmer user to accept or change a parameter for each of the plurality of signal processing circuit elements.

The portable amplifier programmer may preferably include a memory or suitable storage device for storing a plurality of preset signal processing parameters and desired parameter values input through the keypad. The preset signal processing parameters may be stored in a plurality of different groups each of which contains a desired parameter for each of the signal processing circuit elements. For example, if a desired operation of a stereo sound system or public address system varies according to the time of day or the type of event being conducted, the signal processing parameters of an amplifier can be modified by selecting a preset group for that particular time of day or type of event.

SPEC\95928

5

10

15

20

25

- 9 -

Thus, the user of the portable amplifier programmer only has to select a single group from a menu and the programmer will input that stored group to the control circuit of the amplifier.

The embodiments of the present invention provide several advantages. Because the programmer can be quickly and easily connected via a data port in the amplifier, there is no need to open the amplifier housing and remove a signal processing circuit support to change the circuit parameters. Also, there is no need to physically modify the circuit elements by setting a switch or removing and/or replacing a capacitor, resistor, operational amplifier or other suitable circuit element. In addition, the amplifier programmer allows changes in the signal processing circuitry of the amplifier to be made while the amplifier is in operation to thereby allow the results achieved by the modification of the signal processing parameters to be evaluated immediately.

Further, because the programmer contains a microprocessor, this eliminates the need for a microprocessor in the amplifier. Accordingly, the complexity and noise produced by a analog/digital converter required with the microprocessor located within the amplifier is eliminated. Also, if a plurality of amplifiers are provided in a network, a substantial savings in amplifier cost is achieved because only one microprocessor is necessary and provided in the portable amplifier programmer instead of a microprocessor being provided in each amplifier.

An improved security feature is provided by the preferred embodiment of the invention. Because the parameters of the signal processing circuit elements

SPEC\95928

10

15

2.0

25

cannot be changed without using the portable amplifier programmer, no unauthorized modification of the signal processing circuit elements is possible.

Further, non-volatility is achieved without battery backup, RAM or ROM so that when the control signals for the signal processing circuit elements in the amplifier are input from the programmer, the circuit elements remain programmed whether the power to the amplifier is on or off. In addition, the amplifier circuitry can be programmed by either the portable programmer or a standard computer which is connected to a network of amplifiers which allows for maximum flexibility.

Also, the programmer can easily download the same parameter settings via the network to a number of amplifiers ensuring identical setup. This eliminates the need to independently and manually change the knobs on each of a plurality of amplifiers.

Other features and advantages of the present invention will become apparent from the following description of the invention which refers to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a schematic view showing a preferred embodiment of a portable amplifier programmer and amplifier of the present invention;

Figure 2 is a schematic view of the control circuit of the programmer and amplifier shown in Fig. 1: and

Figure 3 is a schematic view of a conventional amplifier circuit having a conventional signal processing parameter programmer.

SPEC\95928

10

15

20

- 11 -

DETAILED DESCRIPTION OF A PREFERRED EMBODIMENT

An amplifier 100 according to one aspect of a preferred embodiment of the invention is shown in Fig. 1. The amplifier includes an amplifier housing 110 which includes a control panel 112 having a plurality of control elements and ports. Input ports 114 for receiving connectors from one or more input devices are provided on the control panel 112. Also, a plurality of control knobs 116 for controlling gain, volume, an equalizer circuit, a level threshold, etc. are provided on the control panel 112 as is conventional. A plurality of output ports 118 and an AC power connector 119 are also provided on the control panel 112.

The control panel 112 also includes a programming port 120 for receiving a connector from the portable amplifier programmer described below. This programming port may also be connected to a data bus of a network of interconnected amplifiers. The network is connected to a computer or other similar device and control information can be input from the computer to the amplifier via the programming port 120.

A preferred embodiment of a portable amplifier programmer 200 is also shown in Fig. 1. The programmer 200 is removably connectable to the amplifier 100 through a connector 300 which is connected to the programming port 120 of the amplifier 100 and an output port 210 of the portable programmer 200. The programmer 200 preferably includes a display screen 220 for displaying parameter values, desired signal modifications and other suitable information. The portable programmer 200 also includes an input device such as keypad 230 for entering parameter and signal modification information, signal processing function programs and program data.

SPEC\95928

10

15

20

25

- 12 -

The portable programmer 200 allows a user to modify parameters of amplifier circuit elements inside the amplifier, modify signal processing functions set by the signal processing circuit, read back previously set parameter values and store a group of input parameter values for future use as will be explained in greater detail below.

Fig. 2 shows an amplifier circuit 150 of the amplifier 100 shown in Fig. 1 and an operational circuit 250 of the portable programmer 200.

The amplifier circuit 150 of the amplifier 100 includes an input interface 152 connected to the input port 116. The input interface 152 provides audio signals from an input device (not shown) such as a musical instrument, public address system, sound system, etc. to a signal processing circuit 154 which is connected to a power amplifier 156. The amplifier circuit 150 is connected to a load 400 such as a loudspeaker.

The signal processing circuit 154 and power amplifier 156 are preferably located within the amplifier housing 110. The amplifier housing 110 also has a control circuit 158 located therein. The control circuit is preferably connected to the programming port 120 and the signal processing circuit 154.

The amplifier circuit 150 may be provided with a memory or storage device 159 for storing input command signals therein. As soon as the command signals have been input from the programmer 200 through the connector 300 to the programming port 120, the programmer 200 can be disconnected from the amplifier 100 because the input commands are stored in the storage device 159. Alternatively, the storage device can be provided in the signal processing circuit 154.

SPEC\95928

10

15

20

25

Programming information is input from the portable programmer 200 through the connector 300 and the programming port 120 to the control circuit 158. This programming information may comprise signal processing function programs and program data for defining function parameters, parameter modification requests, new parameters, and other suitable control information.

The control circuit 158 preferably comprises a programmable microprocessor for performing an interface function between the command signals input from the portable programmer 200 and the signal processing circuit 154. In an alternative embodiment, the control circuit and the signal processing circuit of the amplifier may be formed by a digital signal processor, described in U.S. Patent Application No. If such a digital signal processor is provided in the amplifier 100, both signal processing functions and function parameters can be changed by inputting control information from the portable programmer 200 to the amplifier 100.

The elements of the signal processing circuit 154 are preferably provided with a memory or storage device for storing a set parameter value so that the set parameter value is not changed or deleted upon an off-on operation of the amplifier. For example, a conventional digitally programmable resistor can be used for one or more of the circuit elements. As is known, such a digitally programmable resistor stores a set resistance to provide a desired non-volatility. In addition, other known storage means such as an on board logic circuit or programmable gate array can be used to store the set parameter values.

13

20

25

30

10

15

SPEC\95928

In the programmer circuit 250, a microprocessor 252 is provided and has an output end connected to the connector 300. The keypad 230 and display 220 are connected to an input end of the microprocessor 252. A memory or storage device 254 may be provided in the portable programming circuit. The microprocessor 252 receives information from the keypad 230 and may store the input information in the memory 254. The memory may also store previously set parameter values, a menu and plurality of groups of parameter values, signal processing function programs and program data and other suitable control information. The microprocessor 252 also controls the display screen 220 to display parameter values and various read and input information.

The operation of the preferred embodiment of the invention will be described in the following paragraphs. At least one audio signal input device such as those described above is connected to the input port 114 of the amplifier 100. At least one output device or load such as a loudspeaker 400 is connected to the output port 118.

A programming operation can be conducted while the amplifier is powered through the AC adapter 119 and functioning or while the amplifier 100 is not operating and receiving power. However, it is preferable to perform the amplifier programming operation while the amplifier 100 is receiving and outputting signals to hear the effects of parameter modifications.

The connector 300 is inserted into the programming port 120 of the amplifier 100 to connect the portable programmer 200 to the amplifier 100. A user can select a diagnostic mode by activating an appropriate key on the keypad 230. In the diagnostic mode, a parameter

SPEC\95928

5

10

15

20

25

- 15 -

value for each of the signal processing circuit elements is read by the microprocessor 252 and displayed on the display 220 for operator verification. The microprocessor 252 converts the read data to a numerical value so that each parameter is displayed numerically.

The microprocessor 252 may preferably be programmed to request that a user confirm a read parameter value or change the parameter to a desired value by using an appropriate key on the keypad 230.

The information input via the keypad 230 is converted to control signals by the microprocessor 252. These control signals are preferably digital control signals for modifying the control elements of the signal processing circuit 154.

Once all of the signal processing function programs and/or function parameter values have been input to the programmer 200 and the microprocessor 252 has converted the input control information to control signals, the user can actuate a send key on the keypad 230 to transmit the new signal processing function and/or parameter information to input port 120 of the amplifier.

If a storage device 159 is provided, the input command signals are stored in 159 which allows the programmer 200 to be immediately removed after transmission of the command signals.

The control signals are transmitted from the input port 120 or storage device 159 to the control circuit 158. The control circuit 158 then sends control signals to the signal processing circuit to modify the performance characteristics of various control elements of the signal processing circuit 154 to achieve a desired modification of a signal processing function and/or function parameters.

SPEC\95928

5

10

15

20

25

As discussed above, the signal processing circuit elements are preferably provided with storage means for storing the set parameters to maintain the set parameters despite power up and power down of the amplifier 100.

If the user dislikes the sound produced by the modification of the signal processing function and/or function parameters, the user can modify any one or all of the parameters of the signal processing circuit elements by either individually changing each parameter or selecting the previously set groups of parameter values which are stored in the memory 254. Preferably, the user can select a menu mode in which the programmer displays on the display screen 220 a menu of various groups of previously set parameters. The user can then select one of the groups by actuating an appropriate key on the keypad 230. Then, the stored group of parameter values is input to the amplifier as described above.

Although the present invention has been described in relation to particular embodiments thereof, many other variations and modifications and other uses will become apparent to those skilled in the art. It is preferred, therefore, that the present invention be limited not by the specific disclosure herein, but only by the appended claims.

SPEC\95928

5

10

15

20

WHAT IS CLAIMED IS:

An amplifier comprising:

an input port for receiving an input signal;

a signal processing/circuit for receiving the input signal from the input port and modifying the input signal;

a power amplifier for amplifying the input signal received from the signal processing circuit and outputting a modified signal to an output device; and

a programming signal input device for receiving at least one programming signal from an external programmer removably connected to the programming signal input device for modifying at least one of a signal processing function and a signal processing function parameter defined in said signal processing circuit.

The amplifier of claim 1, further comprising a control circuit for receiving the programming signal and converting the programming signal to a control signal to be sent to the signal processing circuit for modifying at least one of the signal processing function and the signal processing function parameter defined in said signal processing circuit.

The amplifier of claim 1, further comprising a storage device for storing said at least one programming signal.

The amplifier of claim 1, further comprising an amplifier housing, the signal processing circuit and power amplifier being located in said amplifier housing.

SPEC\95928

10

The amplifier of claim 1, further comprising a control panel, wherein said programming signal input device is provided on the control panel.

The amplifier of claim 1, wherein the signal processing circuit comprises a plurality of electronic components each having a non-volatile storage means for storing a set/performance characteristic.

The amplifier of claim 2, wherein the signal processing circuit comprises a plurality of electronic components each having a storage device for storing at least one of the signal processing function and signal processing function parameter value set by the control circuit.

The amplifier of claim 1, wherein the control circuit comprises a programmable microprocessor.

The amplifier of claim 1, wherein the signal processing execuit comprises a digital signal processor.

10. An amplifier programmer comprising: an input/output port for sending and receiving control information;

an data input device for allowing input of programming information to the programmer; and

a controller for receiving the input programming information, generating control signals from the input programming information and transmitting the control signals through the input/output port to an amplifier for modifying at least one of a signal

10

5

SPEC\95928

processing function and signal processing function parameter of the amplifier.

1. The amplifier programmer of claim 10, further comprising a display screen for displaying input programming information and information read by the controller.

12. The amplifier programmer of claim 10, further comprising a storage device for storing the input programming information and previously selected control signals.

Mherein the data input device comprises a keypad having a plurality of keys.

14. The amplifier programmer of claim 10, wherein the controller comprises a microprocessor for receiving programming information from at least one of the input device and a control circuit of an amplifier.

The amplifier programmer of claim 10, wherein the controller comprises a connector for removably connecting the programmer to an amplifier.

16. A method of programming an amplifier comprising the steps of:

providing the amplifier with a programming signal input port;

connecting an external programmer to the programming signal input port;

SPEC\95928

inputting programming information to the external programmer; and

transmitting the programming information from the external programmer to the amplifier for changing at least one of a signal processing function and a signal processing function parameter defined in the amplifier.

1%. The method of claim 16, further comprising the step of displaying the control information on the external programmer.


18. The method of claim 16, further comprising the step of converting the input programming information to control signals for modifying performance characteristics of at least one signal processing control element contained in the amplifier.


19. The method of claim 16, wherein the step of inputting programming information comprises the step of inserting at least one of a signal processing function program, a signal processing function parameter data, a desired signal characteristic modification value and a desired signal processing function parameter value.


The method of claim 16, further comprising the step of storing the input control information.


SPEC\95928

5









P. 03	
	Ø 040

11/UM/W4 17:39 FAL 212 0881	NOV-09-94 WED	16:06			noitE[BUS	CTR
-----------------------------	---------------	-------	--	--	--------	-----	-----

FAX NO. 415 ' /3 8751

- 1		ted states of am				FGS FILE NO.
	COMBINED DECI	P/214-2	6			
	As a below pamed inventor, I hereby do my name; that I worldy believe that I am th (if plural inventors are named) of the subje	eclare that: my resident e original, first and sol et matter which is clai	cc, post office address a le inventor (if only one : med and for which a pa	and citizenship are as so name is listed below) or ment is sought on the inv	ned below next to a joint inventor remion autited:	,
	APPARATUS AND METHOD					
-	the specification of which				<u> </u>	
	is attached hereto.					
	uns filed on	as U	uited States parent applic	estion Serial Number		
	_		CT intensional patent of			and was
	amended on	et				
	I hereby state that I have reviewed and un- referred to above	lestend the consume of	f the above identified sp	صالاتتناهه, نعباسانيج ال	c claims, as amer	eled by any amendment
	I seknowledge the duty to disclose all infor	mation known to be m	enticial to palentability is	n accordance with Title	37. Code of Fed	ral Regulations, \$1.56.
	I heraby claim foreign priority benefits und and have also identified below any foreign claimed:	ler Title 35. United Su	ates Code \$119 of any f	orciem application(s) for	onless or invent	or's certificate listed below
	Prior Foreign Application(s)					
	COUNTRY	APPLICATION	ON NUMBER	DATE OF F	TLING Prop)	PRIORITY CLAIMED UNDER 35 U.S.C. 119
						YESNO
						YES NO
						YES NO
	CONTINUED ON PAGE 2					
2	I hereby appoint OSTROLENK, FABEI BAR, No. 18,510; Jerume M. Berliner - Re- Lieberstein - Reg. No. 22,400; Steven I. W Finder - Reg. No. 30,173; William O. Gro and revocation to prosecute this application					
	SEND CORRESPONDENCE TO:	STROLENK, FADE	R. GERB & SOFFEN E AMERICAS			
	.1 N	180 AVENUE OF TH YEW YORK, NEW YO	E AMERICAS DRK 10036-8403			
	E	RECT TELEPHONE	CALLS TO: (212) 382	2-0700		
	I hereby doclare that all statements mad true; and further that these statements were imprisonment, or both, under Section 1001 application of any patent issued thereon.	made with the knowle	edge that willful folse at	atements and the life on	made am minish	able by fine up
9	FOLL NAME OF SOLE OF FIRST INVENTOR		INVENTOR'S SIGNATU	KE		DATE
	Dennis FINK		Dec			9Nor 94.
	25 Foley Road, Warwi	-1- NOV 100	00 1510		COUNTRY OF C	TIZENSHIP
	POST OFFICE ADDRESS	CK, N1 109	30 NG	<u> </u>	U.S.A.	
	SAME AS ABOVE		_	,		
	FULL NAME OF SECOND MINT INVENTOR (IF	ANY)	INVENTOR'S SIGNATU	RE		DATE
	RESIDENCE		<u> </u>		COUNTRY OF C	TIVINGAUD
					COUNTRI OF C	, CONTRACT.
	POST OFFICE ADDRESS					
	Fuil. Name of Titted foint (nyentor (p &	מא	inventuk's signatui	RE		DATE
	RESIDENCI				COUNTRY OF C	TZENSIÐ
	POST OFFICE ADDRESS					

TRANU6116

NOV-09-94 WED 16:05 ANA HOTEL BUS CTR FAX NO. 415 743 8751 P. 02 OSTROLENK, FABER OSTROLENK, FABER	039
Serial or Patent No.: Filing or Issue Date: Applicant or Patentee: Dennis Fink	
For: Apparatus and method for programming an amplifier	
VERIFIED STATEMENT (DECLARATION) CLAIMING SMALL ENTITY STATUS 37 CPR 1.9(f) and 1.27(c) - SMALL BUSINESS CONCERN	
I hereby declare that with regard to the small business concern identified below I am [] the owner of the small business concern [x] an official of the small business concern empowered to act on behalf of sa NAME OF CONCERN:	
I hereby declare that the above identified small business concern qualifies as a small business concern as defined in 13 CFR 1.21.3-18, and reproduced in 37 CFR 1.9(d), for purposes of paying reduced fees under 35 USC \$41(a) and (b) in that the number of employees of the concern, including those of its affiliates, does not exceed 500 pers for purposes of this statement (1) the number of employees of the business concern is average over the previous fiscal year of the concern of the persons employed on a verage over the previous fiscal year of the concern of the pay periods of the fiscal and (2) concerns the affiliates of each other when either, directly or indirectly, on concern controls or has the power to control the other, or a third party or parties controls or has the power to control both.	ons. the
I hereby declare that rights under contract or law have been conveyed to and remain we the small business concern identified above with regard to the invention entitled APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER by inventor Dennis Fink description	
[x] U.S. Patent Application filed herewith [] U.S. Patent Application Serial No	
If the rights held by the above identified small business concern are not exclusive, individual, concern or organization having the rights to the invention is listed belo and no rights to the invention are held by any person, other than the inventor, who c not qualify as a small business concern under 37 CFR 1.9(c) or by any concern which w not qualify as a small business concern under 37 CFR 1.9(d) or a non-profit organizat under 37 CFR 1.9(e). *NOTE: Separate verified statements are required from each nam person, concern or organization having rights to the invention averring to their statemall entities. 37 CFR 1.27.	w* ould ould ion ed
NAME: ADDRESS: [] INDIVIDUAL [] SMALL BUSINESS CONCERN [] NON-PROFIT ORGANIZATIO NAME: ADDRESS:	N
[] INDIVIDUAL [] SMALL BUSINESS CONCERN [] NON-PROFIT ORGANIZATIO	N
I acknowledge the duty to file in this patent application or patent, notification of change of status resulting in loss of entitlement to small entity status prior to pay or at the time of paying, the earliest of the issue fee or any maintenance fee due af the date on which status as a small entity is no longer appropriate. 37 CFR 1.29(b).	ing,
I hereby declare that all statements made herein of my own knowledge are true and that statements made on information and belief are believed to be true; and further that to statements were made with the knowledge that willful false statements and the like so are punishable by fine or imprisonment, or both, under 18 USC \$1001, and that such with false statements may jeopardize the validity of the patent application, any patent is thereon, or any patent to which this verified statement is directed.	nese made llful
NAME OF PERSON SIGNING: John Lee, President ADDRESS OF DERSON SIGNING: Crest Audio, Inc., 100 Eisenhover Drive, Paramus, NJ 0765	2
SIGNATURE: Nov 9 1991	+

Application Assignment Record

According to the application transmittal letter, an assignment recording ownership was filed with this application; however, a copy of this record was not located in the original file history record obtained from the United States Patent and Trademark Office. Upon your request, we will attempt to obtain the assignment documents from the Assignment Recordation Branch of of the United States Patent and Trademark Office or from a related application case (if applicable). Please note that additional charges will apply for this service.

08/**337157**

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of

is FINK

Concurrently Herewith

Date: November 9, 1994

Group Art Unit: Unknown

Examiner: Unknown

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Commissioner of Patents and Trademarks

Washington, D.C. 20231

INFORMATION DISCLOSURE STATEMENT

Sir:

Pursuant to 37 C.F.R. 1.56, the attention of the Patent and Trademark Office is hereby directed to the references listed on the attached PTO-1449. One copy of each reference is attached. It is respectfully requested that the information be expressly considered during the prosecution of this application, and that the references be made of record therein and appear among the "References Cited" on any patent to issue therefrom.

This Information Disclosure Statement is being filed within three months of the U.S. filing date and before the mailing date of a first Office Action on the merits. No certification or fee is required.

EXPRESS MAIL CERTIFICATE

Respectfully submitted,

Joseph R. Keating Registration No.:

I hereby certify that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee (mail label #RB885681445US) in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on November 9, 1994:

DOROTHY JENKINS

Name of Person Mailing Correspondence

November 9, 1994

Date of Signature

JRK:cfc

37,368

OSTROLENK, FABER, GERB & SOFFEN 1180 Avenue of the Americas New York, New York 10036-8403 Telephone: (212) 382-0700

	(E)
Sheet	<u>l</u> of <u>l</u>

							Appli	cation		OFGS File No. P/214-26			
APPLICANT'S ART CITATION								Applicant Dennis FINK					
(Use several sheets if necessary)							Filing	Date Novem	ber 9, 1994	Group Art	^{Unit} Unkı	nown	
		(30	10	W Da	25.5		U.S.	PATENT	DOCUMENTS				
Examiner Initial			Docum	AD This	lumbei	7		Date	Name	Class	Sub- class		g Date ropriate
Kin	5	0	5	9	9	2	3	10/91	Petty et al.				
kim	.5	0	0	6	8	1	2	4/91	Erickson				
kis	4	8	6	8	5	1	6	9/89	Henderson et al.				
Ein	4	5	4	7	7	4	0	10/85	Nilsson				
Km	4	5	1	0	4	5	4	4/85	Sherman .				
Kilo	5	1	2	7	0	5	9	6/92	Elion et al.				,
Kin	K1/0 4 3 3 5 3 8					8	4	6/82	Roos				
Kin	4	7	8	5	4	1	9	11/88	Huffman				-
Psh	4	5	5	6	8	4	1	12/85	Carlson				
Sol	3	9	7	4.	4	3	8	<i>8</i> 176	Alves, III				
Ozh	5	3	3	9	3	6	2/	8/94	Harris				
Jish	5	2	8	5	5	0	0	2/94	Mantz				
Des M	4	9	8	7	3	8	5	1/91	Engelmann				
						F	ORE	GN PATE	NT DOCUMENTS				
												Tran	slation
			Docur	nent N	Numbe	r		Date	Country	Class	Sub- class	Yes	No
Koh	5	4	1	0	6	4	8	1/79	Japan				
			OT	HER	DO	CUM	IENT	TS (Including	Author, Title, Date, Pertine	nt Pages,	Etc.)		
Jorn Examiner	le	0.	W	fu	ller	iz	Dat	e Considered	5/9/95				
EXAMINE and not con	R: Init	ial if ci	itation o	onside y of thi	red, wh s form	ether o	r not ci	tation is in confo	rmance with MPEP § 609; Draw lapplicant.	ine through	citation if no	ot in confo	rmance



UNITED STATUS DEPARTMENT OF COMMERCE Patent and Trademark Office Address: COMMISSIONER OF PATENTS AND TRADEMARKS Washington, D.C. 20231

SERIAL NUMBER FILING DATE	FIRST NAMED INVENTOR		ATTORNEY DOCKET NO.
08/337,157 11/09	/94 FINK	D	P21426
	• •	MILL TE	(AMINER
	E5M1/0517	HOLLIN	J, J
OSTROLENK FABER GE		ART UNIT	PAPER NUMBER
1180 AVENUE OF THE NEW YORK NY 10036			3
MEM 100% N4 10030	-8403	2515	_
		DATE MAILED:	05/17/95
This is a communication from the examiner in COMMISSIONER OF PATENTS AND TRAD			
.L	_		
This application has been examined	Responsive to communication filed on		This action is made final.
	his action is set to expire month(s), nse will cause the application to become abandor		the date of this letter.
Part I THE FOLLOWING ATTACHMENT(S	a) ARE PART OF THIS ACTION:		
Notice of References Cited by Exa Notice of Art Cited by Applicant, P Information on How to Effect Draw	TO-1449. 4. Notic	ce of Informal Patent A	nt Drawing Review, PTO-948. pplication, PTO-152.
Part II SUMMARY OF ACTION			
1. Claims	-10		are pending in the application.
·		are w	vithdrawn from consideration.
3. Claims			are allowed.
4. Claims 1-2	٥		are rejected.
		·	are objected to.
6. Claims	a	e subject to restriction	or election requirement.
7. This application has been filed with in	nformal drawings under 37 C.F.R. 1.85 which are	acceptable for examin	ation purposes.
8. Formal drawings are required in resp	onse to this Office action.		
9. ☐ The corrected or substitute drawings are ☐ acceptable; ☐ not acceptable	have been received on e (see explanation or Notice of Draftsman's Paten		F.R. 1.84 these drawings O-948).
10. The proposed additional or substitute examiner; disapproved by the ex	e sheet(s) of drawings, filed on aminer (see explanation).	. has (have) been [approved by the
11. The proposed drawing correction, file	d, has been □approv	ved; 🗖 disapproved (s	see explanation).
	in for priority under 35 U.S.C. 119. The certified rial no; filed on		ceived not been received
	in condition for allowance except for formal matter x parte Quayle, 1935 C.D. 11; 453 O.G. 213.	ers, prosecution as to the	he merits is closed in
14. Other			

EXAMINER'S ACTION

Serial Number: 08/337,157

Art Unit: 2515

The disclosure is objected to because of the following informalities: The serial number of the application referenced on pages 5 and 13 should be submitted by the next response.

Claims 8 and 1-15 are rejected under 35 U.S.C. § 112, second paragraph, as being indefinite for failing to particularly point out and distinctly claim the subject matter which applicant regards as the invention.

In claim 8, "the control circuit" and in claim 10 "the amplifier" do not have antecedent basis.

In claims 14 and 15, the recitation "an amplifier" is effectively claiming the amplifier twice. See claim 10, last line.

The following is a quotation of the appropriate paragraphs of 35 U.S.C. \$ 102 that form the basis for the rejections under this section made in this Office action:

A person shall be entitled to a patent unless -- (b) the invention was patented or described in a printed publication in this or a foreign country or in public use or on sale in this country, more than one year prior to the date of application for patent in the United States.

(e) the invention was described in a patent granted on an application for patent by another filed in the United States before the invention thereof by the applicant for patent, or on an international application by another who has fulfilled the requirements of paragraphs (1), (2), and (4) of section 371(c) of this title before the invention thereof by the applicant for patent.

Claims 1-20 are rejected under 35 U.S.C. § $102\,(b)$ as being clearly anticipated by either Feistel or Barclay et al.

QSC Audio Products Exhibit 1002 Page 58

-2-

Serial Number: 08/337,157

Art Unit: 2515

Claims 1-20 are rejected under 35 U.S.C. § 102(e) as being clearly anticipated by Harris.

Claims 1-3 and 5-20 are rejected under 35 U.S.C. § 102(b) as being anticipated by either Miyake et al., Hamilton or Henegar. Note Fig. 1 of Miyake et al. and block 19 of Henegar. Note the digitally controlled amplifier of Fig. 1 of Hamilton.

Claims 10, 11, 13 and 15-20 are rejected under 35 U.S.C. \$ 102(b) as being anticipated by Oiwa. Note Figs 1-5.

Muellner, Sasaki and Back are cited of interest to further show relevant art.

Any inquiry concerning this communication or earlier communications from the examiner should be directed to Mr. James B. Mullins whose telephone number is $(703)\ 308-4912$.

Any inquiry of a general nature or relating to the status of this application should be directed to the Group receptionist whose telephone number is $(703)\ 308-0956$.

JBM


May 10, 1995

JAMES B. MULLINS EXAMINER

GROUP ART UNIT 252 2575

-3-

	AM PTO-892 U.S. DEPARTMENT OF COMMERCE EV. 2-92) PATENT AND TRADEMARK OFFICE PAPER NUMBER										3							
		NO	OTIO	CE (OF F	REF	ER	ENC	ES CITED		APPLICANT	5)			l	NUN	ABER	
FINK																		
										U.S. PATI	ENT DOCUM	ENTS			SI	JB.	FILING D	ATE IF
٠		_	00	ocu	MEN	TN	0.		DATE		NAME		С	LASS		ASS	APPROP	
	Α	3	7_	6	9	Ċ	0	6	10/73		EGAR		3	30	66 -			
	В	4	0	0	0	4	7	5	12476	014	IA		13	330	66			
	С	4	0	7	9	3	3	¥	3/78	HAM	1470N		4	330	ت	79		
	D	4	2	2	3	2	2	2	9/80	FETS				330	5	_/		
	E	4	Ų	9	4	2	-(2	1185	Mue	ELLNET	ı	3	330	2	788		
	F	4	9	2	4	}	9	2	5/40	SAS	4-K-1			30	2	79		
	G	5	0	l	5	9	6	9	5/91	BAR	CLAY E	ET AL.	12	330	_	2 X		
	н	5	0	u	5	ŏ	0	r	9/9/	MIYA	RE ES	M.	3	30	-	۷		
	1	5	1	5	3	5	2	8	12/92	BAC	<u>k /</u>		3	صر	27	9 X	_	
	J						_				. John Ramer							
	K																	
	FOREIGN PATENT DOCUMENTS																	
*			О	ocu	MEN	1T N	10.		DATE	cou	INTRY	NAME	:	CL	ASS	SUB- CLAS		S. PP. SPEC.
_	L																	
	М						_				·							
_	N						ļ											
_	0																	
	Р						_											
	Ω										-3-12							
_		V)Th	HEF	RE	FERENCE	S (Includin	g Author, T	itle, Date, P	ertine	ent Pa	ges, E	tc.)		
	R																	
_																		
	s				•				· · · · · · · · · · · · · · · · · · ·									
																	•	
	Т																	
	U										,							
									DAT	· E								
		NE			C		1			1/2								
_	A	77	70	چ	۷,5	' '						nished with	this of	ffice a	ction			
	* A copy of this reference is not being furnished with this office action. (See Manual of Patent Examining Procedure, section 707.05 (a).)																	



NOTICE OF DRAFTSPERSON'S PATENT DRAWING REVIEW

PTO Draftpersons review all originally filed drawings regardless of whether they are designated as formal or informal. Additionally, patent Examiners will review the drawings for compliance with the regulations. Direct telephone inquiries concerning this review to the Drawing Review Branch, 703-305-8404.

1/19/19/1	Mad:Gad forms 27 CED 1 94/h)/5\
The drawings filed (insert date), are	Modified forms. 37 CFR 1.84(h)(5)
A	Modified forms of construction must be shown in separate views.
B. Objected to by the Draftsperson under 37 CFR 1.84 or 1.152 as	Fig(s)
indicated below. The Examiner will require submission of new, corrected	
drawings when necessary. Corrected drawings must be submitted	8. ARRANGEMENT OF VIEWS. 37 CFR 1.84(i)
according to the instructions on the back of this Notice.	
according to the instructions on the back of this route.	View placed upon another view or within outline of another.
	Fig(s)
 DRAWINGS. 37 CFR 1.84(a): Acceptable categories of drawings: 	Words do not appear in a horizontal, left-to-right fashion when
Black ink. Color.	page is either upright or turned so that the top becomes the right
Not black solid lines Fig(s)	side, except for graphs. Fig(s)
Color drawings are not acceptable until petition is granted.	stuc, except for graphs. Tig(s)
Color drawings are not acceptable units peddon is granted.	
	9. SCALE, 37 CFR 1.84(k)
2. PHOTOGRAPHS. 37 CFR 1.84(b)	Scale not large enough to show mechanism without crowding
Photographs are not acceptable until petition is granted.	
	when drawing is reduced in size to two-thirds in reproduction.
3. GRAPHIC FORMS. 37 CFR 1.84 (d)	Fig(s)
	Indication such as "actual size" or "scale 1/2" i.ot permitted.
Chemical or mathematical formula not labeled as separate figure.	Fig(s)
Fig(s)	Elements of same view not in proportion to each other.
Group of waveforms not presented as a single figure, using	
common vertical axis with time extending along horizontal axis.	Fig(s)
Fig(s)	10 CHARACTER OF LINES NUMBERS & LETTERS 37 CER 1 847)
Individuals waveform not identified with a separate letter	10. CHARACTER OF LINES, NUMBERS, & LETTERS. 37 CFR 1.84(I)
designation adjacent to the vertical axis. Fig(s)	Lines, numbers & letters not uniformly thick and well defined,
· · · · · · · · · · · · · · · · · · ·	clean, durable, and black (except for color drawings).
4. TYPE OF PAPER. 37 CFR 1.84(e)	$Fig(s)$ $\frac{1}{2}$
The same flevible strong white amount nonchine and devoble	
Paper not flexible, strong, white, smooth, nonshiny, and durable.	
Sheet(s)	11. SHADING, 37 CFR 1.84(m)
Erasures, alterations, overwritings, interlineations, cracks, creases,	Shading used for other than shape of spherical, cylindrical, and
and folds not allowed. Sheet(s)	conical elements of an object, or for flat parts.
and long not anonce. Greeks)	
and the same of th	Fig(s)
SIZE OF PAPER. 37 CFR 1.84(f): Acceptable paper sizes:	Solid black shading areas not permitted. Fig(s)
21.6 cm. by 35.6 cm. (8 1/2 by 14 inches)	
21.6 cm. by 33.1 cm. (8 1/2 by 13 inches)	
21.6 cm. by 27.9 cm. (8 1/2 by 11 inches)	NUMBERS, LETTERS, & REFERENCE CHARACTERS. 37 CFR
	1.84(p)
21.0 cm. by 29.7 cm. (D1N size A4)	Numbers and reference characters not plain and legible. 37 CFR
All drawing sheets not the same size. Sheet(s)	1.84(p)(1) Fig(s) 3
Drawing sheet not an acceptable size. Sheet(s)	1.64(p)(1) Fig(s)
	Numbers and reference characters used in conjuction with
A A A D COMP OF COMP ! CA/-). A secondollo superiori	brackets, inverted commas, or enclosed within outlines. 37 CFR
 MARGINS, 37 CFR i.84(g): Acceptable margins: 	1.84(p)(1) Fig(s)
Paper size	Numbers and reference characters not oriented in same direction as
21.6 cm × 35.6 cm 21.6 cm × 33.1 cm 21 cm × 27.9 cm 21 cm × 29.7 cm	
(8 1/2 X 14 inches) (8 1/2 X 13 inches) (8 1/2 X 11 inches) (DIN Size A4)	the view. 37 CFR 1.84(p)(1) Fig(s)
T 5.1 cm. (2") 2.5 cm. (1") 2.5 cm. (1") 2.5 cm.	English alphabet not used. 37 CFR 1.84(p)(2)
	Fig(s)
	Numbers, letters, and reference characters do not measure at least
	.32 cm. (1/8 inch) in height. 37 CFR(p)(3)
Margins do not conform to chart above.	Fig(s)
Shrei(s)	
Top (T) Left (L) Right (R) Bottom (B)	13. LEAD LINES. 37 CFR 1.84(q)
0 *	
7. VIEWS, 37 CFR 1.84(h)	Lead lines cross each other. Fig(s)
REMINDER: Specification may require revision to correspond to	Lead lines missing. Fig(s)
drawing changes.	Lead lines not as short as possible. Fig(s)
All views not grouped together. Fig(s)	
Views connected by projection lines. Fig(s)	 NUMBERING OF SHEETS OF DRAWINGS. 37 CFR 1.84(t)
Views contain center lines. Fig(s)	Number appears in top margin. Fig(s)
Partial views. 37 CFR 1.84(h)(2)	Number not larger than reference characters.
Separate sheets not linked edge to edge.	Fig(s)
,	Chaste not numbered consequitively, and in Ambie numbered
Fig(s)	Sheets not numbered consecutively, and in Arabic numerals,
View and enlarged view not labeled separately.	beginning with number 1. Sheet(s)
Fig(s)	*
Long view relationship between different parts not clear and	LC ATTROPER OF VIEWS 27 CER 1 946.5
unambiguous. 37 CFR 1.84(h)(2)(ii)	15. NUMBER OF VIEWS. 37 CFR 1.84(u)
	Views not numbered consecutively, and in Arabic numerals,
Fig(s)	beginning with number 1. Fig(s)
Sectional views. 37 CFR 1.84(h)(3)	View numbers not preceded by the abbreviation Fig.
Hatching not indicated for sectional portions of an object.	
Fig(s)	Fig(s)
	Single view contains a view number and the abbreviation Fig.
Hatching of regularly spaced oblique parallel lines not spaced	Numbers not larger than reference characters.
sufficiently. Fig(s)	Fig(s)
Hatching not at substantial angle to surrounding axes or principal	
lines. Fig(s)	
Cross section not drawn same as view with parts in cross section	16. CORRECTIONS. 37 CFR 1.84(w)
	Corrections not durable and permanent. Fig(s)
with regularly spaced parallel oblique strokes.	Correction not our acre and printed in a 18/4/
Fig(s)	
Hatching of juxtaposed different elements not angled in a different	17. DESIGN DRAWING. 37 CFR 1.152
way. Fig(s)	Surface shading shown not appropriate. Fig(s)
Alternate position. 37 CFR 1.84(h)(4)	Solid black shading not used for color contrast.
A separate view required for a moved position.	Fig(s)
Fig(s)	1 1
ATTACHMENT TO PAPER NO. 3	REVIEWER Tany DATE 29

\$450.00 - 217 - Ry 2515

P/214-26

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE Patent Application of:

Dennis FINK

Serial No.: RULE 62 CONTINUATION OF

08/337,157

Group Art Unit:

2515

Filed: November 16, 1995

Examiner: J. Mullins

For: APPRATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Hon. Commissioner of Patents and Trade.marks

Washington, D.C. 20231

PETITION AND FEE FOR AUTOMATIC EXTENSION OF TIME UNDER 37 CFR 1.17, 1.136(a) AND 35 USC 41(a)8

Sir:

Applicant(s) hereby petition(s) the Commissioner of Patents and Trademarks to extend the time for filing a response to the outstanding Office Action by three months. Enclosed is our Check No. 53746 which includes the amount of \$450.00 for the petition fee in accordance with 37 CFR 1.17 computed as:

 	Response within first month not small entity (\$110)	small	entity	(\$55)
	Response within second month not small entity (\$380)	small	entity	(\$190)
xx	Response within third month	small	entity	(\$450)

You are authorized to charge to our Deposit Account No. 15-0700 any additional amounts owing.

If this petition is inadequate to avoid abandonment, the Commissioner of Patents and Trademarks is petitioned, under 37 C.F.R. §1.136(a), to extend the time by the number of months which will avoid abandonment under 37 C.F.R. §1.135. The fee under 37 C.F.R. § 1.17 should be charged to our Deposit Account No. 15-0700.

EXPRESS MAIL CERTIFICATE

Respectfully submitted,

I hereby certify that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee (mail label #TB353746547 US) in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on November 16, 1995

Dorothy Jenkins

Name of Person Mailing Correspondence

Aland Huy and Lundens

Synature

November 18, 1995

D-1------

Date of Signature

Joseph R. Keating
Registration No.: 37,368
OSTROLENK, FABER, GERB & SOFFEN, LLP
1180 Avenue of the Americas
New York, New York 10036-8403
Telephone: 21(212) 382-0700

JRK:asa

FORM\137240

QSC Audio Products Exhibit 1002 Page 62

AWC TO A



UNITED STATES DEPARTMENT OF COMMERCE Patent and Trademark Office

01/23/96

Address: COMMISSIONER OF PATENTS AND TRADEMARKS Washington, D.C. 20231

SERIAL NUMBER	FILING DAT	E	FIRST NAMED APPLICANT	ATTORNEY DOCKET NO.				
08733	97, 157	11/09/94	FINK	D	P21426			
				MULTIN	IS T			
oerroe	10 F-8402 F- AV	NETTERN STREET, WASHINGTON	E5M1/01237	E	XAMINER			
		SER GERB & OF THE AMER			-			
		10036-8403		ART UNIT	PAPER NUMBER			
				2515	. ~			

NOTICE OF ABANDONMENT

Th	is ap	oplication is abandoned in view of:
1.	M	Applicant's failure to respond to the Office letter, mailed
2.		Applicant's letter of express abandonment which is in compliance with 37 C.F.R. 1.138.
3.		Applicant's failure to timely file the response received within the period set in the Office letter.
4.		Applicant's failure to pay the required issue fee within the statutory period of 3 months from the mailing date of of the Notice of Allowance.
		☐ The issue fee was received on
		☐ The issue fee has not been received in Allowed Files Branch as of
		In accordance with 35 U.S.C. 151, and under the provisions of 37 C.F.R. 1.316(b), applicant(s) may petition the Commissioner to accept the delayed payment of the issue fee if the delay in payment was unavoidable. The petition must be accompanied by the issue fee, unless it has been previously submitted, in the amount specified by 37 C.F.R. 1.17(I), and a verified showing as to the causes of the delay.
		If applicant(s) never received the Notice of Allowance, a petition for a new Notice of Allowance and withdrawal of the holding of abandonment may be appropriate in view of Delgar Inc. v. Schuyler, 172 U.S.P.Q. 513.
5.		Applicant's failure to timely correct the drawings and/or submit new or substitute formal drawings by as required in the last Office action The corrected and/or substitute drawings were received on
		The recent/a) helew

JAMES B. MULLINS
EXAMINER
GROUP ART UNIT 252

•	PATENT A	\PPL		RD	Application or Docket Number								
	(Effe	ctive Octob	er 1, 1994	the contraction of the contracti	·		<u>00</u>	//	<u> </u>		
11	1	CL		S FILED -		SMALL	ENTITY	OR	THAN				
FOR NUMBER FILED NUMBER EXTRA									FEE		RATE	FEE	
BASIC FEE									365.00	OR		730.0	
TOTA	L CLAIMS		20) minus	20 = *	*				OR	x\$22=		
NDE	PENDENT CLA	AIMS		3 minu	s 3 = *			x38=		OR	x76=		
MULT	TIPLE DEPEND	AIM PRE	SENT		+120=			+240=					
* If th	ne difference in co	olumn 1 is	less than :	cero, enter "0" i	il.	TOTAL 365			TOTAL				
			MS AS A	AMENDED		CMALL	. ENTITY	OR	OTHER THAN				
AMENDMENTA		CL REM	AIMS AINING TER DMENT		(Column 2) HIGHEST NUMBER PREVIOUSLY PAID FOR	PRESENT EXTRA		RATE	ADDI- TIONAL FEE		RATE	ADD TION. FEE	
	Total	* C	70	Minus	A	=		x\$11=		OR	x\$22=		
	Independent	*	3	Minus	··· 3	=		x38=		OR	x76=		
eq.	FIRST PRES	SENTA	TION OF	MULTIPLE		+120=		OR	+240=				
		(Colu	ımn 1)		(Column 2)	(Column 3)	ΑE	TOTAL ADDIT. FEE			TOTAL ADDIT. FEE		
AMENDMENT B		REM/	AIMS AINING FTER IDMENT		HIGHEST NUMBER PREVIOUSLY PAID FOR	PRESENT EXTRA		RATE ADDI- TIONAL FEE			RATE	ADD TION	
20	Total	*		Minus	**	=	x\$11=			OR	x\$22=		
ME	Independent	•		Minus	***	=		x38=		OR	x76=		
۷.	FIRST PRES	SENTA	TION OF	MULTIPLE		+120=		OR	+240=				
		(Coli	umn 1) [.]		ΑE	TOTAL DDIT. FEE		OR	TOTAL ADDIT. FEE				
AMENDMENT C		REM/	AIMS AINING TER IDMENT		HIGHEST NUMBER PREVIOUSLY PAID FOR	PRESENT EXTRA		RATE ADDI- TIONAL FEE			RATE	ADD TION/ FEE	
	Total	*		Minus	**	=		x\$11=		OR	x\$22=		
	Independent	*		Minus	***	=		x38=		OR	x76=		
	FIRST PRES					+120=		OR	+240=				
* If t ** If t **If t	the entry in colur the "Highest Nun the Highest Num	nn 1 is le nber Pre lber Prev	ess than the viously Pa viously Paid	e entry in colu id For" IN THIS I For" IN THIS	mn 2, write "0" in colo S SPACE is less than SPACE is less than Independent) is the h	ımn 3. 20, enter "20." 3, enter "3."		TOTAL DDIT. FEE			TOTAL ADDIT. FEE		

FORM PTO-875

Patent and Trademark Office, U.S. DEPARTMENT OF COMMERCE

PATENT APPLICATION SERIAL NO.08/558344

U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE FEE RECORD SHEET

280 MM 01/05/96 08538344 280 MM 01/05/96 08558344 1 201 375.00-CK P/214 33 1 101 375.00 CK P/214-33

270 MM 12/20/95 08558344

MM27073 01/05/96 08558344

15-0700 270 101

375.00CH P/214-33

PTO-1556 (5/87)

08/558344 WC

OFGS File: P/214-33

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of:

Dennis FINK

Serial No.: RULE 62 CONTINUATION OF

08/337,157

Group Art Unit: 2515

Filed: November 16, 1995

Examiner: J. Mullins

For: APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Hon. Commissioner of Patents and Trademarks

Box FWC

Washington, DC 20231

REQUEST FOR FILE WRAPPER CONTINUING APPLICATION UNDER 37 C.F.R. §1.62

Sir:

This is a request for the filing of a Continuation application, under the provisions of 37 C.F.R. §1.62, of pending application Serial No. 08/337,157, filed on November 9, 1994, by Dennis FINK entitled "APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER".

The following information is furnished pursuant to 37 C.F.R. $\S1.62(h)$:

- 1. Title as originally filed and as last amended: "APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER".
- 2. Name of applicant as originally filed and as last amended: Dennis FINK.
- 3. Current correspondence address of applicant: Ostrolenk, Faber, Gerb & Soffen, LEP, 1180 Avenue of the Americas, New York, New York 19036-8403.
- 4. Amend the Specification by inserting at page 1, after line 1, the paragraph:

FORM\137220

<u>_</u>

QSC Audio Products Exhibit 1002 Page 67

£ 07 # 82 2575

This is a Continuation of Application Serial No. 08/337,157, filed on November 9, 1994. Naw atank

5. It is recognized that the filing of this Request will be considered to be a request to expressly abandon the prior application as of the filing date granted to the continuing application.

6. The filing fee is calculated as follows:
BASIC Filing Fee:\$ 750.00
Number of Claims in Excess of 20: x \$22
Number of Independent Claims over 3: x \$78
One or more multiple dependent claims:\$
TOTAL FILING FEE:\$ 750.00
OR
TOTAL FILING FEE REDUCED 50% FOR SMALL ENTITY\$ 375.00

- 7. Check No. 53742, which includes the amount of \$375.00 in payment of the filing fee, is enclosed herewith.
- 8. The Patent and Trademark Office is hereby authorized to charge any additional fees or to credit any refund at any time during the prosecution of this application, to Deposit Account No. 15-0700.

EXPRESS MAIL CERTIFICATE

I hereby certify that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee (mail label #TB353746547 US) in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on November 16, 1995

Dorothy Jenkins

Name of Person Mailing Correspondence

Ord Human Signature

November 16, 1995

Date of Signature

JRK:asa

Respectfully submitted,

Joseph R. Keating Ph. July 1 Way Rey 1:34,751

Registration No.: 37,368 OSTROLENK, FABER, GERB & SOFFEN, LLP 1180 Avenue of the Americas

New York, New York 10036-8403 Telephone: (212) 382-0700

FORM\137220



UNITED STATES DEPARTMENT OF COMMERCE Patent and Trademark Office

Address: COMMISSIONER OF PATENTS AND TRADEMARKS Washington, D.C. 20231

SERIAL NUMBER FILING DATE FIRST NAMED INVENTOR ATTORNEY DOCKET NO. 08/558,344 11/16/95 FINK EXAMINER MULLINS, J ART UNIT PAPER NUMBER OSTROLENK FABER GERB & SOFFEN 1180 AVENUE OF THE AMERICAS NEW YORK NY 10036-8403 2515 DATE MAILED: This is a communication from the examiner in charge of your application. COMMISSIONER OF PATENTS AND TRADEMARKS This application has been examined Responsive to communication filed on_____ A shortened statutory period for response to this action is set to expire _______ month(s), ______ days from the date of this letier. Failure to respond within the period for response will cause the application to become abandoned. 35 U.S.C. 133 Part I THE FOLLOWING ATTACHMENT(S) ARE PART OF THIS ACTION: 1. Notice of References Cited by Examiner, PTO-892. 2. Notice of Draftsman's Patent Drawing Review, PTO-948. 3. Notice of Art Cited by Applicant, PTO-1449. 4. Notice of Informal Patent Application, PTO-152. 5. Information on How to Effect Drawing Changes, PTO-1474. Part II SUMMARY OF ACTION 2. Claims are subject to restriction or election requirement. 7. This application has been filed with informal drawings under 37 C.F.R. 1.85 which are acceptable for examination purposes. 8. Formal drawings are required in response to this Office action. 9. The corrected or substitute drawings have been received on ____ are ☐ acceptable; ☐ not acceptable (see explanation or Notice of Draftsman's Patent Drawing Review, PTO-948). 10. The proposed additional or substitute sheet(s) of drawings, filed on _____ . has (have) been approved by the examiner; disapproved by the examiner (see explanation). 12. Acknowledgement is made of the claim for priority under 35 U.S.C. 119. The certified copy has Deen received D not been received been filed in parent application, serial no. ; filed on 13. Since this application apppears to be in condition for allowance except for formal matters, prosecution as to the merits is closed in accordance with the practice under Ex parte Quayle, 1935 C.D. 11; 453 O.G. 213. 14. Other

EXAMINER'S ACTION

Serial Number: 08/558,344

Art Unit: 2515

The disclosure is objected to because of the following informalities: The serial number of the application referenced on pages 5 and 13 should be submitted by the next response.

Claims 8 and 1-15 are rejected under 35 U.S.C. § 112, second paragraph, as being indefinite for failing to particularly point out and distinctly claim the subject matter which applicant regards as the invention.

In claim 8, "the control circuit" and in claim 10 "the amplifier" do not have antecedent basis.

In claims 14 and 15, the recitation "an amplifier" is effectively claiming the amplifier twice. See claim 10, last line.

The following is a quotation of the appropriate paragraphs of 35 U.S.C. § 102 that form the basis for the rejections under this section made in this Office action:

A person shall be entitled to a patent unless -- (b) the invention was patented or described in a printed publication in this or a foreign country or in public use or on sale in this country, more than one year prior to the date of application for patent in the United States.

(e) the invention was described in a patent granted on an application for patent by another filed in the United States before the invention thereof by the applicant for patent, or on an international application by another who has fulfilled the requirements of paragraphs (1), (2), and (4) of section 371(c) of this title before the invention thereof by the applicant for patent.

Claims 1-20 are rejected under 35 U.S.C. § $102\,(b)$ as being clearly anticipated by either Feistel or Barclay et al.

Serial Number: 08/558,344

Art Unit: 2515

Claims 1-20 are rejected under 35 U.S.C. § 102(e) as being clearly anticipated by Harris.

Claims 1-3 and 5-20 are rejected under 35 U.S.C. § 102(b) as being anticipated by either Miyake et al., Hamilton or Henegar. Note Fig. 1 of Miyake et al. and block 19 of Henegar. Note the digitally controlled amplifier of Fig. 1 of Hamilton.

Claims 10, 11, 13 and 15-20 are rejected under 35 U.S.C. § 102 (b) as being anticipated by Oiwa. Note Figs 1-5.

Muellner, Sasaki and Back are cited of interest to further show relevant art.

Any inquiry concerning this communication or earlier communications from the examiner should be directed to Mr. James B. Mullins whose telephone number is $(703)\ 308-4912$.

Any inquiry of a general nature or relating to the status of this application should be directed to the Group receptionist whose telephone number is (703) 308-0956.

JBM February 9, 1996

JAMES B. MULLINS EXAMINER

GROUP ART UNIT 252 2515

-3-

(REV. 2-92) U.S. DEPARTMENT OF COMMERC (REV. 2-92) PATENT AND TRADEMARK OFFI NOTICE OF REFERENCES CITED					OFFIC	E	00/ -2-			1	2515			ATTACHMENT TO PAPER NUMBER			7								
	ſ	VO	110	E	<i>3</i> F	KEI	rer	CENC	ES C	ITED		,			FI	NK	(
	ñ	_	_	_								U.S. I	PATE	ENT	ocui	MENT	s			_			1		
1	L	DOCUMENT NO. DATE							NAME								JB- FILING DATE ASS APPROPRIAT								
A		1	_				L					<u> </u>								\perp					
В		1	1	_		L										<u>.</u>				\perp					
С	COMPACINO																			\perp					
D								L																	
Ε	-																								
F	STATE OF THE PARTY	Name and Address of the Address of t																							
G		Section 197														1	7/ /								
н	- Contraction														i	1				T					
1						Constitution								7	1				,						
J		1	1												$\overline{\Box}$					T		-			
К		1	1	7			T						 1							T					
	<u> </u>					B		1	i		F	OREIG	IN PA	ATEN	IT DO	UME	NTS						L		
		DOCUMENT NO.				PATE COL			cou	INTRY NAME			E	CLASS			SUB- CLASS		PERTI SHTS. DWG						
L		T	T					Π		1	Ų,	Ť									1			DWG	SPEC
M		\dagger	+	1			\vdash			1/	J				<u>:</u>										
N		†	+	+	\	1	F	\downarrow													1				
6	7	*	1	1		1															1		·		+
P		1	1	4	_		/	4						-							1	***************************************		-	-
a	-	\dagger	4	7			۲	-	 												+			-	\vdash
	1_					! ЭТН	I HEI	l R RE	l Efef	RENC	ES	(Inclu	dina	Aut	hor.	itle	Date, P	ertii	nent F	ages	E	tc.)		<u> </u>	<u></u>
R																									
	Total Section																								
s							· · · ·		·																
												-													
T																									
				_																					
U										·····						_									
XAMI					```					P	ATE	, ,		1								***************************************			
an	n	r	- 6	<i>/</i>	(,)		-6-		<u> </u>	2	21	19/9	26												
						*	A	cop	y of i	this re	efere Pat	ence is	not kami	beir	ng furi Proce	nished dure	with the section	this o	office	acti (a).)	on.				

		Ţ÷			TC	SE	PARA		AND BOTT	OM EDGES, SNA	AP-APART AND D		CARBO	400	Aug. 17	
	5	•									<u> </u>	F		· · · · · · · · · · · · · · · · · · ·	·	
		PTO-892 2-92) NOT		OF	PA	TEN	IT AN	TMENT OF COM	MERCE OFFICE	SERIAL NO.	58,344	25/	UNIT	ATTACHN TO PAPE NUMBI	R	7
										I Fl	<u>US</u>					
				1841	ENT	10	-	DATE	U.S. PAT	ENT DOCUM NAME	ENTS	CLASS			LING DA	
-	-		T	J	T-	T	T	DATE		ITAME		CEASS	CL	ASS A	PPROPR	TATE
4	A	\vdash	-	\vdash	1 1,	-	-									
_	В		L	-	+	_	_									
_	С		-		-	Ļ	<u> </u>						ļ			
	D		-	L	_	L	_					,	<u> </u>			
	Ε				\perp	L	_					<u> </u>	<u> </u>			
	F									****						
	G			L							17/ /					
	н									1						
	1							·		d						
	J															
	к				T				1							
_							-	F	OREIGN É	ATENT DOC	JMENTS					
		c	ocu	JME	ENT	10.		PATE	× 00	UNTRY	NAME	С	LASS	SUB- CLASS		PP.
	L		Γ			Γ		MY	1			\dashv			Jowe	SPEC
	М			-	1											
	N			١,		h									1	
-	0	7	-		\mathcal{T}							$\neg \vdash$			+	
-	Р		1		1	1	1								1	
-	Ω		1	-					1199						_	
<u>l</u>			l		OTH	1E F	RE	FERENCES	(Includin	g Author, Ti	tle, Date, Perti	nent Pa	ges, E	tc.)		
Name and Address of the Owner, where				,	-					-				· · · · · · · · · · · · · · · · · · ·		
OBSTORESSEE	R	<u>-</u>		÷.				,								
- Contraction					·											
	s				···							1,		· · · · · · · · · · · · · · · · · · ·		
-												-)	- <u> </u>	
Annual Section Section 1	T														200 200 200 200 200	
STATE SECTION AND ADDRESS.	7476	rion.						2		-				· · · · · · · · · · · · · · · · · · ·	15.2	7 1
	Z.								· · · · · · · · · · · · · · · · · · ·							1 1 1
<u> </u>	129 16	NER			` .	<u> </u>		DATE								
Ô		nez-	0)	5,				11 12 20 1	9/90							10 12 12
		å _{VV}			# 	Α	copy See I	of this refere Manual of Pat	ence is no ent Exam	t being furni nining Proced	shed with this lure, section 70	office a 07.05 (a	ction.).)			
.,.	•			<u> </u>	- 200 A	2 /2		And the second s		· Q	SC Audio I	roduc	ts E	xhibit 1	002	Page

Transaction History Date 1996-05-16 Date information minieved from USPTO Patent Application Information Retrieval (PAIR) system records at www.uspto.gov



P/214-33

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re: Patent Application of

Dennis FINK

Date: May 13, 1996

Serial No. 08/558,344

Group Art Unit: 2515

Filed: November 16, 1995

Examiner: J. Mullins

For:

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Hon. Commissioner of Patents

and Trademarks

Washington, D.C. 20231

Att: Application Branch

REQUEST FOR DUPLICATE FILING RECEIPT

sir:

We respectfully request a duplicate filing receipt for this case. Enclosed is our check no. 5754/ in payment of the required fee.

I hereby certify that this correspondence is being deposited with the United States Postal Service with sufficient postage as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on May 13, 1996:

Iames A. Finder

Name of applicant, assignee or Registered Representative

Signature May 13, 1996

Date of Signature

Respectfully submitted,

James A. Finder

Registration No.: 30,173

OSTROLENK, FABER, GERB & SOFFEN, LLP

1180 Avenue of the Americas New York, New York 10036-8403

Telephone: (212) 382-0700

JAF:rk

290 80 03/21/96 06/55/1344 1 526 25.00 St

#220-121

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application

Dennis FINK

Serial No.:

November 16,

Examiner: J. Mullins PROGRAMMING AN AMPLIFIER

New York, New York

Date: July 15, 1996

Group Art Unit: 2515

Hon. Commissioner of Patents and Trademarks Washington, D.C. 20231

Sir:

Pursuant to 37 C.F.R. 1.56, the attention of the Patent and Trademark Office is hereby directed to the references listed on the attached PTO-1449. One copy of each reference is attached. It is respectfully requested that the information be expressly considered during the prosecution of this application, and that the references be made of record therein and appear among the "References Cited" on any patent to issue therefrom.

This Information Disclosure Statement is being submitted before either of a final action, under 37 C.F.R. § 1.113 and a notice of allowance under 37 C.F.R. §1.113 and, accordingly, a check (No. _____) in the amount of \$220.00 is enclosed to cover the required fee.

The Examiner's attention is directed to co-pending U.S. Patent Application No. 08/546,839 filed October 23, 1995. The identification of the above U.S. Patent Application is not to be construed as a waiver of secrecy as to that application now or upon issuance of the present application as a patent. Examiner is respectfully requested to consider the cited application and the prior art references cited therein during examination.

020 JJ 07/29/96 08558344

1 126

220.00 CK

I hereby certify that this deposited with the United ates Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on July 15, 1996:

James A. Finder, Esq.
Name of applicant, assignee or
Registered Representative

Signature
July 15, 1996
Date of Signature

JAF:apm Enclosures Respectfu? submitted,

Registration No.: 30,173 OSTROLENK, FABER, GERB & SOFFEN, LLP

1180 Avenue of the Americas New York, New York 10036-8403

Telephone: (212) 382-0700



Sheet 1 of

			-					ication 08/55		OFGS File	No P/214	1-33	
APPLI						ON		RONK,	Dennis	1			
(Use	seve	ral she	eets if	neces	sary)	2	Filin	Upite Noven	nber 16, 1995	Group Art	^{Uni} 2515	5	
						N. Co	JS	ATE T	DOCUMENTS				
Examiner Initial			Docui	nent N	Numbe	r	MADE	MAR Date	Name	Class	Sub- class	Filin If Ap	g Date propriate
Ash	4	9	9	1	2	2	1	2/91	Rush				
Kins	5	3	1	4	5	2	4	5/94	Van Hulle, et al.				
													-
				-			-						
				_	-								*****
· · · · · · · · · · · · · · · · · · ·		L	L	<u> </u>	L		\	CNAPAGE	VE DOCUMENTS			L	
						F(JKE	GN PATE	NT DOCUMENTS				
			_					D.,			Sub- class	Translation	
			Docui	nent N	lumbe	r	,	Date	Country	Class		Yes	No
			-	-	-							<u> </u>	
				-		-	-						
			-	-									
				-			-						
		I	 ОТ	LED	DO:	CIIN	CENT	Γς σ	Austral Tista Data Basis	Davis N	[L	I
ı,	,		01	пек		CUIV	TEIN	Co (Including	Author, Title, Date, Pertin	ent Pages,	E(C.)		
Aspen		Co	-pend	ling .	Appli	catio	n No	08/546,8	39 "Digital Signal Pro	ocessor fo	r Ampli	fier" fi	led
# (UC	tober	23.	1993								
-													
													
										<u> </u>			
													
00			1		0	,	Ī		1 /-:				
Examiner	w	15	. /	Av	ll	his	Date	e Considered	9/6/94				
EXAMINE	R: Init	ial if ci	tation o	onside	red, who	ether or	r not cit		rmance with MPEP § 609; Drav	line through	citation if no	ot in confo	rmance

Other Prior Art

According to the information contained in form PTO-1449 or PTO-892, there are one or more other prior art/non-patent literature documents missing from the original file history record obtained from the United States Patent and Trademark Office. Upon your request we will attempt to obtain these documents from alternative resources. Please note that additional charges will apply for this service.

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of

Dennis Fink

Date: July 15, 1996

Serial No.: 08/558,344

Group Art Unit: 2515

led: November 16, 1995

Examiner: J.B. Mullins

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

AMENDMENT TRANSMITTAL LETTER - FEE COMPUTATION

Hon. Commissioner of Patents and Trademarks Washington, D.C. 20231

Transmitted herewith is an amendment in the above-identified application.

OFGS Check No. 59059 , which includes the fee of \$226.00 calculated below, is attached.

1	NO.		HIGHEST	NO.						
CLAIM	S AFTER		PREVIOUS	LY						ADDIT.
AME	NDMENT		PAID FOR	I	EXTRA PR	ESENT		RATE		FEE
TOTAL	37	MINUS	20	* :	= 17	X	(\$11	SE or	\$22)	\$187.00
INDEP	. 4	MINUS	3	** =	= 1	. х	(\$39	SE or	\$78)	\$ 39.00
FIRST	PRESENTA	ATION OF	MULTIPL	E DEPENDE	T CLAIM	_ x	(\$125	SE or	\$250)	\$
* not	legg tha	an 20	** not	legg than	3				TOTAL.	\$226 00

If this communication is filed after the shortened statutory time period had elapsed and no separate Petition is enclosed, the Commissioner of Patents and Trademarks is petitioned, under 37 C.F.R. §1.136(a), to extend the time for filing a response to the outstanding Office Action by the number of months which will avoid abandonment under 37 C.F.R. §1.135. The fee under 37 C.F.R. § 1.17 should be charged to our Deposit Account No. 15-0700.

I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on July 15, 1996:

James A. Finder
Name of Registered Representative

Signature July 15, 1996

Date of Signature

Respectfully submitted

James A. Finder

Registration No.: 30,173

OSTROLENK, FABER, GERB & SOFFEN, LLP

1180 Avenue of the Americas New York, New York 10036

Telephone: (212) 382-0700

TRAN\165162

39 - 202 GR25/5

P/214-33
IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

re Patent Application of

New York, New York

L Dennis Fink

Date: July 15, 1996

19

Date: Buly 15, 1996

Serial No.: 08/558,344

Group Art Unit: 2515

red: November 16, 1995

Examiner: J.B. Mullins

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Hon. Commissioner of Patents and Trademarks Washington, D.C. 20231

AMENDMENT PURSUANT TO 37 CFR § 115

Sir:

In response to the Office Action mailed February 14, 1996, please reconsider the above-identified application amended as follows:

IN THE SPECIFICATION:

At page 5, lines 23-24, change "U.S. Patent Application No. ____ (Attorney Docket No. P/214-25)" to: --U.S. Patent Application No. 08/546,839 which is a continuation application of U.S. Patent Application No. 08/336,481--.

At page 13, lines 15-16, change "No. _____ (Attorney Docket No. P/214-25)" to: --No. 08/336,481--.

IN THE CLAIMS:

Please cancel claim without prejudice.

Please amend the claims as follows:

(Amended) An amplifier comprising:

an input port for receiving an input signal;

a signal processing circuit comprising a digital signal

processor capable of receiving at least one of a signal processing function and a signal processing function parameter, wherein the signal processing circuit receives [for receiving] the input signal from the input port and [modifying] modifies the input signal from the input signal fr

AMDT\162373

1

a power amplifier for amplifying the <u>modified</u> input signal received from the signal processing circuit and outputting [a modified] <u>an amplified</u> signal to an output device;

an external programmer; and

a programming signal input [device] <u>port</u> for receiving at least one programming signal from [an] <u>the</u> external programmer, <u>the external programmer being</u> removably [connected] <u>connectable</u> to the programming signal input [device] <u>port</u> for modifying at least one of a signal processing function and a signal processing function parameter defined in said signal processing circuit.

(Amended) The amplifier of claim 1, further comprising a control panel, wherein said programming signal input [device] port is provided on the control panel.

(Amended) The amplifier of claim 1, wherein the signal processing circuit <u>further</u> comprises a plurality of electronic components <u>and</u> [each having] a non-volatile storage means for storing a set performance characteristics.

(Amended) The amplifier of claim 2, wherein the signal processing circuit comprises [a plurality of electronic components each having] a storage device for storing at least one of the signal processing function and the signal processing function parameter [value set] produced by the control circuit.

(Amended) The amplifier of claim [1] 2, wherein the control circuit comprises a programmable microprocessor.

10. (Amended) An amplifier programmer comprising:
an input/output port for sending and receiving control information;

[an] <u>a</u> data input device for allowing input of programming information to the programmer; and

131 A

a controller for receiving the input programming information, generating [control] programming signals from the input programming information and transmitting the [control] programming signals through the input/output port to an amplifier for modifying at least one of a signal processing function and a signal processing function parameter of the amplifier.

34

14. (Amended) The amplifier programmer of claim 10, wherein the controller comprises a microprocessor for receiving programming information from at least one of the input device and a control circuit of [an] the amplifier.

16. (Amended) A method of programming an amplifier comprising the steps of:

providing the amplifier with a programming signal input

5

10

port;

connecting an external programmer to the programming signal input port;

inputting programming information to the external programmer; [and]

transmitting the programming information from the external programmer to the amplifier [for]; and

changing at least one of a signal processing function and a signal processing function parameter defined in the amplifier.

36

18. (Amended) The method of claim 16, further comprising the step of converting the input programming information [to control signals] into at least one programming signal for modifying the performance characteristics of at least one signal processing control element contained in the amplifier.

19. (Amended) The method of claim 16, wherein the step of inputting programming information comprises the step of inserting at least one of a signal processing function program, a signal processing function parameter data, a [desired] signal

characteristic modification value and a [desired] signal processing function parameter value.

20. (Amended) The method of claim 16, further comprising the step of storing the input [control] programming information.

B ()

- --22. The amplifier of claim 1, wherein said amplifier executes operation according to said at least one of a signal processing function and a signal processing function parameter after said external programmer is deactivated.--
- --23. The amplifier of claim 1, wherein said at least one of a signal processing function and a signal processing function parameter of said amplifier cannot be modified after said external programmer is disconnected from said amplifier.--
- --24. The amplifier of claim 1, wherein said at least one of a signal processing function and a signal processing function parameter of said amplifier cannot be modified after said external programmer is deactivated.--
- --25. The amplifier of claim 1, wherein said external programmer is taken from the group consisting of: a personal computer; a networked computer; and a hand held embedded computer controller.--
- --26. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal

processing function and a signal processing function parameter from the group consisting of: a crossover function; a volume control function; an equalizing function; a compression function; and a level threshold function.--

--27. The amplifier of claim 1, wherein said digital signal processor receives and stores a combination of at least two signal processing functions from the group consisting of: a crossover function; a volume control function; an equalizing function; a compression function; and a level threshold function.--

The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter which automatically vary the operation of said amplifier according to the time of day.--

5

5 .

--29. The amplifier programmer of claim 10, wherein said programmer is taken from the group consisting of: a personal computer; a networked computer; and a hand held embedded computer controller.--

--30. The amplifier programmer of claim 10, wherein said programmer stores in groups said at least one of a signal processing function and a signal processing function parameter according to at least one of a time of day, during which said amplifier is to operate, and a type of event, for which said amplifier is to operate.--

--31. An amplifier comprising:

an input port for receiving an input signal;
a signal processing circuit comprising an analog signal
processor capable of receiving and storing at least one signal
processing function parameter, wherein the signal processing

circuit receives the input signal from the input port and modifies the input signal,

a power amplified for amplifying the modified input signal received from the signal processing circuit and outputting an amplified signal to an output device;

an external programmer; and

a programming signal input port for receiving at least one programming signal from the external programmer, the external programmer being removably connectable to the programming signal input port for modifying at least one of a signal processing function and a signal processing function parameter defined in said signal processing circuit.

--32. The amplifier of claim 31, wherein said amplifier executes operation according to said at least one signal processing function parameter after said external programmer is disconnected from said amplifier.--

--33. The amplifier of claim 31, wherein said amplifier executes operation according to said at least one signal processing function parameter after said external programmer is deactivated.--

- --34. The amplifier of claim 31, wherein said at least one signal processing function parameter of said amplifier cannot be modified after said external programmer is disconnected from said amplifier.--
- --35. The amplifier of claim \$1, wherein said at least one signal processing function parameter of said amplifier cannot be modified after said external programmer is deactivated.--
- --36. The amplifier of claim 31, wherein said external programmer is taken from the group consisting of: a personal computer; a networked computer; and a hand held embedded computer controller.--

6

AMDT\162373

10

--37. The amplifier of claim 31, wherein said signal processing circuit receives and stores at least one signal processing function parameter for the group of signal processing functions consisting of: a crossover function; a volume control function; an equalizing function; a compression function; and a level threshold function.--

--38. The amplifier of claim 31, wherein said digital signal processor receives and stores at least one signal processing function parameter which automatically varies the operation of said amplifier according to the time of day.--

REMARKS

Reconsideration and allowance of this application are respectfully requested. Claim 9 has been canceled. Claims 1, 5-8, 10, 14, 16, and 18-20 have been amended and claims 21-38 have been added and are submitted for the Examiner's consideration.

Applicant submits that the amendments to claims 1, 5-8, 10, 14, 16, and 18-20 and added claims 21-38 are fully supported by the specification and claims as originally filed and, therefore, no new matter has been added.

In the Office Action, the Examiner objected to the disclosure because the references to pending U.S. patent applications in the disclosure required updating. In response, Applicant has updated the U.S. patent application numbers referenced in the disclosure as required by the Examiner. Accordingly, no new matter has been added.

The Examiner rejected claims 8 and 14-15 under 35 U.S.C. §112 for inconsistent reliance of antecedent bases. In response, Applicant has amended claims 8 and 14-15 to provide the proper antecedent basis. Accordingly, Applicant submits that the Examiner's 35 U.S.C. §112 rejection has been overcome and should be withdrawn.

The Examiner rejected claims 1-20 under 35 U.S.C. §102(b) as being anticipated by U.S. Patent No. 4,223,272 to Feistel or U.S. Patent No. 5,015,969 to Barclay et al.

Conventional amplifiers having signal processing circuits are comprised of analog and digital components on a printed circuit board. The signal processing function parameters, for example, crossover frequency and amplitude, can be changed by adjusting control knobs provided on an amplifier housing which are operatively connected to the components of the signal processing circuit. Alternatively, the signal processing function parameters may be modified by signals input via a computer or similar device under program control.

However, with the conventional amplifiers as discussed above, the signal processing function is fixed by the circuit design of the signal processing circuit and cannot be easily changed. Although the user can change the signal processing function <u>parameters</u> as described above, it is often necessary or desirable to change the signal processing <u>function</u> or even combine several different signal processing functions in the signal processing circuit. This is not possible with conventional amplifiers.

Accordingly, the present invention provides an amplifier and amplifier programmer being removably connected to the amplifier to quickly and easily change signal processing functions and/or parameters of the amplifier without modifying signal processing circuit elements. The preferred embodiment of the present invention includes a portable amplifier programmer that is capable of receiving input information and transmitting the input information to an amplifier signal processing circuit to modify signal processing functions and/or parameters.

The Feistel reference and the Barclay reference disclose amplifiers comprising microprocessor controlled signal processing circuits where the parameters of the signal processing circuits are modified by the output data of the microprocessor.

Specifically, the Feistel reference shows that an audio signal may be modified by a digital filter where "the various parameters defining the transfer function ... can be chosen on the basis of either frequency or response time." (emphasis added, Col. 2, lines 23-26). The parameters are adjusted by

8

turning knobs or wheels (Col. 5, lines 32, 43 and 64); by physically replacing electrical components (Col. 6, lines 4-8); or by keyboard entry into a microprocessor (Col. 6, lines 19-29).

However, the Feistel reference does not disclose:

a signal processing circuit comprising a digital signal processor capable of receiving at least one of a signal processing function and a signal processing function parameter, wherein the signal processing circuit receives the input signal from the input port and modifies the input signal;

an external programmer; and

a programming signal input port for receiving at least one programming signal from the external programmer, the external programmer being removably connected to the programming signal input port as recited in amended claim 1 of the instant application. Indeed, the Feistel reference discloses a filter circuit in which only the filter function parameters can be modified as opposed to a digital signal processor capable of modifying the signal processing function of an amplifier as recited in Applicant's amended claims 1, 10 and 16. Further, the Feistel reference does not disclose an external programmer which is removably connected to the amplifier via a programming signal input port as recited in amended claim 1.

Similarly, the Barclay reference discloses a signal processing circuit (digital attenuator) where the gain <u>parameter</u> of the attenuator is set by a microprocessor in light of junction temperature data and/or signal fidelity data which is presented to the microprocessor via a feedback loop. As discussed above with respect to the Feistel reference, the Barclay reference does not disclose (i) <u>a digital signal processor capable of receiving at least one of a signal processing function and a signal processing function parameter or (ii) an external programmer being removably connected to a programming signal input port as claimed by Applicant.</u>

Therefore, the Examiner's 35 U.S.C. §102(b) rejection of amended claims 1, 10 and 16 in view of the Feistel reference or the Barclay reference cannot stand because anticipation of a

claim can be found only if the prior art reference discloses every element of the claim. Ex parte Luck, 28 USPQ2d 1875, 1876 (Bd. App. 1993). Accordingly, Applicant respectfully requests that the Examiner's 35 U.S.C. §102(b) rejection of claims 1, 10 and 16 in view of the Feistel reference or the Barclay reference be withdrawn.

The Examiner rejected claims 1-20 under 35 U.S.C. \$102(e) as being anticipated by U.S. Patent No. 5,339,362 to Harris. The Harris reference discloses a controller which is connected to a remote data access terminal (RDAT), where the controller passes commands from the RDAT to a digital signal processor and/or signal processing card(s). The RDAT is not removably connected to the controller (indeed, the RDAT must always be connected to the controller for the system to operate) and the signal processing card(s) are not capable of receiving at least one of a signal processing function and a signal processing function parameter as recited in claims 1, 10 and 16.

Therefore, as was discussed above with reference to the Feistel reference and the Barclay reference, the Examiner's 35 U.S.C. §102(e) rejection of amended claims 1, 10 and 16 in view of the Harris reference cannot stand because anticipation of a claim can be found only if the prior art reference discloses every element of the claim. Ex parte Luck, 28 USPQ2d 1875, 1876 (Bd. App. 1993). Accordingly, Applicant respectfully requests that the Examiner's 35 U.S.C. §102(e) rejection of claims 1, 10 and 16 in view of the Harris reference be withdrawn.

The Examiner rejected claims 1-3 and 5-20 under 35 U.S.C. §102(b) as being anticipated by U.S. Patent No. 5,045,802 to Miyake, U.S. Patent No. 4,079,334 to Hamilton or U.S. Patent No. 3,769,606 to Henegar.

The Miyake reference discloses a microprocessor controlled frequency response equalizer where the "base characteristic," "treble characteristic" and "peak characteristics" of the equalizer (comprising a plurality of band pass filters) can be "set." (Col. 1, lines 26-31; and Col. 2, lines 52-65). The "characteristics" of the band pass filters are

nothing more than the <u>parameters</u> (corner frequencies and gains) of the equalizer.

The Hamilton reference discloses a microprocessor controlled signal processing circuit comprising discrete operational amplifiers having reactive feedforward and feedback impedances for creating fixed signal processing functions such as "sustain," "wah-wah" and "fuzz." (Col. 1, lines 4-38). The feedforward and feedback impedances are altered by switching means operatively connected to the impedances and the operational amplifiers. The adjustment of the impedances is no more than adjusting the <u>parameters</u> of the fixed functions of the signal processing circuit.

The Henegar reference discloses that a digital word alters the "filtering range" of either a first order or a second order analog filter circuit (Fig. 5). As in the circuit of the Hamilton reference, the Henegar reference shows that feedforward and feedback impedances are altered by switching means operatively connected to the impedances and an operational amplifier. Again, the adjustment of the impedances is no more than adjusting the parameters of the fixed function provided by the first order or second order analog filter. It is noted that the function of the circuit of the Henegar reference may be altered by manual processes. Specifically, the filter circuit may be changed from a first order filter to a second order filter by manually changing the "slab" which orients the analog circuit components. (Col. 6, lines 54-58).

However, as discussed above with respect other cited references, neither the Miyake reference, the Hamilton reference nor the Henegar reference disclose (i) a digital signal processor capable of receiving at least one of a signal processing function and a signal processing function parameter or (ii) an external programmer being removably connected to a programming signal input port as claimed by Applicant.

Therefore, the Examiner's 35 U.S.C. §102(b) rejection of amended claims 1, 10 and 16 in view of the Miyake reference, the Hamilton reference or the Henegar reference cannot stand

AMDT\162373 11

because anticipation of a claim can be found only if the prior art reference discloses every element of the claim. Ex parte Luck, 28 USPQ2d 1875, 1876 (Bd. App. 1993). Accordingly, Applicant respectfully requests that the Examiner's 35 U.S.C. §102(b) rejection of claims 1, 10 and 16 in view of the Miyake reference, the Hamilton reference or the Henegar reference be withdrawn.

The Examiner rejected claims 10, 11, 13 and 15-20 under 35 U.S.C. §102(b) as being anticipated by U.S. Patent No. 4,000,475 to Oiwa. The Oiwa reference discloses that a manipulation unit (the front control panel of an amplifier) may be "detachably directly coupled" to the amplifier unit. When the manipulation unit is "detached," a cable means is extended between the amplifier and the manipulation unit so that fidelity of the audible signal may be adjusted by knobs and switches at a location beyond arms length from the amplifier. (Figs. 1-4; Col. 3, lines 6-10; and Col. 4, lines 18-21). In fact, the manipulation unit cannot be disconnected from the amplifier without replacing the manipulation unit connection with a simplified manipulation unit because, without some connection to the amplifier, the amplifier will not function. (Col. 6, lines 32-36). Further, the adjustment of the knobs and switches of the manipulation unit merely change the parameters of the fixed functions of the amplifier.

However, as discussed above with respect other cited references, the Oiwa reference does not disclose (i) a digital signal processor capable of receiving at least one of a signal processing function and a signal processing function parameter or (ii) an external programmer being removably connected to a programming signal input port as claimed by Applicant.

Therefore, the Examiner's 35 U.S.C. §102(b) rejection of amended claims 10 and 16 in view of the Oiwa reference cannot stand because anticipation of a claim can be found only if the prior art reference discloses every element of the claim. Exparte Luck, 28 USPQ2d 1875, 1876 (Bd. App. 1993). Accordingly, Applicant respectfully requests that the Examiner's 35 U.S.C.

12

§102(b) rejection of claims 10 and 16 in view of the Oiwa reference be withdrawn.

None of the reference cited by the Examiner teach or suggest all the limitations recited new independent claim 31.

Namely, the cited references do not recite an external programmer being removably connected to a programming signal input port as claimed by Applicant. Therefore, a 35 U.S.C. §§ 102, 103 rejection of new claim 31 in view of the cited art would be improper because anticipation of a claim can be found only if the prior art reference discloses every element of the claim. Exparte Luck, 28 USPQ2d 1875, 1876 (Bd. App. 1993). Accordingly, Applicant submits that claim 31 recites a patentable combination.

Further, claims 32-38 all depend on claim 31 and contain all of the limitations of claim 31 as well as other limitation(s) which, for the reasons articulated above, also define patentable combinations.

Still further, claims 2-5, 7, 8, and 21-28 all depend on claim 1 and contain all of the limitations of claim 1 as well as other limitation(s) which, for the reasons articulated above, also define patentable combinations. Therefore, Applicant respectfully requests that the Examiner's 35 U.S.C. §102 rejections of claims 2-5, 7 and 8 be withdrawn.

Still further, claims 11-15 and 29-30 all depend on claim 10 and contain all of the limitations of claim 10 as well as other limitation(s) which, for the reasons articulated above, also define patentable combinations. Therefore, Applicant respectfully requests that the Examiner's 35 U.S.C. §102 rejections of claims 11-15 be withdrawn.

Still further, claims 17-20 all depend on claim 16 and contain all of the limitations of claim 16 as well as other limitation(s) which, for the reasons articulated above, also define patentable combinations. Therefore, Applicant respectfully requests that the Examiner's 35 U.S.C. §102 rejections of claims 17-20 be withdrawn.

The Examiner may contact the undersigned to discuss any still outstanding matters. Early and favorable action is earnestly solicited.

I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on July 15, 1996

James A. Finder
Name of applicant, assignee or
Registered Representative

Signature July 15, 1996

Date of Signature

Respectfully submitted,

James A. Finder

Registration No.: 30,173

OSTROLENK, FABER, GERB & SOFFEN, LLP

1180 Avenue of the Americas

New York, New York 10036-8403 Telephone: (212) 382-0700

JAF: MBD

MAIL R. \$ 190-2," GR 25/5
IN THE UNITED STATES PATENT AND TRADEMARK OFFICE
Date: July 15, 1996 Serial No.: 08/558,344 Group Art Unit: 2515
Filed: November 16, 1995 Examiner: J.B. Mullins
For: APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER
R_{r}
Hon. Commissioner of Patents and Trademarks Washington, D.C. 20231
PETITION AND FEE FOR AUTOMATIC EXTENSION OF TIME 99 UNDER 37 CFR 1.17, 1.136(a) AND 35 USC 41(a)8
Applicant hereby petitions the Commissioner of Patents and Trademarks to extend the time for filing a response to the outstanding Office Action by two (2) months. Enclosed is our check No which includes the amount of \$190.00 for the petition fee in accordance with 37 CFR 1.17 computed as:
Response within first month not small entity (\$110) small entity (\$55)
<pre>XX Response within second monthXX small entity (\$190)</pre>
Response within third month not small entity (\$450)
Response within fourth month not small entity (\$1,400) small entity (\$700)
You are authorized to charge to our Deposit Account No. 15-0700 any additional amounts owing.
If this petition is inadequate to avoid abandonment, the Commissioner of Patents and Trademarks is petitioned, under 37 C.F.R. §1.136(a), to extend the time by the number of months which will avoid abandonment under 37 C.F.R. §1.135. The fee under 37 C.F.R. § 1.17 should be charged to our Deposit Account No. 15-0700.
I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 202317 on Telly 15, 1996. James A. Finder 190.00 CK 190.00

MISC\165159



UNITED STATES EPARTMENT OF COMMERCE Patent and Trademark Office

Address: COMMISSIONER OF PATENTS AND TRADEMARKS Washington, D.C. 20231

APPLICATION NUMBER FILING DATE FIRST NAMED APPLICANT ATTORNEY DOCKET NO. P/214-33 11/16/95 FINK 08/558.344 EXAMINER E5M1/0917 OSTROLENK FABER GERB & SOFFEN ART UNIT PAPER NUMBER 1180 AVENUE OF THE AMERICAS NEW YORK NY 10036-8403 2515 DATE MAILED: 09/17/96 This is a communication from the examiner in charge of your application. COMMISSIONER OF PATENTS AND TRADEMARKS OFFICE ACTION SUMMARY Responsive to communication(s) filed on _ This action is FINAL. ☐ Since this application is in condition for allowance except for formal matters, prosecution as to the merits is closed in accordance with the practice under Ex parte Quayle, 1935 D.C. 11; 453 O.G. 213. A shortened statutory period for response to this action is set to expire_ whichever is longer, from the mailing date of this communication. Failure to respond within the period for response will cause the application to become abandoned. (35 U.S.C. § 133). Extensions of time may be obtained under the provisions of 37 CFR 1.136(a). Disposition of Claims Claim(s) _ _ is/are pending in the application. Of the above, claim(s) is/are withdrawn from consideration. Claim(s)_ Claim(s) is/are rejected. ☐ Claim(s) _ is/are objected to. ☐ Claims are subject to restriction or election requirement. **Application Papers** ☐ See the attached Notice of Draftsperson's Patent Drawing Review, PTO-948. _____is/are objected to by the Examiner. ☐ The drawing(s) filed on _ ☐ The proposed drawing correction, filed on _____ _____ is approved disapproved. ☐ The specification is objected to by the Examiner. ☐ The oath or declaration is objected to by the Examiner. Priority under 35 U.S.C. § 119 Acknowledgement is made of a claim for foreign priority under 35 U.S.C. § 119(a)-(d). ☐ All ☐ Some* ☐ None of the CERTIFIED copies of the priority documents have been received. received in Application No. (Series Code/Serial Number) _ received in this national stage application from the International Bureau (PCT Rule 17.2(a)). *Certified copies not received: _ Acknowledgement is made of a claim for domestic priority under 35 U.S.C. § 119(e). Attachment(s) ☐ Notice of Reference Cited, PTO-892 Information Disclosure Statement(s), PTO-1449, Paper No(s). ☐ Interview Summary, PTO-413 ☐ Notice of Draftsperson's Patent Drawing Review, PTO-948 Notice of Informal Patent Application, PTO-152 -- SEE OFFICE ACTION ON THE FOLLOWING PAGES --

-2-

Serial Number: 08/558,344

Art Unit: 2515

The following is a quotation of the first paragraph of 35 U.S.C. § 112:

The specification shall contain a written description of the invention, and of the manner and process of making and using it, in such full, clear, concise, and exact terms as to enable any person skilled in the art to which it pertains, or with which it is most nearly connected, to make and use the same and shall set forth the best mode contemplated by the inventor of carrying out his invention.

The specification is objected to under 35 U.S.C. § 112, first paragraph, as the specification, as originally filed, does not provide support for the invention as is now claimed. More specifically, the limitations as specified in claims 21-30 and 32-38 do not find support in the original disclosure.

Claims 21-30 and 32-38 are rejected under 35 U.S.C. \$ 112, first paragraph, for the reasons set forth in the objection to the specification.

Claims 25-27, 29, 30, 36 and 37 are rejected under 35 U.S.C. § 112, second paragraph, as being indefinite for failing to particularly point out and distinctly claim the subject matter which applicant regards as the invention. These claims recite alternative structure and accordingly are deemed to be indefinite. "Markush"-type claims 25-26, 29, 36 and 37 are deemed to be improper in this instance since they recite alternative structure.

The following is a quotation of the appropriate paragraphs of 35 U.S.C. \S 102 that form the basis for the rejections under this section made in this Office action:

-3-

Serial Number: 08/558,344

Art Unit: 2515

A person shall be entitled to a patent unless -- (b) the invention was patented or described in a printed publication in this or a foreign country or in public use or on sale in this country, more than one year prior to the date of application for patent in the United States.

(e) the invention was described in a patent granted on an application for patent by another filed in the United States before the invention thereof by the applicant for patent, or on an international application by another who has fulfilled the requirements of paragraphs (1), (2), and (4) of section 371(c) of this title before the invention thereof by the applicant for patent.

Claims 10-15, 29 and 30 are rejected under 35 U.S.C. \$ 102(b) as being anticipated by either Feistel, Barclay et al. or Miyake et al. All the references show a controller for modifying at least a signal processing function parameter of an amplifier. Feistel modifies the parameters of resistors and capacitors; Barclay et al. modify the attenuation of an audio input signal, which is input at terminals 12; and Miyake et al. modify the frequency characteristic of an audio signal by varying the gain of amplifiers 14_1 - 14_n . Thus, it is deemed that the references show all that is claimed.

Claims 10-20 and 29-38 are rejected under 35 U.S.C. § 102(e) as being anticipated by Harris. RDAT 16, read as an input data device, is connected to the controller 12 via hardware or RF link (col. 3, lines 26-28) and thus, is removably connected to the controller; however, this is not an issue, insofar as claims 10-15, 29 and 30 are concerned, since such limitation is not present in the claims. Controller 12 may be read as the recited

Serial Number: 08/558,344

Art Unit: 2515

"controller" and will accomplish the function as recited in the claims.

Applicant's arguments have been carefully considered; however, they are not persuasive since it is deemed that the claims can be read directly on the references.

Claims 1-8 are allowable over the prior art of record.

Applicant's amendment necessitated the new grounds of rejection. Accordingly, **THIS ACTION IS MADE FINAL**. See M.P.E.P. § 706.07(a). Applicant is reminded of the extension of time policy as set forth in 37 C.F.R. § 1.136(a).

A SHORTENED STATUTORY PERIOD FOR RESPONSE TO THIS FINAL ACTION IS SET TO EXPIRE THREE MONTHS FROM THE DATE OF THIS ACTION. IN THE EVENT A FIRST RESPONSE IS FILED WITHIN TWO MONTHS OF THE MAILING DATE OF THIS FINAL ACTION AND THE ADVISORY ACTION IS NOT MAILED UNTIL AFTER THE END OF THE THREE-MONTH SHORTENED STATUTORY PERIOD, THEN THE SHORTENED STATUTORY PERIOD WILL EXPIRE ON THE DATE THE ADVISORY ACTION IS MAILED, AND ANY EXTENSION FEE PURSUANT TO 37 C.F.R. § 1.136(a) WILL BE CALCULATED FROM THE MAILING DATE OF THE ADVISORY ACTION. IN NO EVENT WILL THE STATUTORY PERIOD FOR RESPONSE EXPIRE LATER THAN SIX MONTHS FROM THE DATE OF THIS FINAL ACTION.

Any inquiry concerning this communication or earlier communications from the examiner should be directed to Mr. James B. Mullins whose telephone number is (703) 4912.

Any inquiry of a general nature or relating to the status of this application should be directed to the Group receptionist whose telephone number is (703) 308-0956.

JBM September 6, 1996

JAMES B. MULLINS
EXAMINER
GROUP ART UNIT-252 251)

amer B. Wulling

-4-

P/214-33



IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

e Patent Application of

nnis Fink

Date: December 17, 1996

Serial No.: 08/558,344

Group Art Unit: 2515

Filed: November 16, 1995

Examiner: J.B. Mullins

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER For: __________

AMENDMENT TRANSMITTAL LETTER - FEE COMPUTATION

Hon. Commissioner of Patents and Trademarks Washington, D.C. 20231

Transmitted herewith is an amendment in the aboveidentified application.

XX "Small Entity" status (37 C.F.R. §1.9 & §1.27) established XX previously __by enclosed verified statement.

_, which includes the fee of $\frac{$-0-$}{}$ calculated OFGS Check No. below, is attached.

	NO.		HIGHEST NO	ο.								
CLAIM	S AFTER		PREVIOUSLY	ď							Α	DDIT.
AME	NDMENT		PAID FOR	EX	TRA PRES	SENT		R.P.	TE			FEE
TOTAL	26	MINUS	37	* =	-0-	х	(\$11	SE	or	\$22)	\$	
INDEP	. 1	MINUS	4	** =	-0-	х	(\$39	SE	or	\$78)	\$	
FIRST	PRESENTA	ATION OF	MULTIPLE	DEPENDENT	CLAIM	×	(\$125	SE	or	\$250)	\$	
* 20+	loca the	20	** not 1	ace than 3						TOTAL	c	-0-

or is inadvertently not enclosed or if any additional fee during the prosecution of this application is not paid, the Patent Office is authorized to charge the underpayment to Deposit Account No. 15-0700.

If this communication is filed after the shortened statutory time period had elapsed and no separate Petition is enclosed, the Commissioner of Patents and Trademarks is petitioned, under 37 C.F.R. §1.136(a), to extend the time for filing a response to the outstanding Office Action by the number of months which will avoid abandonment under 37 C.F.R. §1.135. The fee under 37 C.F.R. § 1.17 should be charged to our Deposit Account No. 15-0700.

I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on December 17, 1996:

James A. Finder Name of Registered Representative

> Signature December 17, 1996 Date of Signature

Respectfully submitted.

James A. Finder

Registration No.: 30,173

OSTROLENK, FABER, GERB & SOFFEN, LLP

1180 Avenue of the Americas New York, New York 10036

Telephone: (212) 382-0700

TRAN\183189



Corres. and Mail

RESPONSE UNDER 37 CFR §1.116 EXPEDITED PROCEDURE **EXAMINING GROUP 2515**

P/214-33

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of

New York, New York

Dennis Fink

Date: December 17, 1996

Serial No.: 08/558,344

Group Art Unit: 2515

Filed: November 16, 1995

Examiner: J.B. Mullins

APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Assistant Commissioner of Patents and Trademarks 20231 Washington, D.C.

AMENDMENT PURSUANT TO 37 CFR § 1.116

Sir:

In response to the Office Action mailed September 17, 1996, please reconsider the above-identified application amended as follows:

IN THE CLAIMS:

Please cancel claims 16-20, 22-24 and 31-38 without prejudice.

Please amend the claims as follows:

(Twice Amended) [An amplifier programmer comprising:] The amplifier of claim 1, wherein the external programmer comprises:

an input/output port for sending and receiving control information;

a data input device for allowing input of programming information to the programmer; and

a controller for receiving the input programming information, generating programming signals from the input programming information and transmitting the programming signals through the input/output port to an amplifier for modifying at

AMDT\183098

10

least one of a signal processing function and a signal processing function parameter of the amplifier.

wherein the external programmer further comprises [further comprising] a display screen for displaying input programming information and information read by the controller.

// 9.

12. (Amended) The amplifier [programmer] of claim 10,
wherein the external programmer further comprises [further
comprising] a storage device for storing the input programming
information and previously selected control signals.

(Amended) The amplifier [programmer] of claim 10, wherein the data input device comprises a keypad having a plurality of keys.

g. 14. (Twice Amended) The amplifier [programmer] of claim 10, wherein the controller comprises a microprocessor for receiving programming information from at least one of the input device and a control circuit of the amplifier.

(Amended) The amplifier [programmer] of claim 10, wherein the controller comprises a connector for removably connecting the programmer to the amplifier.

(Amended) The amplifier of claim 1, wherein said external programmer is [taken from the group consisting of: a personal computer; a networked computer; and a hand held embedded computer controller] a standard computer.

(Amended) The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter [from the group consisting of:] for a crossover

function[; a volume control function; an equalizing function; a compression function; and a level threshold function].

(Amended) The amplifier of claim 1, wherein said digital signal processor receives and stores a combination of at least two signal processing functions [from the group consisting of: a crossover function; a volume control function; an equalizing function; a compression function; and a level threshold function].

The amplifier programmer of claim 10, wherein said programmer [is taken from the group consisting of: a personal computer; a networked computer; and a hand held embedded computer controller] a standard computer.

30. The amplifier programmer of claim 10, wherein said programmer stores in groups said at least one of a signal processing function and a signal processing function parameter according to [at least one of a] the time of day[,] during which said amplifier is to operate[, and a type of event, for which said amplifier is to operate].

Please add the following new claims:

The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for a volume control function.

24. 40. The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for an equalizing function.

25. The amplifier of claim 1, wherein said digital 41. signal processor receives and stores at least one of a signal

processing function and a signal processing function parameter for a compression function.

The amplifier of claim 1, wherein said digital signal processor receives and stores at least one of a signal processing function and a signal processing function parameter for a level threshold function.

and the

5

48. The amplifier programmer of claim 10, wherein said programmer stores in groups said at least one of a signal processing function and a signal processing function parameter according to the type of event for which said amplifier is to operate.--

REMARKS

Reconsideration and allowance of this application are respectfully requested. Claims 16-20, 22-24 and 31-38 have been canceled; claims 10-15, 25-27 and 29 have been amended; and claims 39-43 have been added.

Pursuant to 37 CFR §1.116(a), Applicant submits that the amendments made hereinabove merely cancel claims, adopt the Examiner's suggestions and remove issues for appeal and, therefore, the above amendments are proper and should be entered.

At page 2 of the Office Action, the Examiner objected to the specification under 35 U.S.C. § 112, first paragraph, for failing to provide an adequate written description of the invention. Consequently, the Examiner rejected claims 21-30 and 32-38 under 35 U.S.C. §112, first paragraph. Applicant has canceled claims 22-24 and 32-38 and, therefore the Examiner's rejection of those claims is moot. However, Applicant respectfully traverses the Examiner's §112 rejection of claims 21 and 25-30.

Support for the invention of claim 21 may be found at page 4 lines 19-25 of the originally filed specification which recites that "the present invention provides an amplifier and amplifier programmer capable of being removably connected to the

amplifier to quickly and easily change signal processing functions and/or parameters of the amplifier."

Support for amended claims 25 and 29 may be found at page 10, lines 9-13 of the originally filed specification which recite that "the amplifier circuitry can be programmed by either the portable programmer or a standard computer."

Support for amended claim 26 and new claims 39-42 may be found at page 1, line 26 through page 2, line 4 of the originally filed specification which recites that "various elements of the signal processing circuit define a plurality of sound processing parameters such as a frequency and an amplitude of a cross-over function, relative levels and routing in a mixer, response times, ratios and thresholds in a compressor and frequency, gain and bandwidth in an equalizer."

Support for amended claims 27, 28, 30 and new claim 43 and may be found at page 8, line 25 through page 9, line 4 of the originally filed specification which recites that "if a desired operation of a stereo sound system or public address system varies according to the time of day or the type of event being conducted, the signal processing parameters of an amplifier can be modified by selecting a preset group for that particular time of day or type of event. Thus, the user of the portable amplifier programmer only has to select a single group from a menu and the programmer will input that stored group to the control circuit of the amplifier."

Applicant submits that for the forgoing reasons claims 21, 25-30 and new claims 39-43 are supported by the specification as originally filed and, therefore, the Examiner's 35 U.S.C. §112 first paragraph, rejection of claims 21 and 25-30 should be withdrawn.

At page 2 of the Office Action, the Examiner rejected claims 25-27, 29, 30, 36 and 37 under 35 U.S.C. §112, second paragraph, as improperly reciting alternative structure. In response, Applicant has amended claims 25-27, 29, 30 and has added claims 39-43. Specifically, claims 39-42 have been added to recite individual processing functions previously recited as a

group in claim 26. Further, claim 43 has been added to recite that "the programmer stores in groups said at least one of a signal processing function and a signal processing function parameter according to the type of event for which said amplifier is to operate" as a separate claim from claim 30. Claims 36 and 37 have been canceled.

Applicant submits that for the forgoing reasons claims 25-27, 29, 30 and new claims 39-43 are definite and the Examiner's 35 U.S.C. §112, second paragraph, rejection of claims 25-27, 29 and 30 should be withdrawn.

At page 3 of the Office Action, the Examiner rejected claims 10-15, 29 and 30 under 35 U.S.C. §102(b) as being anticipated by either the Feistel, Barclay or Miyake references. Further, the Examiner rejected claims 10-20 and 29-38 under 35 U.S.C. §102(e) as being anticipated by Harris. In response, Applicant has amended claim 10 to depend from claim 1, an allowed claim. Claims 11-15, 29-30 and new claim 43 depend from claim 10 and, therefore, claims 10-15, 29-30 and new claim 43 should also be allowed for the reasons that claim 1 is allowed.

In light of the amendments made hereinabove, Applicant believes that the instant claims are in condition for allowance. The Examiner is invited to contact the undersigned to discuss any still outstanding matters. Early and favorable action is earnestly solicited.

I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on December 17, 1996

James A. Finder

Name of applicant, assignee or Registered Representative

Signature

December 17, 1996 Date of Signature Respectfully submitted,

James A. Finder

Registration No.: 30,173

OSTROLENK, FABER, GERB & SOFFEN, LLP. 1180 Avenue of the Americas

New York, New York 10036-8403 Telephone: (212) 382-0700

JAF/MBD



UNITED STATES DEPARTMENT OF COMMERCE Patent and Trademark Office

Address: COMMISSIONER OF PATENTS AND TRADEMARKS

Washington, O.C. 20231 ATTORNEY DOCKET NO FIRST NAMED APPLICANT FILING DATE APPLICATION NUMBER 08/558,344 11/16/95 FINK EXAMINER E5M1/0107 ART UNATULL I NESPET NUMBER OSTROLENK FABER GERB & SOFFEN 1180 AVENUE OF THE AMERICAS NEW YORK NY 10036-8403 DATE MAILE 3515 This is a communication from the examiner in charge of your application. COMMISSIONER OF PATENTS AND TRADEMARKS NOTICE OF ALLOWABILITY All claims being allowable, PROSECUTION ON THE MERITS IS (OR REMAINS) CLOSED in this application. If not included herewith (or previously mailed), a Notice of Allowance and Issue Fee Due or other appropriate communication will be mailed in due course This communication is responsive to are acceptable. Acknowledgement is made of a claim for foreign priority under 35 U.S.C. § 119(a)-(d). ☐ All ☐ Some* ☐ None of the CERTIFIED copies of the priority documents have been received in Application No. (Series Code/Serial Number) Treceived in this national stage application from the International Bureau (PCT Rule 17.2(a)). *Certified copies not received: Acknowledgement is made of a claim for domestic priority under 35 U.S.C. § 119(e). A SHORTENED STATUTORY PERIOD FOR RESPONSE to comply with the requirements noted below is set to EXPIRE **THREE MONTHS** FROM THE "DATE MAILED" of this Office action. Failure to timely comply will result in ABANDONMENT of this application. Extensions of time may be obtained under the provisions of 37 CFR 1.136(a). □ Note the attached EXAMINER'S AMENDMENT or NOTICE OF INFORMAL APPLICATION, PTO-152, which discloses that the oath or declaration is deficient. A SUBSTITUTE OATH OR DECLARATION IS REQUIRED. Applicant MUST submit NEW FORMAL DRAWINGS because the originally filed drawings were declared by applicant to be informal. $\hfill \square$ including changes required by the proposed drawing correction filed on by the examiner. including changes required by the attached Examiner's Amendment/Comment. Identifying indicia such as the application number (see 37 CFR 1.84(c)) should be written on the reverse side of the drawings. The drawings should be filed as a separate paper with a transmittal letter addressed to the Official Draftperson. ☐ Note the attached Examiner's comment regarding REQUIREMENT FOR THE DEPOSIT OF BIOLOGICAL MATERIAL. Any response to this letter should include, in the upper right hand corner, the APPLICATION NUMBER (SERIES CODE/SERIAL NUMBER). If applicant has received a Notice of Allowance and Issue Fee Due, the ISSUE BATCH NUMBER and DATE of the NOTICE OF ALLOWANCE should also be included. Attachment(s) Notice of References Cited, PTO-892 Information Disclosure Statement(s), PTO-1449, Paper No(s). Notice of Draftsperson's Patent Drawing Review, PTO-948

Examiner's Comment Regarding Requirement for Deposit of Biological Material ☐ Examiner's Statement of Reasons for Allowance

Notice of Informal Patent Application, PTO-152

☐ Interview Summary, PTO-413 Examiner's Amendment/Comment

GROUP ART UNIT 252

-2-

Serial Number: 08/558,344

Art Unit: 2515

Part III EXAMINER'S AMENDMENT

- 1. An Examiner's Amendment to the record appears below. Should the changes and/or additions be unacceptable to applicant, an amendment may be filed as provided by 37 C.F.R. § 1.312. To ensure consideration of such an amendment, it MUST be submitted no later than the payment of the Issue Fee.
- 2. The application has been amended as follows: In claim 10, line 11, "an" has been changed to --the-- in order to correct an obvious error.
- 3. Any inquiry concerning this communication or earlier communications from the examiner should be directed to Mr. James B. Mullins whose telephone number is (703) 308-4912.

JBM January 6, 1997 JAMES B. MULLINS
EXAMINER
GROUP ART UNIT 252 25 ()



UNITED STATES DEPARTMENT OF COMMERCE Patent and Trademark Office

Address: Box ISSUE FEE ASSISTANT COMMISSIONER FOR PATENTS WASHINGTON, D.C. 20231

NOTICE OF ALLOWANCE AND ISSUE FEE DUE

OSTROLENK FABER GERB & SOFFEN 1180 AVENUE OF THE AMERICAS NEW YORK MY 10036-8408

APPLICA	TION NO.	FÍLING DAT	E / T	OTAL CLAIMS	EXAM	NER AND GROUP ART UNI	т	DATE	MAILED
	08/558	344 11	/16/95	026	MULLINS	i, J	25	i.c.	01/07/
First Named Applicant	FINE			/ DEI	WIS				
TLE OF VENTION	APPARATI	IS AND ME	THOD FO	R PROGRAM	MMING AN A	MPLIFIER		7, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1,	•
	APPARATU	S AND ME	THOD/FO	R PROGRAM	MING AN A	MPLIFIER			•

THE APPLICATION IDENTIFIED ABOVE HAS BEEN EXAMINED AND IS ALLOWED FOR ISSUANCE AS A PATENT. PROSECUTION ON THE MERITS IS CLOSED.

THE ISSUE FEE MUST BE PAID WITHIN <u>THREE MONTHS</u> FROM THE MAILING DATE OF THIS NOTICE OR THIS APPLICATION SHALL BE REGARDED AS ABANDONED. THIS STATUTORY PERIOD CANNOT BE EXTENDED.

HOW TO RESPOND TO THIS NOTICE:

- I. Review the SMALL ENTITY status shown above. If the SMALL ENTITY is shown as yes, verify your current SMALL ENTITY status:
 - A. If the status is changed, pay twice the amount of the FEE DUE shown and notify the Patent and Trademark Office of the change in status, or
 - B. If the status is the same, pay the FEE DUE shown
- If the SMALL ENTITY is shown as NO:
- A. Pay FEE DUE shown above, or
- B. File verified statementof Small Entity Status before, or with, payment of 1/2 the FEE DUE shown above.
- II. Part B of this notice should be completed and returned to the Patent and Trademark Office (PTO) with your ISSUE FEE. Even if the ISSUE FEE has already been paid by charge to deposit account, Part B should be completed and returned. If you are charging the ISSUE FEE to your deposit account, section "6b" of Part B should be completed.
- III. All communications regarding this application must give application number and batch number. Please direct all communication prior to issuance to Box ISSUE FEE unless advised to the contrary.

IMPORTANT REMINDER: Patents issuing on applications filed on or after Dec. 12, 1980 may require payment of maintenance fees. It is patentee's responsibility to ensure timely payment of maintenance fees when due.

3. PATENT AND TRADEMARK OFFICE COPY

OFGS File No. P/214-33

UNITED STATES PATENT AND TRADEMARK OFFICE

application of:

Dennis Fink

Serial No.: 08/558,344

Filed: November 16, 1995

Notice of Allowance: 01/07/97

Date: March 11, 1997 Group Art Unit: 2515

Examiner: J. Mullins

Batch No.: I20

For: APPARATUS AND METHOD FOR PROGRAMMING AN AMPLIFIER

Hon. Commissioner of Patents and Trademarks Washington, DC 20231

Attention: Official Draftsman

FORMAL DRAWINGS

Sir:

Responsive to Paper No. 3 attached to the Office Action dated May 17, 1995, and referred to in the Notice of Allowance dated January 7, 1997, enclosed herewith please find one (1) sheet of formal drawings containing Figures 1-3 for the above-identified application.

It is respectfully requested that these drawings be substituted for the originally filed drawings.

I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Commissioner of Patents and Trademarks, Washington, D.C. 20231, on March 11, 1997:

James A. Finder ame of applicant, assignee or Registered Representative

> Signature March 11, 1997

> Date of Signature

fully submitted,

James A. Finder


Registration No.: 30,173

OSTROLENK, FABER, GERB & SOFFEN, LLP

1180 Avenue of the Americas New York, New York 10036-8403 Telephone: (212) 382-0700

JAF/MBD:kat Enclosure

AMDT\193433




Transaction History Date 1997-03-17
Date Information retrieved from USPTO Patent
Application Information Retrieval (PAIR)
system records at www.uspto.gov

PAR	T B—ISSUE F	EE TRANS	SMITTAL 2	7 - Ce	71.5cl >0/6		
#AILING INSTRUCTIONS: This form should be used for transmicluding the issue Fee Receipt, the Patent, advance orders and no y; (a) specifyinga new correspondence address in Block 3 below; of issue Fee or thereafter. See reverse for Certificate of Mailing, below.	otification of mainter r (b) providing the P	nance fees will	be mailed to autress	pleted where appropres entered in Block for maintenance te	1 unless you	direct otherwise,	
Inder the Paperwork Reduction Act of 1995, no persons are required to	respond to a collection	on of informatio	n unless it displays a va	ilid OMB control num	ber.		
3urden Hour Statement: This form is estimated to take 0.2 hours lepending on the needs of the individual case. Any comments on tomplete this form should be sent to the Chief Information Officer, F	he amount of time r	equired to	2. INVENTOR(S) ADDRESS CHANGE (Complete only, if there is a change) INVENTOR'S NAME				
Nashington, D.C. 20231.			Street Address				
O NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. Assistant Commissioner for Patents, Washington D.C. 20231	SEND TO: Box Issue	Fee,					
•			City, State and Zip Co	38	Y >	A	
1. CORRESPONDENCE ADDRESS		L/0107	CO-INVENTOR'S NAME				
OSTROLENK FABER GERB & 1180 AVENUE OF THE AME		/	Street Address				
NEW YORK NY 10036-8403	/ ,	City, State and Zip Co	do				
	·		City, State and 210 CO				
			☐ Check if additional	changes are enclosed			
APPLICATION NO. FILING DATE	TOTAL CLAIMS		EXAMINER AND GROU	IP ART UNIT	DAT	TE MAILED	
08/558,344 11/16/95	026	MULL	INS, J		2515	01/07/97	
First Named FINK,	DEN	NIS	-				
Applicant							
TITLE OF APPARATUS AND METHOD FO	IR PROGRAM	MING A	N AMPLIFIE	R			
ATTY'S DOCKET NO. CLASS-SUBCLASS B	ATCH NO. AP	PLN, TYPE	SMALL ENTITY	FEE DUE	T DA1	TE DUE	
							
2 P/214-33 330-06	5.000	(20 U	TILITY >	165 4 64	20.00 5,心	04/07/97	
3. Correspondence address change (Complete only if there is a change)		page, list to 3 registere OR, alterna having as a attorney or	g on the patent front the names of not more the d patent attorneys or agatively, the name of a fir a member a registered agent, If no name is lis fill be printed.	gents 2	K, FABER, GE	RB & SOFFEN; LLP	
5. ASSIGNMENT DATA TO BE PRINTED ON THE PATENT. (print or type)		L					
(1) NAME OF ASSIGNEE:			6a. The following fees ar	e enclosed: \$3/	,00_	1/2	
Crest Audio Inc. (2) ADDRESS: (CITY & STATE OR COUNTRY)			18sue Fee	Advance Order - # c	of Copies		
Paramus, New	Jersey		6b. The following fees a DEPOSIT ACCOUNT				
			(ENCLOSE A COP)				
A. This application is NOT assigned.			Issue Fee Any Deficiencies	Advance Order - # in Enclosed Fees	от серіез	-	
Assignment previously submitted to the Patent and Trademark Office.			The COMMISSIONER	F PATENTS AND TRAC	DEMARKS is		
Assignment is being submitted under separate cover. Assignment should be directed to Box ASSIGNMENTS.		<	requested to apply the	sue Fee to the applicati	on identified above	9.	
PLEASE NOTE: Unless an assignee is identified in Block 5, no assignee d Inclusion of assignee data is only appropriate when an assignment has be	ata will appear on the pa on perviously submitted	stent. to the	Barries A. F.	inder-RN:30	.173	3/12/97	
PTO or is being submitted under separate cover. Completion of this form is an assignment.			NOTE: The Issue Fee w	ill not be accepted from	anyone other than	the	
			in interest as shown by t	ttomey or agent; or the a the records of the Patent	and Trademark C	Mice.	
Note: If this cortificate of mailing is used it as he would be to		of Mailing	to cannot be used 4-	r any other sees-	nanvina naza	are	
Note: If this certificate of mailing is used, it can be used to trans Each additional paper, such as an assignment or formal drawin				any oner accom	panying pape		
I hereby certify that this correspondence is being deposited with	-		•	tage as first class	mail in		
an envelope addressed to: Box ISSUE FEE			810 BL 03/28/9				
Assistant Commissioner for P Washington D.C. 20331	BIENIS			45.00 CK		•	
on: March 12, 1997	(Data)		1 00%	30.00 CK			
James A. Finder	(Date) (Name of p	erson makir	ng deposit)				
	(Signature						
March 12, 1997	(Date)						

1. TRANSMIT THIS FORM WITH FEE

5B (REV. 05-96) Approved for use through 05/31/99. OMB 0651-0033

Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE



Transaction History Date 1997-07-29

Date Information retrieved from USPTO Patent
Application Information Retrieval (PAIR)
system records at www.uspto.gov

The United

States

of America PTO UTILITY GRANT
Paper Number

The Commissioner of Patents and Trademarks

Has received an application for a patent for a new and useful invention. The title and description of the invention are enclosed. The requirements of law have been complied with, and it has been determined that a patent on the invention shall be granted under the law.

Therefore, this

United States Patent

Grants to the person(s) having title to this patent the right to exclude others from making, using, offering for sale, or selling the invention throughout the United States of America or importing the invention into the United States of America for the term set forth below, subject to the payment of maintenance fees as provided by law.

If this application was filed prior to June 8, 1995, the term of this patent is the longer of seventeen years from the date of grant of this patent or twenty years from the earliest effective U.S. filing date of the application, subject to any statutory extension.

If this application was filed on or after June 8, 1995, the term of this patent is twenty years from the U.S. filing date, subject to an statutory extension. If the application contains a specific reference to an earlier filed application or applications under 35 U.S.C. 120, 121 or 365(c), the term of the patent is twenty years from the date on which the earliest application was filed, subject to any statutory extension.

Commissioner of Patents and Trademarks

Attest

Form PTO-1584 (Rev. 2/97)



Commissioner for Patents
United States Patent and Trademark Office
P.O. Box 1450
Alexandria, VA 22313-1450
www.usplo.gov

PAYOR NUMBER 2352

P75M

OSTROLENK FABER GERB & SOFFEN 1180 AVENUE OF THE AMERICAS NEW YORK NY 10036-8403 DATE PRINTED
02/02/09

MAINTENANCE FEE REMINDER

According to the records of the U.S. Patent and Trademark Office (USPTO) the maintenance fee for the patent(s) listed below (for which the above address is on record as the fee address under 37 CFR 1.363) has not been paid within the six-month period set forth in 37 CFR 1.362(d). THE MAINTENANCE FEE MAY STILL BE PAID WITH THE APPLICABLE SURCHARGE SET FORTH IN 37 CFR 1.20(h), WITHIN THE SIX-MONTH GRACE PERIOD SET FORTH IN 37 CFR 1.362(e).

Unless payment of the maintenance fee and the applicable surcharge is received in the USPTO within the six-month grace period, THE PATENT WILL EXPIRE AS OF THE END OF THE GRACE PERIOD. 35 U.S.C. 41(b).

The total payment due is the amount required on the date the fee is paid (and not necessarily the amount indicated below). All USPTO fees (including maintenance fees) are subject to change. Customers should refer to the USPTO Web site (www.uspto.gov) or call the Maintenance Fee Branch at 571-272-6500 for the most current fee amounts for the correct entity status before submitting payment. The total payment due indicated below is based on the entity status according to current Office records (shown below).

Timely payment of the total payment due is required in order to avoid expiration of the patent. A maintenance fee payment can be timely made using the certificate of mailing or transmission procedure set forth in 37 CFR 1.8.

•	U.S.	PATENT	APPL.	PAY-		TOTAL	ATTORNEY
PATENT FEE MAINT.	APPL	ISSUE	FILING	MENT	SMALL	PYMT	DOCKET
NUMBER AMT SURCHG	NUMBER	DATE	DATE	YEAR	ENTITY?	DUE	NUMBER
E6E2E11 1110 120	0855831.1.	07/20/07	11/16/04	1 1 2	NO	1,21,0	D/211-22

The maintenance fee and the applicable surcharge can be paid quickly and easily over the Internet at www.uspto.gov by electronic funds transfer (EFT), credit card, or USPTO deposit account payment methods. The mailing address for all maintenance fee payments not electronically submitted over the Internet is: U.S. Patent and Trademark Office, P.O. Box 979070, St. Louis, MO 63197-9000.

Direct any questions about this notice to: Mail Stop M Correspondence, Director of the United States Patent and Trademark Office, P.O. Box 1450, Alexandria, VA 22313-1450.

NOTE: This notice was automatically generated based on the amount of time that elapsed since the date a patent was granted. It is possible that the patent term may have ended or been shortened due to a terminal disclaimer that was filed in the application. Also, for any patent that issued from an application filed on or after June 8, 1995 containing a specific reference to an earlier filed application or applications under 35 U.S.C. 120, 121, or 365(c), the patent term ends 20 years from the date on which the earliest such application was filed, unless the term was adjusted or extended under 35 U.S.C. 154 or 156. Patentee should determine the relevant patent term for a patent before paying the maintenance fee.

MF4401 (7/2007)

Application or Docket Number PATENT APPLICATION FEE DETERMINATION RECORD Effective October 1, 1995 **CLAIMS AS FILED - PART I** OTHER THAN SMALL ENTITY **SMALL ENTITY** OR (Column 1) (Column 2) NUMBER FILED FOR NUMBER EXTRA RATE FEE BASIC FEE 375.00 750.00 OR TOTAL CLAIMS minus 20 = x\$11=x\$22= OR INDEPENDENT CLAIMS x39= minus 3 = x78= OR MULTIPLE DEPENDENT CLAIM PRESENT +125= +250= OR If the difference in column 1 is less than zero, enter "0" in column 2 TOTAL TOTAL OR **CLAIMS AS AMENDED - PART II** OTHER THAN OR SMALL ENTITY (Column 3) **SMALL ENTITY** CLAIMS HIGHEST ADDI-REMAINING PRESENT ADDI-NUMBER EXTR/ RATE TIONAL RATE TIONAL **AFTER PREVIOUSLY AMENDMENT** FEE FEE AMENDMENT PAID FOR Total Minus x\$11=x\$22= OR Independent Minus x39 =x78= OR FIRST PRESENTATION OF MULTIPLE DEPENDENT CLAYM +125= +250= OR TOTAL ADDIT, FEE OR ADDIT. FEE (Column 1) (Column 3) (Column 2) CLAIMS HIGHEST ADDI-REMAINING ADDI-NUMBER PRESENT RATE TIONAL RATE TIONAL AFTER **EXTRA** AMENDMENT **PREVIOUSLY** FEE FEE AMENDMENT PAID FOR Total Minus x\$11=OR x\$22= Independent Minus x39= OR x78= FIRST PRESENTATION OF MULTIPLE DEPENDENT CLAIM +125= +250= TOTAL ADDIT. FEE TOTAL OR ADDIT. FEE (Column 1) (Column 3) (Column 2) CLAIMS HIGHEST ADDI-ADDI-REMAINING NUMBER PRESENT TIONAL **AFTER** RATE RATE TIONAL ENT **EXTRA PREVIOUSLY** FEE FEE AMENDMENT PAID FOR AMENDM Total Minus x\$11=x\$22= Minus x39= x78= FIRST PRESENTATION OF MULTIPLE DEPENDENT CLAIM +125= OR +250= If the entry in column 1 is less than the entry in column 2, write "0" in column 3. TOTAL

If the "Highest Number Previously Paid For" IN THIS SPACE is less than 20, enter "20."

If the "Highest Number Previously Paid For" IN THIS SPACE is less than 3, enter "3."

ADDIT. FEE

OR


AI

The "Highest Number Previously Paid For" (Total or Independent) is the highest number found in the appropriate box in column 1. TOTA OR ADDIT. FEE

All the second s

FORM PTO-875 (Rev. 10/95) 10.

						D. 41		DEAC			pplication o	r Dock	et Number	
	PATENT	APPLIC		ctive Octo			ION	HECO	HE	'	A			
		CLA		S FILED -	PART		umn 2)			SMALL	ENTITY	OR	OTHEF SMALL	
FOR		1	NUMBE	R FILED	NUMBER EXTRA				RATE	FEE		RATE	FEE	
BASI	C FEE	1600									375.00	OR		750.00
TOTA	L CLAIMS			minu	s 20 =	*				x\$11=		OR	x\$22=	
INDE	PENDENT CLA	AIMS		mini	us 3 =	*				x39=		OR	x78=	
MUL.	TIPLE DEPEND	DENT CLA	IM PRE	SENT			-			+125=		OR	+250=	
* If th	e difference in co	olumn 1 is le	ss than :	zero, enter :"0"	n colum	n 2				TOTAL		OR	TOTAL	
		CLAIM (Colum		AMENDED		RT II olumn 2)	(Col	umn 3)		SMALL	ENTITY	OR		R THAN ENTITY
N. A.		CLAII REMAII AFTI AMEND	NING ER		NI PRE	GHEST JMBER VIOUSLY ID FOR		ESENT (TRA		RATE	ADDI- TIONAL FEE		RATE	ADDI- TIONAL FEE
AMENDMEN	Total	.3	7	Minus		10	=(7		x\$11=	187	OR	x\$22=	
MEN	Independent	*	4	Minus	***	3	=	/		x39=	39	OR	x78=	
¥	FIRST PRES	SENTATIO	ON OF	MULTIPLE	DEPE	NDENT CL	AIM			+125=	-01	OR	+250=	
		(Colum	n 1)		(C	olumn 2)	(Col	umn 3)	A	TOTAL DDIT. FEE	226	OR	TOTAL ADDIT. FEE	
ENT B	Ô	CLAII REMAII AFTI AMEND	NING ER		NI PRE	GHEST JMBER VIOUSLY ID FOR		SENT (TRA		RATE	ADDI- TIONAL FEE		RATE	ADDI- TIONAL FEE
AMENDMENT	Total	. 2	6	Minus	··· d	\$37	=			x\$11=		OR	x\$22=	
MEN	Independent	. 2	·	Minus .	***	4	-=			x39=		OR	x78=	
⋖	FIRST PRES	SENTATIO	ON OF	MULTIPLE	DEPE	NDENT CL	AIM			+125=		OR	+250=	
	•	(Colum	in 1)		IC.	olumn 2)	(Col	umn 3)	A	TOTAL DDIT. FEE		OR	TOTAL ADDIT. FEE	
ENTC		CLAII REMAII AFTE AMEND	MS NING ER		HI NI PRE	GHEST JMBER VIOUSLY	PRE	ESENT		RATE	ADDI- TIONAL FEĘ		RATE	ADDI- TIONAL FEE
AMENDMENT	Total	*		Minus	**		=			x\$11=		OR	x\$22=	
MEN	Independent			Minus	***		=			x39=		OR	x78=	
Ā	FIRST PRES	SENTATIO	ON OF	MULTIPLE	DEPE	NDENT CL	AIM			+125=		OR	+250=	
" " If I	he entry in colur he "Highest Nur	nhar Pravic	mely Dai	d Ear" IN THE	CDAC	E ic loce than	20 ani	er "20."	' !	TOTAL DDIT. FEE		OR	TOTAL ADDIT, FEE	
Th	he "Highest Nur e "Highest Num	nber Previou ber Previou	usly Pai Isly Paid	id For" IN THI I For" (Total or	S SPAC Indepe	E is less than ndent) is the t	3, ente ighest	r "3." number fo		-	priate box in			



THOMSON INNOVATION

Thomson Innovation Patent Export, 2013-10-24 08:37:10 -0500

Table of Contents

1. US5652544A Apparatus and method for programming an amplifier

Family 1/1

1 record(s) per family

Record 1/1 US5652544A Apparatus and method for programming an amplifier

Title: Apparatus and method for programming an amplifier

Title - DWPI: Amplifier with portable programmer receives input via keypad which is transmitted from programmer via microprocessor to signal processing controller which changes signal processing functions or function parameters

Priority Number: US1994337157A

Priority Date: 1994-11-09

Application Number: US1995558344A

Application Date: 1995-11-16

Publication Date: 1997-07-29

IPC Class Table:

IPC	Section	Class	Subclass	Class Group	Subgroup
H03G000300	Н	H03	H03G	H03G0003	H03G000300

IPC Class Table - DWPI:

IPC - DWPI	Section - DWPI	Class - DWPI	Subclass - DWPI	Class Group - DWPI	Subgroup - DWPI
H03F000100	Н	H03	H03F	H03F0001	H03F000100

Assignee/Applicant: Crest Audio Inc., Paramus, NJ, US

JP F Terms: JP FI Codes:

Assignee - Original: Crest Audio Inc.

Any CPC Table:

Туре	Invention	Additional	Version	Office
Current	H03G 3/00	-	20130101	EP

ECLA: H03G000300

Abstract:

An apparatus and method for programming an amplifier includes an amplifier and a portable programmer that is removably connectable to the amplifier. The portable programmer includes a microprocessor, a keypad, and a display screen. The amplifier includes a programming input port, a signal processing circuit, a power amplifier and a control circuit. When the portable programmer is connected to the amplifier, information relating to parameter of various signal processing circuit elements can be read and modified through the programmer. The information input via the keypad and displayed on the display screen is transmitted from the programmer via the microprocessor to the signal processing control circuit to change signal processing functions and/or signal process function parameters of at least one of the signal processing circuit elements. As a result, processing of a signal transmitted through the amplifier is changed so that a sound produced by the signal can be modified. The signal processing circuit elements remain programmed when the programmer is removed and/or power is disconnected.

Language of Publication: EN INPADOC Legal Status Table:

Gazette Date	Code	INPADOC Legal Status Impact						
2009-02-02	REMI	-						
Description: MAINTENANCE FEE REMINDER MAILED								
2009-01-23	FPAY	+						
Description: FEE PAYMENT								
2004-11-26	FPAY	+						
Description: FEE PAYMENT								
2001-01-04								
Description: FEE PAYMENT								

Post-Issuance (US):

Reassignment (US) Table:

Maintenance Status (US):

Litigation (US): 2013-09-27 2013 Crest Audio, Inc. QSC Audio Products, LLC S.D. Missouri


3:13cv00610

Opposition (EP):

License (EP):

EPO Procedural Status:

Front Page Drawing:





Copyright 2007-2013 THOMSON REUTERS

USPTO Maintenance Report

Patent Bibliographic Data			10/24/2013 09:46 AM			
Patent Number:	5652544		Application Number:	08558344		
Issue Date:	07/29/1997		Filing Date:	11/16/1995		
Title:	APPARATUS	AND METHOD	FOR PROGRA	MMING AN A	MPLIFIER	
Status:	4th, 8th and 12th	th year fees paid		Entity:	LARGE	
Window Opens:	N/A	Surcharge Date:	N/A	Expiration:	N/A	
Fee Amt Due:	Window not open	Surchg Amt Due:	_		Window not open	
Fee Code:						
Surcharge Fee Code:						
Most recent events (up to 7):	02/02/2009 01/23/2009 11/26/2004 01/08/2001 01/04/2001	Payment of M Payment of M Payor Number Payment of M	Tee Reminder Ma aintenance Fee, 1 aintenance Fee, 8 Assigned. aintenance Fee, 4 ntenance History	12th Year, Larg 8th Year, Large 4th Year, Large	Entity.	
Address for fee purposes:	OSTROLENK 1180 AVENUE NEW YORK N	E OF THE AME	RICAS			